

Jayron RL-HM202A

Jayron 9,999 Days Digital Countdown Timer Instruction Manual

MODEL: RL-HM202A

Brand: Jayron

Introduction

This manual provides detailed instructions for the setup, operation, and maintenance of your Jayron 9,999 Days Digital Countdown Timer. This device is designed for precise time tracking, offering both countdown and stopwatch functionalities for various events.

Key Features:

- Large, clear digital display for days, hours, minutes, and seconds.
- Countdown range: 0-9999 days, 23 hours, 59 minutes, 59 seconds.
- Integrated stopwatch function.
- Loud alarm for countdown completion.
- Magnetic adsorption for convenient placement.
- Battery operated with replaceable CR2032 batteries.

Setup

Before using your timer, please follow these steps for initial setup.

1. Battery Installation

The timer requires two CR2032 lithium metal batteries (included). To install or replace batteries:

1. Locate the battery compartment on the back of the timer.
2. Open the battery compartment cover.

3. Insert two CR2032 batteries, ensuring correct polarity (+/-).
4. Close the battery compartment cover securely.

2. Initial Placement

The timer features magnetic adsorption on its back for easy placement on metallic surfaces like refrigerators. Ensure the surface is clean and dry before attaching. It is recommended to press it firmly to ensure secure attachment.



Image: Back of the timer with battery compartment and magnetic pads. This view highlights the location for battery installation and the magnetic features for mounting.

Operating Instructions

The timer features four buttons on the back: ▲ (Up), ▼ (Down), SET, and S/S (Start/Stop).

1. Setting the Countdown Timer

The timer can be set for up to 9,999 days, 23 hours, 59 minutes, and 59 seconds.

1. Press the **SET** button to enter setting mode. The display will flash.
2. Use the ▲ (Up) and ▼ (Down) buttons to adjust the desired value for days, hours, minutes, and

seconds.

3. Press **SET** again to move to the next time unit (Days → Hours → Minutes → Seconds).
4. Once all values are set, press **SET** one last time to confirm and exit setting mode.
5. Press the **S/S** button to start the countdown.
6. When the countdown reaches zero, the buzzer will sound for 1 minute.



Image: Front display of the timer, showing the separate windows for days, hours, minutes, and seconds.

2. Stopwatch Function (Count-up)

In addition to countdown, the device can function as a stopwatch.

1. Ensure the timer is not in countdown mode (display shows 0000 00 00 00).
2. Press the **S/S** button to start the stopwatch. The timer will begin counting up from 0000 00 00 00.
3. Press **S/S** again to pause the stopwatch.
4. Press **S/S** again to resume.
5. To reset the stopwatch, press and hold the **S/S** button while it is paused.

COUNTDOWN / COUNT UP



Image: This illustration demonstrates the visual difference between the count-up and count-down modes on the timer's display.

3. Power On/Off

To conserve battery life, the timer can be shut down.

- To shut down: Press and hold the power button (usually the **S/S** button or a dedicated power symbol button if present) until the display turns off.
- To turn on: Press any button. The timer will resume from its last set interface or countdown state.

Your browser does not support the video tag.

Video: This video demonstrates the setting and countdown functionality of the Jayron 9,999 Days Digital Countdown Timer, including button presses and display changes.

Maintenance

1. Battery Replacement

When the display dims or the timer functions erratically, it is time to replace the batteries. Refer to the "Battery Installation" section under Setup for detailed steps.

2. Cleaning

To clean the timer, wipe it with a soft, dry cloth. Do not use abrasive cleaners or immerse the device in water.

Troubleshooting

- **Display shows "Err":** This typically occurs if the number of days set exceeds 9999 days, or if the end date is set to be earlier than the start date. Please re-enter your desired countdown period within the valid range.
- **Timer not responding:** Check battery installation and ensure batteries are not depleted. Replace if necessary.
- **Alarm not sounding:** Ensure the timer is not in silent mode (if applicable, refer to specific model features) and that the countdown has completed.
- **Magnet not holding securely:** Ensure the metallic surface is clean and flat. Press firmly to engage the magnets.

Specifications

Brand	Jayron
Model Number	RL-HM202A
Material	Plastic
Item Weight	2.56 ounces
Product Dimensions	4.3 x 1.9 x 0.53 inches
Power Source	2 x CR2032 Lithium Metal batteries (included)
Maximum Countdown	9,999 Days, 23 Hours, 59 Minutes, 59 Seconds
Certifications	CE, ROHS



Image: Dimensional diagram of the timer, illustrating its physical measurements.

Warranty and Support

This product is manufactured to high-quality standards and is CE and ROHS certified. For any questions or assistance with your Jayron countdown timer, please contact customer support through your purchase platform. We are committed to providing satisfactory service.