

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Ajazz](#) /

› [Lomiluskr K680T Mechanical Keyboard User Manual](#)

Ajazz K680T

Lomiluskr K680T Mechanical Keyboard User Manual

Model: K680T | Brand: Ajazz

1. INTRODUCTION

This manual provides detailed instructions for the setup, operation, maintenance, and troubleshooting of your Lomiluskr K680T Wireless 60% Mechanical Keyboard. Please read this manual thoroughly before using the product to ensure optimal performance and longevity.



Image: The Lomiluskr K680T Mechanical Keyboard, featuring a compact 60% layout with white backlighting and brown switches.

2. PRODUCT OVERVIEW AND FEATURES

The Lomiluskr K680T is an ultra-compact 60% mechanical keyboard designed for versatility and performance.

It offers both Bluetooth wireless and wired connectivity, making it suitable for various devices and environments.

- **68-Key Mini and Compact Layout:** Optimized for space-saving while retaining essential keys for gaming and daily use. Dimensions: 13.4 x 4.25 x 1.4 inches.
- **Bluetooth Wireless/Wired Dual Mode:** Seamlessly switch between Bluetooth 3.0 wireless connection (up to 10 meters) and wired USB-C mode. The wired mode also charges the keyboard.
- **Multi-Device Connection:** Connects up to 3 devices simultaneously via Bluetooth, easily switchable with FN+Q/W/E.
- **1000mAh Built-in Large Capacity Battery:** Provides extended usage time, approximately 10 hours with backlight on, and up to 60 hours with backlight off. Standby time is up to 360 hours with 3 hours fast charging time.
- **18 Light Effects:** Features a white backlight with 18 customizable lighting modes (flashing, static, breathing, etc.). Brightness and speed are adjustable.
- **Professional Mechanical Switches:** Equipped with brown mechanical switches for a balanced typing and gaming experience, offering a lightweight, weak tactile, and audible feedback. Designed for over 50 million clicks.
- **N-Key Rollover:** In wired mode, all keys are registered simultaneously, preventing ghosting during intense use.




N-Key Rollover
全キー無衝突



Wired/Bluetooth
有線/bluetooth



White Backlit
あつさりした白い光



Compact 68 Keys
シンプル68ボタン



Double-Shot
Injection Keycap
二色射出成形

Image: An overview of the keyboard's key features, including N-Key Rollover, Wired/Bluetooth connectivity, White Backlight, Compact 68 Keys, and Double-Shot Injection Keycaps.



Image: Close-up of a brown mechanical switch and icons indicating compatibility with Android, Windows, iOS, mobile phones, PCs, tablets, and dual-mode Bluetooth/Wired connection.

3. SETUP GUIDE

3.1 Wired Mode Setup

To use the keyboard in wired mode, simply connect the provided USB-C cable from the keyboard to an available USB port on your computer or device. The keyboard will be automatically recognized and will begin charging.

3.2 Bluetooth Mode Setup

The K680T keyboard supports connecting up to three Bluetooth devices. Follow these steps to pair your keyboard:

- Step 1:** Locate the switch on the bottom of the keyboard and dial it to the "BT" position.
- Step 2:** Select a device slot by pressing **FN + Q** (Device 1, indicator light red), **FN + W** (Device 2, indicator

light green), or **FN + E** (Device 3, indicator light blue). This product can memorize 3 devices, stored in Q/W/E buttons.

3. **Step 3:** Press and hold **FN + P** for 2 seconds. Release the keys when the indicator light flashes, indicating the keyboard is in pairing mode.
4. **Step 4:** On your device (computer, tablet, smartphone), turn on its Bluetooth function and search for available devices.
5. **Step 5:** Find the device named "AJAZZ K680T Keyboard" in the list and click "Connect" to complete the pairing process.

Bluetooth/Wired Dual-Mode Bluetooth/有線 両対応

Bluetooth connection and USB wired connection, dual-mode connection supports multi-devices, easier to switch.

キーボードはBluetooth接続とUSBケーブル接続をサポートしています。デュアルモード接続方式は様々な設備の使用をサポートしています。設備のシームレスな切り替えに便利です。

Bluetooth Mode/bluetoothモード

Wireless Bluetooth 3.0 stable transmission,
10 m effective transmission distance

有効距離10 m、線材の束縛を抜け出して、
仕事が便利であります。



USB Wired Mode/有線モード

Type-C interface, usb while charging,
Transmission is more stable

USBケーブルは分離でき、伝送は安定的で効率的で、ゲームをより快適にします。



Image: Visual representation of the keyboard's Bluetooth and wired connectivity options, highlighting the 10m transmission distance for Bluetooth and USB-C for wired use and charging.

Bluetooth Connection Method

Bluetooth接続方法

Dial the bottom button to the "BT" position

下のボタンを「BT」の位置にダイヤルします



Step1

FN+Q

Device 1
設備1

FN+W

Device 2
設備2

FN+E

Device 3
設備3

Switch to this device,
the indicator light is red

設備を切り替え
対応ランプが赤色に点灯します

Switch to this device,
the indicator light is green

設備を切り替え
対応ランプがグリーンに点灯します

Switch to this device,
the indicator light is blue

設備を切り替え
対応ランプがブルーに点灯します

Step2

Press Fn and one of Q/W/E as the storage key and then release the key.
(This product can memorize 3 devices, stored in Q/W/E buttons)

Fn+Q/W/ Eのいずれかを保存キーとして押してからキーを離します。
(この製品は3つの端末装置を記憶して、それぞれQ/W/Eの3つのキーに保存します。)

Step3

Press the FN+P button for 2 seconds, release it to enter the pairing state after the indicator flashes.

FN+Pキー2sを長押しし、指示灯が点滅してから離して接続状態にします。

Step4

Turn on the device's Bluetooth function and search.

設備のbluetooth機能を開いて検索し。

Step5

Find the device named "AJAZZ K680T Keyboard" and click Connect to complete the connection.

「AJAZZ K680T Keyboard」という機器が接続をクリックすると接続が完了します。

Image: Step-by-step guide for Bluetooth connection, showing the FN key combinations for device selection and pairing.

4. OPERATING INSTRUCTIONS

4.1 Key Functions and Combinations

The K680T keyboard utilizes an 'Fn' (Function) key to access secondary functions of certain keys. This allows for a compact layout while retaining full functionality.

- Switching Bluetooth Devices:** Press **FN + Q**, **FN + W**, or **FN + E** to switch between the three paired Bluetooth devices.
- Backlight Control:** Use **FN + →** (Right Arrow) to cycle through 18 different backlight effects. Use **FN + ←** (Left Arrow) to cycle backward.

- **Adjusting Backlight Brightness:** Press **FN + ↑** (Up Arrow) to increase backlight brightness and **FN + ↓** (Down Arrow) to decrease brightness.
- **F-Keys (F1-F12):** The F-keys are typically accessed by holding the **Fn** key and pressing the corresponding number key (e.g., **Fn + 1** for F1).

Up to 3 devices, Easy to Switch

3台の機器に対応し、ワンタッチで切り替える

Compatible with a variety of devices, can store three Bluetooth device connections, use Fn+QWE directly to switch to the corresponding device when you use it again, no need to connect again.

複数の機器に対応しており、3つのbluetooth機器接続が格納されている。
再利用はFn+Q/W/Eを直接使用して対応機器に切り替えることで利用可能であり、
再接続操作は不要であります。



Image: Illustration showing the keyboard connecting to and switching between a tablet, smartphone, and laptop, emphasizing the ease of switching between up to 3 devices.

5. MAINTENANCE

To ensure the longevity and optimal performance of your Lomiluskr K680T keyboard, follow these maintenance guidelines:

- **Cleaning:** Regularly clean the keyboard with a soft, dry cloth. For deeper cleaning, use compressed air to remove dust and debris from between the keycaps. You may carefully remove keycaps for thorough cleaning, but ensure to reattach them correctly.
- **Avoid Liquids:** Keep liquids away from the keyboard to prevent damage to the internal electronics. In case of spills, immediately disconnect the keyboard and allow it to dry completely before reconnecting.
- **Battery Care:** To prolong battery life, avoid fully discharging the keyboard frequently. Charge the keyboard

when the battery indicator is low. Store the keyboard in a cool, dry place when not in use for extended periods.

- **Storage:** Store the keyboard in a clean, dust-free environment. Avoid exposing it to extreme temperatures or direct sunlight.

6. TROUBLESHOOTING

If you encounter issues with your Lomiluskr K680T keyboard, please refer to the following common problems and solutions:

6.1 Bluetooth Connectivity Issues

- **Keyboard not pairing:** Ensure the switch on the bottom of the keyboard is set to "BT". Confirm the keyboard is in pairing mode (FN+P held for 2 seconds until indicator flashes). Make sure your device's Bluetooth is enabled and within the 10-meter range. Try restarting both the keyboard and your device.
- **Intermittent connection or repeated key presses:** This can sometimes occur with Bluetooth connections. Try re-pairing the keyboard with your device. Ensure there are no strong interferences (e.g., other wireless devices) nearby. If the issue persists, try using the keyboard in wired mode.

6.2 Key Input Problems

- **Keys not responding:** Ensure the keyboard is properly connected (either via Bluetooth or wired). Check the battery level if in Bluetooth mode. If in wired mode, ensure the USB-C cable is securely connected.
- **F-keys (F1-F12) not working as expected:** Remember that F-keys require the **Fn** key to be held down simultaneously (e.g., Fn + 1 for F1). Some devices or operating systems might require specific driver installations or settings adjustments for full compatibility with compact keyboards.

6.3 Backlight Issues

- **Backlight not turning on:** Ensure the keyboard has sufficient battery charge. Try adjusting the brightness using **FN + ↑** (Up Arrow).
- **Backlight not changing effects:** Cycle through effects using **FN + →** (Right Arrow).

7. SPECIFICATIONS

Feature	Specification
Model Number	K680T
Brand	Ajazz
Connectivity Technology	Bluetooth 3.0 & Wired (USB-C)
Keyboard Layout	60% (68 Keys)
Switch Type	Brown Mechanical Switches
Backlight	White Backlight, 18 Effects
Battery Capacity	1000mAh Lithium Ion
Battery Life (approx.)	10 hours (backlight on), 60 hours (backlight off)

Feature	Specification
Standby Time	360 hours
Charging Time	3 hours (fast charging)
Product Dimensions	13.39 x 4.25 x 1.39 inches (34.01 x 10.80 x 3.53 cm)
Item Weight	1.87 pounds (0.85 kg)
Compatible Devices	Mac, PC, Laptop, Tablet, Smartphone, PS
Manufacturer	Lomiluskr

68 Key Compact Layout 68キー コンパクトレイアウト

K680t retains the keys commonly used in games, and it will give you more space for right mouse activity.

ゲームで一般的に使用されるキーを保持します、そしてそれはあなたに右マウスの活動のためのより多くのスペースを与えるでしょう。



Mini size is 34x10.8x3.5cm(13.4x4.25x1.4 inch), which simplifies the layout, takes into account the practicability, supports the lock of Win key, and is quick to operate.

ミニサイズは34x11x3.5cm(13.4x4.25x1.4 inch)で、レイアウトを簡素化し、実用性を考慮し、Winキーのロックをサポートし、操作が簡単です。

Image: Diagram illustrating the compact 68-key layout and dimensions of the K680T keyboard, highlighting its space-saving design.

Long Battery Life

恒久航続

With 1000mAh battery, which can allow you to use at least 10 hours, turn off the backlight to use 60 hours, 360 hours of standby time, 3 hours of fast charging time.

1000 mAhのリチウム電池を搭載しており、あなたは少なくとも10時間を使うことができます、バックライトをオフして60時間連続使用し、360時間待機することができます、3時間の急速充電時間。



Image: Graphic illustrating the 1000mAh battery capacity and its long battery life, with a visual of the keyboard and a pen holder with colored pencils.

8. WARRANTY AND SUPPORT

For warranty information and customer support, please refer to the documentation included with your product packaging or contact the manufacturer, Lomiluskr, or the brand, Ajazz, directly through their official channels. Keep your purchase receipt as proof of purchase for any warranty claims.

For further assistance, you may also visit the [Ajazz Store on Amazon](#).