

[manuals.plus](#) /

› [Arteck](#) /

› [Arteck HB030B Universal Slim Portable Wireless Bluetooth Keyboard User Manual](#)

Arteck HB030B

Arteck HB030B Universal Slim Portable Wireless Bluetooth Keyboard User Manual

Model: HB030B

1. INTRODUCTION

Thank you for choosing the Arteck HB030B Universal Slim Portable Wireless Bluetooth Keyboard. This keyboard is designed for broad compatibility across various operating systems, offering a comfortable typing experience with its backlit keys and portable design. This manual will guide you through the setup, operation, maintenance, and troubleshooting of your new keyboard.



Figure 1: Arteck HB030B Bluetooth Keyboard showcasing its slim design and vibrant 7-color backlighting options.

2. PACKAGE CONTENTS

Please verify that all items are present in your package:

- Arteck Backlit Bluetooth Keyboard
- USB Charging Cable
- Welcome Guide (this manual)

3. SETUP

3.1 Charging the Keyboard

Before initial use, fully charge the keyboard. Connect the provided USB charging cable to the keyboard's charging port and to a USB power source (e.g., computer USB port, USB wall adapter). The 'Charge' indicator light will illuminate during charging and turn off when fully charged.



Figure 2: Close-up view of the keyboard's indicator lights, including the 'Charge' light, which indicates charging status.

3.2 Bluetooth Pairing

The Arteck HB030B keyboard supports Bluetooth connectivity with iOS, Android, Mac OS, and Windows devices.

1. Ensure the keyboard is charged and the 'OFF/ON' switch (located on the top right) is in the 'ON' position. The 'Power' indicator light will turn on.
2. Press the 'Connect' button (next to the OFF/ON switch). The 'Status' indicator light will start blinking, indicating the keyboard is in pairing mode.
3. On your device (tablet, smartphone, computer), go to Bluetooth settings.
4. Search for available Bluetooth devices. You should see "Arteck HB030B" or a similar name appear in the list.
5. Select the keyboard from the list. Your device may prompt you to enter a pairing code displayed on the screen. Type this code on the Arteck keyboard and press Enter.
6. Once paired, the 'Status' indicator light on the keyboard will stop blinking and remain solid for a few seconds, then turn off. The keyboard is now connected and ready for use.



Figure 3: The keyboard is compatible with major operating systems including iOS, Android, and Windows, making it versatile for various devices.

4. OPERATING INSTRUCTIONS

4.1 Backlight Control

The keyboard features 7 unique LED backlight colors and 2 brightness levels.

- **To adjust brightness:** Press **Fn + Light Bulb icon** (usually F11 or F12) to cycle through 2 brightness levels.
- **To change backlight color:** Press **Fn + Light Bulb icon + Page Up or Page Down** to cycle through the 7 available colors.

The backlight has an auto-sleep feature to conserve battery life.

Light · Slim · Portable



Figure 4: Illustration of how to use the Fn key in combination with the light bulb icon and Page Up/Down keys to control backlight brightness and color.

4.2 Function Keys

The top row of keys (F1-F12) serves dual purposes. By default, they may act as standard function keys. To access their special functions (e.g., media controls, volume, search), press and hold the **Fn** key simultaneously with the desired function key.

4.3 Operating System Specific Keys

The keyboard includes keys optimized for different operating systems:

- **iOS/Mac:** Look for keys with Apple-specific icons (e.g., Command, Option).
- **Android:** Keys may have Android-specific functions.
- **Windows:** Standard Windows keys (e.g., Win key, Alt).

The keyboard automatically adapts to the connected operating system for optimal key mapping.

5. MAINTENANCE

5.1 Battery Life and Charging

The keyboard features a rechargeable lithium battery designed to last up to 6 months between charges with backlight off (based on 2 hours non-stop use per day). When the battery is low, the 'Charge' indicator light may blink or turn red. Recharge the keyboard as described in Section 3.1.

5.2 Cleaning

To clean the keyboard, gently wipe the surface with a soft, damp cloth. Do not use harsh chemicals or abrasive cleaners. Avoid getting moisture into the keyboard's ports or between the keys.

6. TROUBLESHOOTING

If you encounter issues with your Arteck HB030B keyboard, please refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Keyboard does not connect via Bluetooth.	Keyboard is off, not in pairing mode, or device's Bluetooth is off.	Ensure keyboard is ON and 'Connect' button is pressed. Verify Bluetooth is enabled on your device and try re-pairing.
Frequent Bluetooth connection drops.	Low battery, interference, or device issue.	Fully charge the keyboard. Move closer to your device. Try re-pairing or restarting both keyboard and device.
Keys are not responding or typing errors occur (e.g., repeated characters).	Low battery or software glitch.	Charge the keyboard fully. Restart the keyboard and your device. If issues persist, try connecting to another device to isolate the problem.
Backlight does not work or only shows limited colors.	Backlight is off, low battery, or a specific setting.	Ensure backlight is turned on (Fn + Light Bulb icon). Charge the keyboard. Refer to Section 4.1 for backlight control.
Keyboard is not "plug and play".	This is a Bluetooth keyboard, not a wired or USB dongle keyboard.	The keyboard requires Bluetooth pairing as described in Section 3.2. It is not designed for direct plug-and-play via USB for data transfer.

7. SPECIFICATIONS

Feature	Detail
Model	HB030B
Connectivity Technology	Bluetooth 3.0
Compatible Devices	iOS, Android, Mac OS, Windows (Tablets, Smartphones, PCs)
Backlight Colors	7 Unique LED colors
Brightness Levels	2
Battery Type	Rechargeable Lithium Battery
Estimated Battery Life	Up to 6 months (backlight off, 2 hours/day use)
Product Dimensions	9.72 x 5.91 x 0.24 inches (247 x 150 x 6 mm)
Item Weight	10.5 ounces (0.37 lbs)

Feature	Detail
Keyboard Layout	US
Color	Black



Figure 5: Visual representation of the keyboard's ultra-slim and light design, highlighting its compact dimensions and weight.

8. WARRANTY AND SUPPORT

Your Arteck HB030B keyboard comes with a **24-month warranty** from the date of purchase. This warranty covers manufacturing defects and ensures friendly customer service.

For technical support, warranty claims, or any inquiries, please refer to the contact information provided in your welcome guide or visit the official Arteck support website. Please have your model number (HB030B) and purchase details ready when contacting support.