Arcchio 9626133

Arcchio Tadej Pendant Lamp - Instruction Manual

Model: 9626133

1. Introduction

The Arcchio Tadej pendant lamp features a modern, minimalist design with funnel-shaped metal shades that direct light downwards. This lamp is designed to provide beautiful and functional lighting for various indoor settings, such as living rooms and dining rooms. This manual provides essential information for the safe installation, operation, and maintenance of your new pendant lamp.

Please read these instructions carefully before installation and retain them for future reference. Incorrect installation or use can lead to hazards.



Image 1.1: The Arcchio Tadej pendant lamp installed in a dining room setting.

2. Safety Instructions

- **Electrical Safety:** Installation must be performed by a qualified electrician in accordance with local wiring regulations.
- **Power Disconnection:** Always disconnect the main power supply before installation, maintenance, or bulb replacement.
- **Voltage:** Ensure the supply voltage matches the lamp's operating voltage (230V).
- **Bulb Type:** Use only E27 bulbs with a maximum wattage of 40W per bulb. Do not exceed the specified wattage.
- **Indoor Use Only:** This lamp is designed for indoor use (IP20 protection class). Do not expose to moisture or extreme temperatures.
- **Handling:** Handle the lamp components with care to avoid damage.
- **Cleaning:** Use a soft, dry cloth for cleaning. Do not use abrasive cleaners or solvents.

3. Package Contents

Carefully unpack the product and ensure all components are present and undamaged. If any parts are missing or damaged, contact your retailer immediately.

- 1x Ceiling bar with integrated wiring
- 1x Mounting bracket
- 4x Pendant lamp shades with cables
- Mounting hardware (screws, wall plugs)
- Instruction manual



Image 3.1: Overview of the Arcchio Tadej pendant lamp components.

4. Installation Guide

Follow these steps for proper installation. It is recommended that two people perform the installation due to the size and weight of the fixture.

4.1 Mounting the Ceiling Bar

1. **Disconnect Power:** Turn off the main power supply at the circuit breaker before starting any electrical work.
2. **Positioning:** Mark the desired position for the lamp on the ceiling.
3. **Attach Mounting Bracket:** Hold the mounting bracket against the ceiling at the marked position and mark the drilling points. Drill holes and insert appropriate wall plugs. Secure the mounting bracket to the ceiling using the provided screws.

4. **Electrical Connection:** Connect the household electrical wires to the terminal block inside the ceiling bar. Ensure correct polarity (Live, Neutral, Earth).
5. **Secure Ceiling Bar:** Carefully lift the ceiling bar and align it with the mounting bracket. Secure the ceiling bar to the bracket using the provided screws.



Image 4.1: Detail of the ceiling mount.

4.2 Attaching and Adjusting Pendant Shades

1. **Insert Bulbs:** Screw E27 bulbs (max 40W each) into the lamp holders of each pendant shade.
2. **Adjust Cable Length:** The length of each pendant cable can be adjusted. Loosen the cable grip at the top of each pendant and pull the cable through to achieve the desired hanging height. Tighten the cable grip securely once adjusted. The maximum adjustable length is 1500mm.
3. **Secure Pendants:** Ensure each pendant is securely attached to the ceiling bar's internal wiring.



Image 4.2: Detail of the pendant cable adjustment mechanism.

5. Operation

Once installed, the Arcchio Tadej pendant lamp operates like any standard lighting fixture. Restore power at the circuit breaker. The lamp can be switched on and off using a standard wall switch connected to the circuit.



Image 5.1: The Arcchio Tadej pendant lamp illuminated.

6. Maintenance

- **Cleaning:** To clean the lamp, ensure the power is off. Use a soft, dry, lint-free cloth to wipe the metal surfaces. Do not use water, chemical cleaners, or abrasive materials, as these can damage the finish.
- **Bulb Replacement:** Disconnect power before replacing bulbs. Allow old bulbs to cool completely before removal. Replace with E27 bulbs, ensuring they do not exceed 40W.
- **Inspection:** Periodically check the lamp for any signs of wear or damage to the cables or connections. If any issues are found, consult a qualified electrician.

7. Troubleshooting

- **Lamp does not light up:**
  - Check if the power supply is connected and switched on.

- Ensure bulbs are correctly screwed in and not faulty.
- Verify the circuit breaker has not tripped.

- **Flickering light:**
  - Ensure bulbs are fully tightened.
  - Replace bulbs to check if they are faulty.
  - Consult an electrician if the issue persists, as it may indicate a wiring problem.

8. Product Specifications

Feature	Specification
Brand	Arcchio
Model Number	9626133
Material	Metal
Color	Black, White
Dimensions (Product)	112 x 19 x 28 cm (Length x Width x Height)
Weight	2.73 kg
Number of Lights	4
Lamp Holder	E27
Max Wattage per Bulb	40 W
Operating Voltage	230 V
Protection Class	I
IP Rating	IP20 (Indoor use)
Style	Modern
Max Pendant Height	1500 mm
Shade Diameter	190 mm



Image 8.1: Dimensional drawing of the pendant lamp.

9. Warranty and Support

Arcchio products are manufactured to high-quality standards. For warranty information, please refer to the terms and

conditions provided by your retailer at the time of purchase. If you have any questions, require technical assistance, or need to report a defect, please contact your point of purchase or the manufacturer directly.

Please have your model number (9626133) and proof of purchase ready when contacting support.

© 2023 Arcchio. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question