Arcchio 9928035

Arcchio LED Ceiling Light 'Rotari' (Model 9928035) Instruction Manual

Comprehensive guide for installation, operation, and maintenance.

1. Introduction

Thank you for choosing the Arcchio LED Ceiling Light 'Rotari'. This manual provides essential information for the safe and efficient installation, operation, and maintenance of your new lighting fixture. Please read these instructions carefully before beginning installation and retain them for future reference.



Image 1.1: Front view of the Arcchio Rotari LED Ceiling Light.

2. Safety Instructions

WARNING: Electrical installations should only be carried out by a qualified electrician. Incorrect installation can lead to electric shock, fire, or damage to the product.

- Ensure the main power supply is switched off at the circuit breaker before installation, maintenance, or cleaning.
- Do not modify the product in any way.
- Do not look directly into the LED light source when illuminated.
- This product is designed for indoor use only (IP20 rating). Do not expose to moisture or extreme temperatures.
- Keep packaging materials out of reach of children.
- Ensure all connections are secure and properly insulated.

3. Package Contents

Verify that all components are present and undamaged before proceeding with installation:

- Arcchio LED Ceiling Light 'Rotari' fixture (Model 9928035)
- 2 x 8.9W LED light sources (bulbs included)
- Mounting bracket
- Installation hardware (screws, wall plugs - may vary)

4. Specifications

Feature	Specification
Brand	Arcchio
Model Number	9928035
Material	Metal (Aluminium)
Colour	White
Dimensions (L x W x H)	21.2 cm x 10 cm x 10.3 cm
Weight	1.5 kg
Light Source	2 x 8.9W LED
Voltage	230 Volts
Luminous Flux	1640 Lumen
Colour Rendering Index (CRI)	90.00
Protection Class	IP20 (Indoor use only)
Energy Efficiency Label	E (New EU Label)



Image 4.1: Product dimensions (Length: 212mm, Height: 103mm, Diameter: 100mm).

5. Setup and Installation

IMPORTANT: Installation must be performed by a qualified electrician to ensure safety and compliance with local electrical codes.

1. **Preparation:** Switch off the main power supply at the circuit breaker before starting any electrical work.
2. **Mounting Bracket Installation:**
    - Position the mounting bracket on the ceiling at the desired location.
    - Mark the drilling points.
    - Drill holes and insert appropriate wall plugs (if necessary).
    - Secure the mounting bracket to the ceiling using screws.
3. **Electrical Connection:**
    - Connect the household electrical wires to the terminal block inside the fixture. Ensure correct polarity (Live, Neutral,

Earth).

- The fixture is designed for 230V AC supply.
- Ensure all connections are tight and secure.



Image 5.1: View of the internal wiring compartment and mounting bracket.

4. **Fixture Attachment:**
    - Carefully attach the light fixture to the installed mounting bracket, ensuring it is securely fastened.



Image 5.2: The Arcchio Rotari LED Ceiling Light installed on a ceiling.

5. **Power Restoration:** Once installation is complete and all connections are verified, restore power at the circuit breaker.

6. Operating Instructions

The Arcchio LED Ceiling Light 'Rotari' is operated via a standard wall switch connected to its power supply. There are no integrated controls on the fixture itself.

- **Turning On/Off:** Use the wall switch to turn the light fixture on or off.
- **Adjusting Light Heads:** The two light heads can be individually rotated and tilted to direct light as desired.



Image 6.1: The Arcchio Rotari LED Ceiling Light with both light sources illuminated.

7. Maintenance

Regular maintenance ensures the longevity and optimal performance of your light fixture.

- **Cleaning:**
  - Always switch off the power supply before cleaning.
  - Wipe the fixture with a soft, dry, or slightly damp cloth.
  - Do not use abrasive cleaners, solvents, or harsh chemicals, as these can damage the finish.
- **LED Replacement:** The integrated LED light sources are designed for long life and are generally not user-replaceable. If a light source fails, contact a qualified electrician or the manufacturer for assistance.

8. Troubleshooting

If you encounter issues with your Arcchio LED Ceiling Light, refer to the following common troubleshooting steps:

- **Light does not turn on:**
  - Check if the main power supply is switched on at the circuit breaker.
  - Verify that the wall switch is in the "ON" position.
  - Ensure all electrical connections are secure (consult a qualified electrician if unsure).
- **Flickering light:**
  - Ensure stable power supply.
  - If flickering persists, consult a qualified electrician.

For issues not resolved by these steps, please contact customer support or a qualified electrician.

9. Energy Efficiency Information

This product complies with European Union energy efficiency regulations.



Image 9.1: EU Energy Label for the light fixture, indicating Energy Class E and 9 kWh/1000h consumption.

For detailed product information and the official EU energy label, please visit the EPREL database by scanning the QR code on the label or by visiting: https://eprel.ec.europa.eu/qr/744373

10. Warranty and Support

Arcchio products are manufactured to high-quality standards. For warranty information or technical support, please refer to the retailer where the product was purchased or visit the official Arcchio website. Please retain your proof of purchase for warranty claims.

Manufacturer: Lampenwelt

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question