Spider Farmer SF1000Dkits-USA-DE

Spider Farmer SF1000D Grow Tent Kit 2x2x5ft Instruction Manual

Model: SF1000Dkits-USA-DE

1. Introduction

This manual provides detailed instructions for the assembly, operation, maintenance, and troubleshooting of your Spider Farmer SF1000D Grow Tent Kit. Please read this manual thoroughly before setting up and operating your grow tent to ensure safe and efficient use. This kit is designed to provide a complete and controlled environment for indoor plant cultivation.

2. Safety Information

- Always ensure the grow tent is set up on a stable, level surface.
- Keep all electrical components away from water and moisture.
- Do not overload electrical outlets. Use surge protectors if necessary.
- Ensure proper ventilation to prevent heat buildup and maintain air quality.
- Keep children and pets away from the grow tent and its electrical components.
- Unplug all electrical components before performing any maintenance or cleaning.

3. Package Contents

Your Spider Farmer SF1000D Grow Tent Kit includes the following components:

- Pro-grade 2x2x5ft Grow Tent (24"x24"x55")
- SF1000D Samsung LM301B Diodes Full Spectrum LED Grow Light (100W)
- 4" Inline Fan (205 CFM)
- RC412 Activated Carbon Filter
- Flexible Ducting
- 6" Clip Fan (0-2500 RPM, 10 speeds)

- Thermometer & Hygrometer Monitor
- Timer
- Grow Bags (x3)
- Trellis Plant Netting
- YOYO Hanger (x2)
- Vent Cover (x2)
- Corner Shelves (x2)
- Hose Clamps
- Leak-proof Tray



Figure 1: All components included in the Spider Farmer SF1000D Grow Tent Kit.



Figure 2: Labeled diagram of the Spider Farmer SF1000D Grow Tent Kit components.

4. Setup Instructions

4.1. Grow Tent Assembly

1. Unpack all components and verify against the package contents list.
2. Assemble the alloy steel frame according to the provided instructions, ensuring all poles and connectors are securely fitted. The triangular design enhances stability.
3. Drape the 1680D Oxford exterior tent fabric over the assembled frame.
4. Zip up the tent using the smooth SBS zippers, ensuring the reinforced double stitching provides light protection.
5. Insert the high reflective Mylar interior liner.
6. Place the removable leak-proof tray at the bottom of the tent.



Figure 3: The grow tent frame is designed for stability, supporting up to 120 lbs.

4.2. LED Grow Light Installation

1. Using the YOYO hangers, suspend the SF1000D LED grow light from the top bars of the tent.
2. Adjust the height of the light according to the plant growth stage (refer to Section 5.1 for recommended heights).
3. Connect the LED grow light to a power source.

4.3. Ventilation System Setup

1. Mount the 4" inline fan and RC412 activated carbon filter inside the tent, typically near the top.
2. Connect the flexible ducting between the fan and an exhaust port, ensuring proper airflow direction (arrow points to wind direction).
3. Secure the ducting with hose clamps.
4. Attach the 6" clip fan to a tent pole at a suitable height for air circulation around plants.
5. Connect the inline fan and clip fan to power sources.



Figure 4: Proper installation of the ventilation system for effective odor removal and air circulation.

4.4. Accessory Placement

1. Place the thermometer/hygrometer monitor inside the tent at plant canopy level for accurate readings.
2. Connect the timer to the grow light's power cord to automate light cycles.
3. Utilize grow bags for planting and trellis netting for plant support as needed.

Your browser does not support the video tag.

Video 1: A detailed guide on quickly setting up your Spider Farmer grow tent kit.

Your browser does not support the video tag.

Video 2: An overview of the Spider Farmer Complete Grow Tent Kits for indoor gardening.

5. Operating Instructions

5.1. LED Grow Light Operation

The SF1000D LED grow light features premium Samsung LM301B diodes, providing a full spectrum suitable for all plant growth stages. It consumes 100W, offering high energy efficiency and deep canopy penetration.

- **Germination:** Hang at 24"-30", 18 hours ON / 6 hours OFF.
- **Seedling:** Hang at 24", 18 hours ON / 6 hours OFF.
- **Vegetative:** Hang at 18"-24", 18 hours ON / 6 hours OFF.
- **Flowering:** Hang at 12"-18", 12 hours ON / 12 hours OFF.



Figure 5: The SF1000D LED grow light utilizes Samsung LM301B diodes for optimal plant growth.




Figure 6: PPFD (Photosynthetic Photon Flux Density) map for the SF1000D in a 2x2ft grow tent at various heights.

5.2. Ventilation System Operation

The 4" inline fan provides 205 CFM airflow, ensuring excellent air circulation and odor elimination with the RC412 activated carbon filter. The 6" clip fan offers 10 customizable speeds (0-2500 RPM) for flexible circulation and cooling.

- Use the fan speed controller to adjust the inline fan's airflow as needed to maintain optimal temperature and humidity.
- Position the clip fan to provide gentle air movement around the plants, preventing stagnant air and strengthening stems.
- Monitor noise levels; the inline fan operates quietly at 26.8 dB.



Figure 7: The inline fan provides high airflow with minimal noise (26.8 dBA).




Figure 8: The RC412 activated carbon filter effectively removes odors with its multi-layer design.



Figure 9: Detailed specifications for the 6-inch clip fan.

Your browser does not support the video tag.

Video 3: Instructions on controlling your Spider Farmer Inline Fan via App or GGS Controller.

Your browser does not support the video tag.

Video 4: Demonstration of the 2025 New Upgrade APP Remote Control Smart Ventilation System.

5.3. Environmental Monitoring

Use the included thermometer/hygrometer to monitor temperature and humidity levels. Adjust fan speeds or introduce additional environmental controls (e.g., humidifier/dehumidifier, heater) as needed to maintain optimal conditions for your plants.

- **Temperature:** Maintain appropriate temperature ranges for your specific plant species and growth stage.
- **Humidity:** Adjust humidity levels to suit the plant's needs, typically higher for seedlings and lower for flowering.

6. Maintenance

6.1. Cleaning the Tent

Regular cleaning helps maintain a sterile environment and optimal light reflection.

- Wipe down the Mylar interior with a damp cloth and mild detergent as needed.
- Remove and clean the leak-proof tray regularly to prevent water accumulation and mold growth.
- Ensure all duct ports and mesh ventilation ports are clear of debris.



Figure 10: The grow tent features convenient duct ports, mesh ventilation, and a removable floor tray for easy maintenance.

6.2. Filter Maintenance

The RC412 activated carbon filter requires periodic maintenance to remain effective.

- Check the carbon filter regularly for blockages or reduced airflow.
- The filter has a reversible flange to double its lifespan; rotate it when one side shows wear.
- Replace the activated carbon as needed, typically every 6-12 months depending on usage.

7. Troubleshooting

- **Problem:** High temperature inside the tent.
  Solution: Increase inline fan speed, ensure exhaust ports are clear, or add a clip fan for better air circulation.
- **Problem:** Low humidity.
  Solution: Reduce inline fan speed, ensure all tent openings are sealed, or introduce a humidifier.
- **Problem:** Odor issues.
  Solution: Check carbon filter for clogs or exhaustion; replace activated carbon if necessary. Ensure all tent zippers and ports are sealed.
- **Problem:** Grow light not turning on.
  Solution: Check power connections, ensure the timer is set correctly, and verify the dimmer is not set to 0%.

8. Specifications

Feature	Specification
Brand	Spider Farmer
Model Number	SF1000Dkits-USA-DE
Product Dimensions	24"L x 24"W x 55"H
Chamber Volume	18.32 Cubic Feet
Frame Material	Alloy Steel
Inner Material	Mylar (PET)
Outer Material	1680D Oxford cloth
Light Source Wattage	100 Watts
Inline Fan Airflow	205 CFM
Inline Fan Noise Level	26.8 dB
Clip Fan Speeds	0-2500 RPM (10 speeds)
Item Weight	37.5 pounds

9. Warranty and Support

Spider Farmer products come with a manufacturer's warranty. Please refer to the warranty card included in your package or visit the official Spider Farmer website for detailed warranty terms and conditions. For technical support, troubleshooting assistance, or replacement parts, please contact Spider Farmer customer service through their official channels. Keep your purchase receipt as proof of purchase for warranty claims.
Contact Information: Please visit the Spider Farmer Store on Amazon or their official website for the most up-to-date support contact details.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question