

[Manuals.plus](#) /

> [Logitech](#) /

> Logitech G915 TKL Tenkeyless Lightspeed Wireless RGB Mechanical Gaming Keyboard User Manual

Logitech G915 Tenkeyless

Logitech G915 TKL Tenkeyless Lightspeed Wireless RGB Mechanical Gaming Keyboard User Manual

Model: G915 TKL Tenkeyless

1. PRODUCT OVERVIEW

The Logitech G915 TKL is a tenkeyless mechanical gaming keyboard designed for high-performance wireless connectivity and customizable RGB lighting. It features low-profile mechanical switches and a durable, ultra-thin design crafted from aircraft-grade aluminum alloy.



Figure 1.1: Top view of the Logitech G915 TKL keyboard, showcasing its compact layout and vibrant RGB backlighting.

2. KEY FEATURES

- **LIGHTSPEED Wireless Technology:** Delivers pro-grade performance with a 1ms report rate, offering flexibility and freedom from cables.
- **Bluetooth Connectivity:** Allows connection to multiple devices, easily toggling between LIGHTSPEED wireless and Bluetooth.
- **LIGHTSYNC RGB Lighting:** Customizable RGB lighting with approximately 16.8 million colors. Personalize each key or create custom animations using Logitech G HUB software.
- **Low-Profile Mechanical Switches:** Available in GL Tactile, GL Linear, or GL Clicky options, providing the speed, accuracy, and performance of mechanical switches at half the height.
- **Tenkeyless Design:** Compact form factor provides more room for mouse movement and enhances portability. The USB receiver can be stored in the back of the keyboard.
- **Durable Construction:** Crafted from aircraft-grade aluminum alloy for an incredibly thin, rigid, and durable design.

- **Extended Battery Life:** Up to 40 hours of game time on a single charge. Features low battery warnings via keyboard LED and Logitech G HUB software notification. Recharges fully in approximately 3 hours.
- **Dedicated Media Controls:** Includes a precision-engineered, edgeless volume wheel and dedicated buttons for convenient control of media playback (play, pause, skip, mute).



Figure 2.1: Overview of key features including LIGHTSPEED, Bluetooth, Game Mode, LIGHTSYNC RGB, and Low-Profile Mechanical Switches.

LOW-PROFILE MECHANICAL



**PRO PERFORMANCE AT HALF THE HEIGHT
IN THREE SWITCH TYPES**

Figure 2.2: Illustration of the three low-profile mechanical switch types: Tactile, Linear, and Clicky.

3. PACKAGE CONTENTS

Ensure all items are present in the package:

- Logitech G915 TKL Tenkeyless Lightspeed Wireless RGB Mechanical Gaming Keyboard
- LIGHTSPEED USB Receiver
- USB Cable (for charging and wired connection)
- User Documentation (this manual)

4. SETUP

4.1 Initial Charging

Before first use, it is recommended to fully charge the keyboard. Connect the supplied USB cable to the micro-USB port

on the keyboard and the other end to a USB port on your computer or a USB power adapter. The battery indicator LED on the keyboard will show charging status.

4.2 Connecting via LIGHTSPEED Wireless

1. Locate the LIGHTSPEED USB receiver. It is typically stored in a compartment on the back of the keyboard for portability.
2. Plug the LIGHTSPEED USB receiver into an available USB port on your computer.
3. Turn on the keyboard using the power switch located on the top edge. The keyboard should automatically connect to the receiver.
4. For optimal performance, ensure the keyboard is within close proximity to the receiver and away from sources of interference.



Figure 4.1: The G915 TKL supports LIGHTSPEED wireless for high-performance connectivity.

4.3 Connecting via Bluetooth

1. Turn on the keyboard using the power switch.

2. Press and hold the Bluetooth button (usually indicated by a Bluetooth icon) on the keyboard until the indicator light starts blinking rapidly, indicating pairing mode.
3. On your device (computer, tablet, smartphone), go to Bluetooth settings and select "Logitech G915 TKL" from the list of available devices.
4. Follow any on-screen prompts to complete the pairing process.

5. OPERATING INSTRUCTIONS

5.1 Switching Connection Modes

The G915 TKL allows seamless switching between LIGHTSPEED wireless and Bluetooth connections. Use the dedicated buttons on the keyboard to toggle between the two modes.

5.2 LIGHTSYNC RGB Customization

To fully customize the RGB lighting effects, colors, and animations, download and install the Logitech G HUB software from the official Logitech website. The software provides granular control over individual key lighting and allows for synchronization with other LIGHTSYNC-enabled devices.

5.3 Media Controls

The keyboard features dedicated media control buttons and an edgeless volume wheel located on the top right. These controls allow for quick adjustment of audio volume, playback, pause, skip, and mute functions without interrupting your activity.

5.4 Battery Management

The G915 TKL offers approximately 40 hours of continuous use with RGB lighting enabled. When the battery level drops to 15%, a low battery warning will be indicated by the keyboard's battery LED and a notification in the Logitech G HUB software. Connect the USB cable to recharge the keyboard. A full charge typically takes 3 hours.

40 HOURS BATTERY LIFE



WITH LIGHTSYNC RGB

Figure 5.1: The G915 TKL provides up to 40 hours of battery life with LIGHTSYNC RGB enabled.

6. MAINTENANCE

- **Cleaning:** Use a soft, lint-free cloth to wipe down the keyboard surface. For deeper cleaning, a can of compressed air can be used to remove dust and debris from between the keycaps. Avoid using harsh chemicals or abrasive materials.
- **Storage:** When not in use for extended periods, store the keyboard in a cool, dry place. Ensure the USB receiver is securely stored in its designated compartment on the keyboard.
- **Battery Care:** To prolong battery life, avoid fully discharging the keyboard frequently. Recharge when the low battery warning appears.

7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Keyboard not responding (LIGHTSPEED)	USB receiver not plugged in; keyboard off; out of range; low battery.	Ensure receiver is plugged in. Turn keyboard on. Move keyboard closer to receiver. Charge keyboard.
Keyboard not responding (Bluetooth)	Not paired; Bluetooth off on device; out of range; low battery.	Enter pairing mode and re-pair. Enable Bluetooth on your device. Move keyboard closer. Charge keyboard.
RGB lighting not working or incorrect	Logitech G HUB software issue; low battery.	Ensure G HUB is installed and updated. Check keyboard battery level. Restart G HUB.
Keys not registering or double-typing	Dust/debris under keycap; firmware issue.	Clean under keycaps with compressed air. Check Logitech G HUB for firmware updates.

8. SPECIFICATIONS

- **Model:** G915 TKL Tenkeyless
- **Dimensions:** 15.2 x 5.9 x 0.9 inches
- **Weight:** 5.3 ounces
- **Connectivity:** LIGHTSPEED Wireless, Bluetooth
- **Switch Type:** Low-Profile Mechanical (Tactile, Linear, Clicky options)
- **Backlighting:** LIGHTSYNC RGB (16.8 million colors)
- **Battery Life:** Up to 40 hours (with RGB)
- **Charging Time:** Approximately 3 hours
- **Cable Type:** USB Micro (for charging and wired connection)

9. WARRANTY AND SUPPORT

For warranty information and technical support, please visit the official Logitech support website or contact their customer service. Keep your proof of purchase for warranty claims.
Logitech Support Website: support.logi.com

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for

conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B08L8BP9KK>

More documents and user manuals: <https://manuals.plus/>