

EMEET M2 Max

# EMEET M2 Max Bluetooth Speakerphone User Manual

Model: M2 Max  
Brand: EMEET

## 1. INTRODUCTION

This user manual provides comprehensive instructions for the setup, operation, maintenance, and troubleshooting of your EMEET M2 Max Bluetooth Speakerphone. Please read this manual carefully before using the device to ensure optimal performance and longevity.

## 2. PRODUCT OVERVIEW

The EMEET M2 Max is a professional conference speakerphone designed for business conference calls, supporting up to 15 participants. It features advanced audio technology for clear communication in various meeting environments.



Figure 2.1: EMEET M2 Max Speakerphone and USB Dongle

The image displays the EMEET M2 Max speakerphone, a circular black device with a perforated top surface and a central control panel featuring illuminated icons for Bluetooth, call, volume, and mute. A small USB dongle is shown next to it, indicating wireless connectivity options.

### 2.1 Key Features

- 4 Professional Audio Level Microphones:** Equipped with four directional microphones with a 48kHz sampling rate for high-definition voice pickup, suitable for 1-15 attendees.
- Daisy Chain Capability:** Allows connecting two M2 Max units for extended voice pickup and transmission range, accommodating up to 30 attendees.
- VoicelA Noise Reduction:** Patented technology and rubber insulators effectively eliminate ambient noise and vibrations, ensuring clear audio.
- Multiple Connection Methods:** Supports USB, Bluetooth, AUX, and Dongle connections for versatile compatibility with various devices and operating systems (Windows, macOS, Android, Linux).
- Dual Bluetooth Device Support:** Connects to two Bluetooth devices simultaneously, or one Bluetooth device and one USB/dongle connection.

- **Personalization via eMeetLink:** Offers customization options for Bluetooth name, standby time, firmware updates, and LED light control.
- **12-Hour Playtime:** Provides extended battery life for full-day meeting usage.

### 3. SETUP

#### 3.1 Package Contents

- EMEET M2 Max Speakerphone
- USB Cable
- USB Bluetooth Dongle
- User Manual (this document)

#### 3.2 Connecting Your Speakerphone

The EMEET M2 Max offers several connection options:



Figure 3.1: Connection Options (USB, Dongle, AUX, Bluetooth)

This image illustrates the various connectivity options for the EMEET M2 Max, including USB, a dedicated dongle, AUX cable, and Bluetooth 5.0, showing how the device can connect to both a laptop and a smartphone.

##### 1. USB Connection:

Connect the speakerphone to your computer using the provided USB cable. The device will automatically power on and be recognized by your operating system. This is the recommended method for stable audio and power.

##### 2. Bluetooth Connection:

- Press and hold the Bluetooth button on the speakerphone until the indicator light flashes blue.
- On your device (smartphone, tablet, or computer), enable Bluetooth and search for "EMEET M2 Max".
- Select the device to pair. Once connected, the indicator light will turn solid blue.
- The M2 Max can connect to two Bluetooth devices simultaneously.

##### 3. USB Dongle Connection:

Plug the USB dongle into an available USB port on your computer. The speakerphone will automatically connect to the dongle, providing a stable wireless connection. This is ideal for computers without built-in Bluetooth or for a more reliable connection.

##### 4. AUX Connection:

Use a 3.5mm AUX cable (not included) to connect the speakerphone to devices with an audio output jack. This provides a direct audio connection without Bluetooth or USB.

#### 3.3 Daisy Chain Setup (Optional)

For larger meeting rooms or more attendees (up to 30 people), you can daisy chain two EMEET M2 Max units using an EMEET daisy chain cable (sold separately).

# Flexible for Medium/Large Meetings

Alone use up to 15 people, Daisy chain up to 20 people



Figure 3.2: Daisy Chain Configuration

This image shows two EMEET M2 Max speakerphones placed along a long conference table, illustrating how they can be daisy-chained to extend audio coverage for medium to large meetings, accommodating up to 20 people.

1. Connect the first M2 Max unit to your computer via USB or Bluetooth.
2. Connect the EMEET daisy chain cable to the "OUT" port of the first M2 Max and the "IN" port of the second M2 Max.
3. Ensure both units are powered on. The system will automatically configure for expanded coverage.

## 4. OPERATING INSTRUCTIONS

### 4.1 Controls and Indicators

The EMEET M2 Max features intuitive touch controls and LED indicators on its top surface:

- **Power Button:** Press and hold to turn on/off.
- **Bluetooth Button:** Press to enter pairing mode.
- **Answer/End Call Button:** Press to answer or end a call.
- **Volume Up (+):** Increase speaker volume.
- **Volume Down (-):** Decrease speaker volume.
- **Mute Microphone Button:** Mute or unmute the microphones. The LED ring will indicate mute status.
- **LED Ring Indicator:** Displays power status, Bluetooth pairing status, call status, and microphone mute status.

### 4.2 Making and Receiving Calls

1. Ensure the M2 Max is connected to your device (computer, smartphone).
2. Initiate a call from your connected device or conferencing software.
3. To answer an incoming call, press the Answer/End Call button.
4. To end a call, press the Answer/End Call button again.

### 4.3 VoiceIA Noise Reduction

The EMEET M2 Max utilizes VoiceIA technology to minimize background noise and echoes, ensuring clear voice transmission during calls.

## Unique VoicelA® Noise Reduction

Cancel echos and over 282 types of noises with deep learning



Figure 4.1: VoicelA Noise Reduction in Action

This image visually represents the VoicelA Noise Reduction feature, showing sound waves before and after processing. The "Before" section depicts a mix of voice and noise waves, while the "After" section shows only clear voice waves, indicating effective noise cancellation.

This feature is automatically active. For advanced settings or to toggle specific noise reduction features, use the eMeetLink software.

### 4.4 eMeetLink Software (Personalization)

Download the eMeetLink software from the official EMEET website to customize your M2 Max speakerphone.



Figure 4.2: eMeetLink Personalization Options

The image shows a laptop screen displaying the eMeetLink software interface, which allows users to personalize settings for the EMEET M2

Max speakerphone, such as renaming Bluetooth, setting standby time, updating firmware, and controlling the DOA light.

With eMeetLink, you can:

- Rename the Bluetooth device.
- Adjust standby time.
- Update product firmware and software.
- Turn on/off the DOA (Direction of Arrival) light.
- Configure pickup angle and other audio settings.

5. MAINTENANCE

- Clean the device with a soft, dry cloth. Do not use abrasive cleaners or solvents.
- Avoid exposing the speakerphone to extreme temperatures, humidity, or direct sunlight.
- Do not disassemble the device. Any unauthorized repairs will void the warranty.
- Store the speakerphone in a cool, dry place when not in use for extended periods.

6. TROUBLESHOOTING

Problem	Possible Cause	Solution
No sound from speakerphone.	Volume too low; device not selected as audio output; muted.	Increase volume on speakerphone and connected device. Ensure M2 Max is selected as default audio output. Unmute the speakerphone.
Microphone not picking up sound.	Microphone muted; M2 Max not selected as input device.	Unmute the microphone on the speakerphone. Select M2 Max as the default microphone input in your device's sound settings or conferencing software.
Bluetooth connection unstable or failing.	Too far from device; interference; pairing issue.	Move speakerphone closer to the connected device. Avoid obstacles. Re-pair the Bluetooth connection. Try using the USB dongle.
Daisy chain not working.	Incorrect cable; improper connection.	Ensure you are using an official EMEET daisy chain cable. Verify connections to "IN" and "OUT" ports are correct.
Device not charging.	Faulty cable or power source.	Try a different USB cable and power adapter/port. Ensure the cable is securely connected.

7. SPECIFICATIONS

Feature	Detail
Model Name	M2 Max
Speaker Type	Computer Speakerphone
Microphones	4 Directional Microphones
Connectivity Technology	Bluetooth, USB, AUX, Daisy Chain, Dongle
Wireless Communication	Bluetooth
Bluetooth Range	10 Meters
Speaker Maximum Output Power	5 Watts
Signal-to-Noise Ratio	89 dB
Power Source	Battery Powered (1 Lithium Polymer battery required)
Product Dimensions	7.4 x 7.4 x 1.77 inches
Item Weight	2.48 pounds
Color	Black
Compatible Devices	Desktop, Laptop, Projector, Smartphone, Tablet
Control Method	Voice, Buttons
Included Components	Microphone (integrated)



8. WARRANTY AND SUPPORT

8.1 Warranty Information



Figure 8.1: Warranty Coverage  
An icon representing a shield with a checkmark, indicating a 2-year exclusive warranty for the product.

The EMEET M2 Max speakerphone comes with a **2-year exclusive warranty** from the date of purchase. This warranty covers manufacturing defects and malfunctions under normal use. Please retain your proof of purchase for warranty claims.

8.2 Technical Support



Figure 8.2: Lifetime Technical Support  
An icon depicting a headset, symbolizing lifetime professional technical team support available for the product.

EMEET provides **lifetime professional technical support** for the M2 Max. If you encounter any issues or have questions not covered in this manual, please contact EMEET customer service. Inquiries are typically replied to within 24 hours. For support, visit the official EMEET website or refer to the contact information provided with your product packaging.

© 2024 EMEET. All rights reserved.

Related Documents

	<p><a href="#">eMeet M2 Max Conference Speaker - User Manual and Features</a></p> <p>Comprehensive guide to the eMeet M2 Max conference speaker, covering its buttons, overview, power management, VoicelA and MIC mute functions, call handling, volume control, Bluetooth and USB connectivity, dongle usage, headset integration, daisy chain capability, lock port, charging, and application download.</p>
	<p><a href="#">eMeet OfficeCore M2/M2ce Smart Conference Speaker User Manual</a></p> <p>User manual for the eMeet OfficeCore M2 and M2ce smart conference speakerphones. Learn about product features, functions, connectivity options (USB, Bluetooth, AUX), operation, charging, and troubleshooting.</p>
	<p><a href="#">eMeet OfficeCore M2 User Manual: Smart Wireless Speakerphone</a></p> <p>User manual for the eMeet OfficeCore M2 smart wireless speakerphone, detailing its features, connectivity (Bluetooth, USB, AUX), and usage for clear conference calls.</p>
	<p><a href="#">OfficeCore M2 Max Professional Speakerphone User Manual   eMeet</a></p> <p>Comprehensive user manual for the eMeet OfficeCore M2 Max professional speakerphone. Learn about button functions, connectivity options (Bluetooth, USB, Dongle), VoicelA noise reduction, MIC mute, Daisy Chain, and charging.</p>



[pdf] Specifications

eMeet Professional Speakerphone eMeetOfficeCore M2 Max Product na zhang@emeet ai The offers 4 condenser microphones to give you a 360° pickup OfficeCc SHENZHEN EMEET TECHNOLOGY CO., LTD. TEL: 18026618626 www.emeet.ai Professional Speakerphone eMeet OfficeCore **M** contact na.zhang emeet.ai SHENZHEN EMEET TECHNOLOGY CO., LTD. TEL: 18026618626 www.emeet.ai 1. Product introducti... lang:en score:28 filesize: 553.71 K page\_count: 5 document date: 2021-05-27



[pdf]

Професійний портативний USB Bluetooth спікерфон eMeet OfficeCore M2 MAX M2MAX DAFbL8LHDxI BACw3VfHC8 missdemidova70 Page 1 Інструкція українська m2max i citrus world files |||


USB/Bluetooth- eMeet OfficeCore **M2 MAX** eMeet-M2MAX ...

lang:en score:27 filesize: 46.6 K page\_count: 1 document date: 2024-05-03




[pdf]

EMEET OfficeCore M2 Max Conference Speaker Datesheet max v 1675417307 ocn shopify s files 1 0594 9472 7851 ||| EMEET OfficeCore **M2 Max** Dual Way Audio Quality Max Professional Speakerphone 360 5m Ultra HD Voice Pickup 4 highly-sensitive sampling rate ensures exceptional clarity and reality. Smart Voice Tracking and Strengthening AI-powered vocal... lang:en score:27 filesize: 955.88 K page\_count: 3 document date: 2023-01-13




[pdf] Test Report SAR Rating

Microsoft Word SZ20120190S01 EMEET OfficeCore M2 Max FCC RF Exposure Exempt Report docx Morlab Shenzhen eMeet technology Co Ltd M2MAX Profess REPORT No.SZ20120190S01 RF EXPOSURE EXEMPT REPORT APPLICANT : SHENZHEN EMEET TECHNOLOGY CO., LTD. F OfficeCore **M2 Max**, OfficeCore **M2 Max** 330, OfficeCore **M2 Max** 260 BRAND NAME : eMeet FCC ID STANDARD S RECEIPT DAT lang:en score:26 filesize: 298.88 K page\_count: 8 document date: 2021-01-15




eMeet M2 Max Conference Speaker - User Manual and Features

Comprehensive guide to the eMeet M2 Max conference speaker, covering its buttons, overview, power management, VoiceIA and M connectivity, dongle usage, headset integration, daisy chain capability, lock port, charging, and application download. lang:en score:26 filesize: 9.39 M page\_count: 9 document date: 2021-01-27




[pdf] Declaration of Conformity

Microsoft Word OfficeCore M2 Max Declaration Letter WJN Shenzhen eMeet technology Co Ltd M2MAX Professional Speakerphone 2ALCN 2ALCNM2MAX m2m: SHENZHEN EMEET TECHNOLOGY CO., LTD. Model difference Declaration Letter Date:2021.01.04 Hereby, we, SHENZHEN EME number:OfficeCore **M2 Max**, with model number: OfficeCore **M2 Max** 330 OfficeCore **M2 Max** 260 have the same hardware and softy lang:tl score:25 filesize: 93.36 K page\_count: 1 document date: 2021-01-14



Професійний портативний USB/Bluetooth-спікерфон eMeet OfficeCore M2 MAX (eMeet M2MAX)




[pdf] Specifications

eMeet 202219250 cdn petec ch documents2 0 5 2  
SHENZHEN EMEET TECHNOLOGY CO., LTD. TEL: 18026618626 www.emeet.ai Professional Speakerphone eMeet OfficeCore **M2 Max**  
contact na.zhang\_emeet.ai SHENZHEN EMEET TECHNOLOGY CO., LTD. TEL: 18026618626 www.emeet.ai 1. Product introduction  
lang:en score:23 filesize: 553.99 K page\_count: 5 document date: 2021-02-02

[pdf]

Професійний портативний USB Bluetooth спікерфон eMeetКнопка VoiceA 2 Кнопка 3 прийняття завершення дзвінка виклику 4 збільшення гучності 5 зменшення гучності 6 м'яке вимкнення  
m2max citrus world files profesyniy m2max |||  
USB/Bluetooth eMeet OfficeCore **M2 MAX** eMeet-M2MAX j 1. VoiceA 2. Bluetooth 3. // 4. 5. 6. 7. 8. LED-9. 10. 11. 12. 13. LINK 14  
lang:nl score:23 filesize: 1.13 M page\_count: 10 document date: 2024-04-30




[pdf] Test Report

Microsoft Word SZ20120190W01 EMEET OfficeCore M2 Max BTclassic DSS Administrator Shenzhen eMeet technology Co Ltd M2MAX Professional Speakerphone  
REPORT No.SZ20120190W01 TEST REPORT APPLICANT PRODUCT NAME MODEL NAME BRAND NAME : SHENZHEN EMEET  
**M2 Max**, OfficeCore **M2 Max** 330, OfficeCore **M2 Max** 260 : eMeet FCC ID : 2ALCN-M2MAX STANDARD S : 47 CFR Part 15 Subpart C  
lang:en score:22 filesize: 4.77 M page\_count: 81 document date: 2021-01-15



[pdf] Borchure Catalog

eMeet PRODUCT CATALOG Microphone Array Signal Processing speakerphone offers crystal clear audio by applying the proprietary VoiceIA® technology  
00P6900002pWfImEAG |||  
PRODUCT CATALOG Audio and Video Solutions - Q1, 2021 - Make Meeting Simple CONTENTS eMeet Commitment ... action. Voice IA  
OFFICECORE **M2 MAX** OfficeCore **M2 Max** offers 4 Uni-directional microphones to functional a 360° voice pickup pattern. Built-in Voice IA  
lang:en score:20 filesize: 3.47 M page\_count: 28 document date: 2021-02-24



[pdf]

M2Max ES Bedienungsanleitung eMeet OfficeCore M2 Max Konferenzlautsprecher schwarz ab € 151 95 2022 Preisvergleich Geizhals Deutschland 4a36c175  
Buttons Overview VoiceIA button Bluetooth button Answer/End Phone Call button Volume button Volume button Mute button Power  
port 1 LINK Daisy Chain port USB port Type C Dongle Namep...  
lang:en score:20 filesize: 9.39 M page\_count: 9 document date: 2021-10-27



[pdf] Declaration of Conformity Test Report

FCC SDoC docx shenzhen letter Shenzhen eMeet technology Co Ltd M2MAX Professional Speakerphone 2ALCN 2ALCNM2MAX m2max  
SHENZHEN EMEET TECHNOLOGY CO., LTD. Supplier's Declaration Of Conformity for the FCC SDoC Procedure The following information  
Product Name:Professional Speakerphone Brand Name:eMeet Model Number:OfficeCore **M2 Max**, OfficeCore **M2 Max** 330, OfficeCore  
lang:en score:18 filesize: 92.26 K page\_count: 1 document date: 2021-01-18





Download Now User Manual EMEET M2 Max 2 Pack with Daisy Chain Speakerphone Downloads Product Uesr v 1659001152 cdn shopify s files 1 0594 9472 785  
...  
lang:en score:18 filesize: 5.38 M page\_count: 65 document date: 2022-07-28



Microsoft Word SZ20120183C01 RED CE VOC Administrator VERIFICATION OF CONFORMITY eleonto medias context  
bWfZdGvYIGrY3VIZW50c3wyjME3NTJ8YXBwbGJlYXRpb24vcGRmIGRvY3VIZW50cy9oODMwaDlxZg5MTg5NzY3OTA1NTguoGRmIGJzJAwZWWhMjllODQ5I  
attachment true |||  
Shenzhen Morlab Communications Technology Co., Ltd. VERIFICATION OF CONFORMITY No.: SZ20120183C01 Page 1 of 1 Proc  
Speakerphone eMeet OfficeCore **M2 Max**, OfficeCore **M2 Max** 330, OfficeCore **M2 Max** 260 SHENZHEN EMEET TECHNOLOGY C  
lang:en score:14 filesize: 216.55 K page\_count: 1 document date: 2021-01-12