Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

Arcchio 9969185

Outdoor Wall Light 'Ismera' User Manual

Brand: Arcchio | **Model:** 9969185

1. Product Overview

The Arcchio 'Ismera' outdoor wall light is designed with a modern, linear aesthetic, featuring a die-cast aluminium frame and clear glass panels. This design allows light to escape to all sides, providing effective illumination for exterior and interior walls, houses, terraces, and balconies. It is compatible with an E27 bulb (not included) and is dimmable, offering flexibility in lighting ambiance.



Image: The Arcchio 'Ismera' outdoor wall light, showcasing its modern design with a clear glass enclosure and an exposed E27 bulb.

2. Safety Information

Please read all safety instructions carefully before installation and operation. Failure to follow these instructions may result in electric shock, fire, or other hazards.

- **Electrical Safety:** Installation should only be performed by a qualified electrician or competent person in accordance with local electrical codes and regulations. Always disconnect power at the main circuit breaker before installation, maintenance, or bulb replacement.
- **IP65 Rating:** This product is rated IP65, meaning it is protected against dust ingress and low-pressure water jets from any direction. While suitable for outdoor use, ensure all connections are properly sealed during installation to maintain this rating.

- **Bulb Compatibility:** Use only E27 bulbs with a maximum wattage of 20W. Ensure the bulb is suitable for dimming if you intend to use the dimmable feature.
- **Handling:** Handle the light fixture and glass components with care to prevent breakage.
- **Disposal:** Dispose of old light bulbs and packaging materials responsibly, following local recycling guidelines.

3. Package Contents

Verify that all components are present and undamaged before beginning installation:

- Arcchio 'Ismera' Outdoor Wall Light Fixture
- Dimmer (integrated or compatible component)
- Socket (E27)
- Mounting hardware (screws, wall plugs - typically included, though not explicitly listed in "whats_in_the_box", it's standard for light fixtures)
- *Note: Lightbulb is not included and must be purchased separately.*



Image: Exploded view of the Arcchio 'Ismera' wall light, showing the main housing, mounting plate, and glass enclosure, indicating components for assembly.

4. Setup and Installation

Tools Required: Screwdriver, drill, wire strippers, voltage tester, pencil, measuring tape.

1. **Prepare for Installation:**
   - Turn off the main power supply to the installation area at the circuit breaker. Verify power is off using a voltage tester.
   - Carefully unpack the light fixture and inspect for any damage.
2. **Mark Mounting Position:**
   - Determine the desired mounting location on the wall. Consider the light's dimensions (Height: 25.5 cm, Width: 13 cm, Depth: 11.5 cm) for proper placement.
   - Use the mounting plate as a template to mark the drill holes on the wall.
3. **Mount the Fixture Base:**
   - Drill holes at the marked positions and insert appropriate wall plugs (if necessary).
   - Secure the mounting plate to the wall using the provided screws. Ensure it is firmly attached.
4. **Wire the Fixture:**
   - Connect the household electrical wires to the fixture's wires according to standard wiring practices (Live to Live, Neutral to Neutral, Earth to Earth). Use appropriate wire connectors.
   - Ensure all connections are secure and insulated.
5. **Attach the Light Body:**
   - Carefully align the light fixture body with the mounted base and secure it using the provided screws or fasteners.
   - Ensure the fixture is flush against the wall and all seals are properly seated to maintain the IP65 rating.
6. **Install the Lightbulb:**
   - Insert an E27 bulb (max 20W) into the socket.
   - Attach the clear glass enclosure to the fixture, ensuring it is securely fastened.
7. **Test Operation:**
   - Restore power at the main circuit breaker.
   - Test the light to ensure it functions correctly.



Image: Diagram showing the dimensions of the Arcchio 'Ismera' wall light: 255mm height, 130mm width, and 115mm depth.



Image: The Arcchio 'Ismera' wall light installed on an exterior wall next to a door, demonstrating its appearance in a typical setting.

5. Operating Instructions

The Arcchio 'Ismera' wall light operates like a standard light fixture once installed. It is designed to be dimmable, allowing for adjustable light intensity.

- **Turning On/Off:** Use your existing wall switch to turn the light fixture on or off.
- **Dimming Function:** If connected to a compatible dimmer switch and equipped with a dimmable E27 bulb, you can adjust the light output by operating the dimmer switch. Ensure the bulb used is explicitly rated as dimmable for optimal performance.

6. Maintenance

Regular maintenance will help prolong the life and appearance of your 'Ismera' wall light.

- **Cleaning:**

- Before cleaning, ensure the power supply to the fixture is turned off.
- Wipe the aluminium frame with a soft, damp cloth. Avoid abrasive cleaners or solvents that could damage the finish.
- Clean the glass panels with a glass cleaner and a soft cloth.

- **Bulb Replacement:**
  - Always turn off the power supply before replacing the bulb.
  - Allow the old bulb to cool down before handling.
  - Unscrew the old E27 bulb and screw in a new E27 bulb (max 20W).
  - Ensure the new bulb is securely seated before restoring power.
- **Inspection:** Periodically inspect the fixture for any signs of wear, damage, or loose connections. Address any issues promptly.

7. Troubleshooting

If you encounter issues with your 'Ismera' wall light, refer to the following common troubleshooting steps:

Problem	Possible Cause	Solution
Light does not turn on.	No power supply. Loose wiring. Faulty bulb.	Check circuit breaker. Verify all wire connections are secure (with power off). Replace bulb with a known working one.
Light flickers or dims incorrectly.	Incompatible dimmer switch. Non-dimmable bulb. Loose bulb connection.	Ensure dimmer switch is compatible with LED/dimmable bulbs. Use a dimmable E27 bulb. Tighten the bulb in the socket.
Water inside the fixture.	Improper sealing during installation. Damage to fixture.	Ensure all seals and gaskets are correctly seated and tightened. Re-seal if necessary. If damaged, replace the fixture.

If the problem persists after attempting these solutions, please contact customer support.

8. Specifications

Feature	Detail
Brand	Arcchio
Model Number	9969185
Manufacturer	Lampenwelt
Material	Aluminium (Frame), Glass (Shade)
Colour	Silver / Dark Grey
Product Dimensions (L x W x H)	11.5 x 13 x 25.5 cm

Feature	Detail
Item Weight	2.08 kg
Socket Type	E27
Max. Wattage	1 x 20 W
Operating Voltage	230 V
IP Code	IP65
Protection Class	I
Special Features	Dimmable
Included Components	Dimmer, Socket



Image: Certification marks (UKCA, CE, WEEE, electrical safety) and EAN (4251096589405) for the Arcchio Ismera light.

9. Warranty and Support

For warranty information and customer support, please contact the seller or manufacturer, Lampenwelt. Keep your proof of purchase for any warranty claims.

Manufacturer: Lampenwelt

For further assistance or technical inquiries, refer to the contact information provided with your purchase or visit the official Arcchio/Lampenwelt website.

© 2024 Arcchio. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0912ZRDWJ

More documents and user manuals: **https://manuals.plus/**