

[Manuals.plus](#) /

› [Lomiluskr](#) /

› Lomiluskr K680T Wireless 60% Mechanical Keyboard User Manual

Lomiluskr K680T

Lomiluskr K680T Wireless 60% Mechanical Keyboard

USER MANUAL

Introduction

Thank you for choosing the Lomiluskr K680T Wireless 60% Mechanical Keyboard. This manual provides detailed instructions for setting up, operating, and maintaining your new keyboard. Please read this manual thoroughly before use to ensure optimal performance and longevity of your device.



Image: Front view of the Lomiluskr K680T Mechanical Keyboard, showcasing its compact 60% layout and vibrant RGB backlighting.

Key Features

- **68-Key Compact Layout:** A 60% layout with 68 keys, designed to save desktop space while retaining essential keys for gaming and daily use.

- **Bluetooth Wireless / Wired Dual Mode:** Offers flexibility with both Bluetooth 3.0 wireless and USB Type-C wired connectivity.
- **Multi-Device Connection:** Connects to up to 3 devices simultaneously, allowing easy switching between them (FN+Q/W/E).
- **N-Key Rollover:** Full N-key rollover in wired mode ensures all key presses are registered accurately, preventing ghosting.
- **Multicolor Backlight with 18 Effects:** Features a vibrant multicolor backlight with 18 customizable lighting effects.
- **1000mAh Built-in Battery:** Provides long-lasting wireless usage.
- **Professional Mechanical Switches:** Equipped with durable mechanical switches for a responsive and tactile typing experience.



N-Key Rollover
全キー無衝突



Wired/Bluetooth
有線/bluetooth



Multicolor Backlit
マルチカラーバックライト



Compact 68 Keys
シンプル68ボダン



Double-Shot
Injection Keycap
二色射出成形

Image: The K680T keyboard alongside its packaging, highlighting key features such as N-Key Rollover, Wired/Bluetooth connectivity, Multicolor Backlight, Compact 68 Keys, and Double-Shot Injection Keycaps.

Package Contents

Please check the package contents upon unboxing to ensure all items are present:

- Lomilusr K680T Mechanical Keyboard
- USB Type-C Cable
- Keycap Puller
- User Manual (this document)



Image: The complete package contents of the Lomilusr K680T, including the keyboard, USB-C cable, keycap puller, and user manual.

Setup

Wired Connection

1. Locate the USB Type-C port on the keyboard.
2. Connect one end of the provided USB Type-C cable to the keyboard.
3. Connect the other end of the USB cable to an available USB port on your computer.
4. The keyboard will be automatically recognized by your system and is ready for use. The keyboard will also charge in wired mode.

Bluetooth Connection

The K680T keyboard supports Bluetooth 3.0 and can connect to up to 3 devices simultaneously.

1. **Step 1:** Locate the switch on the bottom of the keyboard and slide it to the "BT" position to enable Bluetooth mode.
2. **Step 2:** Select a device slot by pressing **FN + Q** (Device 1, indicator light red), **FN + W** (Device 2, indicator light green), or **FN + E** (Device 3, indicator light blue).
3. **Step 3:** Enter pairing mode by pressing and holding **FN + P** for 2 seconds. The indicator light will flash, indicating it is ready for pairing.
4. **Step 4:** On your device (computer, tablet, smartphone), enable Bluetooth and search for available devices.
5. **Step 5:** Select "AJAZZ K680T Keyboard" from the list of found devices to complete the pairing process.

Bluetooth Connection Method Bluetooth接続方法

Dial the bottom button to the "BT" position
下のボタンを「BT」の位置にダイヤルします



Step1



Switch to this device,
the indicator light is red
設備を切り替え
対応ランプが赤色に点灯します



Switch to this device,
the indicator light is green
設備を切り替え
対応ランプがグリーンに点灯します



Switch to this device,
the indicator light is blue
設備を切り替え
対応ランプがブルーに点灯します

Step2

Press Fn and one of Q/W/E as the storage key and then release the key.
(This product can memorize 3 devices, stored in Q/W/E buttons)

Fn+Q/W/ Eのいずれかを保存キーとして押してからキーを離します。

(この製品は3つの端末装置を記憶して、それぞれQ/W/Eの3つのキーに保存します。)

Step3

Press the FN+P button for 2 seconds, release it to enter the pairing state after the indicator flashes.

FN+Pキー2sを長押しし、指示灯が点滅してから離して接続状態にします。

Step4

Turn on the device's Bluetooth function and search.

設備のbluetooth機能を開いて検索し。

Step5

Find the device named "AJAZZ K680T Keyboard" and click Connect to complete the connection.

「AJAZZ K680T Keyboard」という機器が接続をクリックすると接続が完了します。

Bluetooth/Wired Dual-Mode Bluetooth/有線 両対応

Bluetooth connection and USB wired connection, dual-mode connection supports multi-devices, easier to switch.

キーボードはBluetooth接続とUSBケーブル接続をサポートしています。デュアルモード接続方式は様々な設備の使用をサポートしています。設備のシームレスな切り替えに便利です。

Bluetooth Mode/bluetoothモード

Wireless Bluetooth 3.0 stable transmission,
10 m effective transmission distance

有効距離10 m、線材の束縛を抜け出して、
仕事が便利であります。



USB Wired Mode/有線モード

Type-C interface, usb while charging,
Transmission is more stable

USBケーブルは分離でき、伝送は安定的
で効率的で、ゲームをより快適にします。



Image: Visual representation of the keyboard's dual-mode capability, showing both Bluetooth wireless and USB wired connections for versatile use.

Operating Instructions

Switching Between Modes

To switch between wired and Bluetooth modes, use the physical switch located on the bottom of the keyboard. Slide it to the desired position (USB for wired, BT for Bluetooth).

Multi-Device Switching

Once paired with multiple devices (up to 3), you can easily switch between them:

- Press **FN + Q** to switch to Device 1.
- Press **FN + W** to switch to Device 2.
- Press **FN + E** to switch to Device 3.

Up to 3 devices, Easy to Switch

3台の機器に対応し、ワンタッチで切り替える

Compatible with a variety of devices, can store three Bluetooth device connections, use Fn+QWE directly to switch to the corresponding device when you use it again, no need to connect again.

複数の機器に対応しており、3つのbluetooth機器接続が格納されている。
再利用はFn+Q/W/Eを直接使用して対応機器に切り替えることで利用可能であり、再接続操作は不要であります。



Image: The keyboard connected to multiple devices (laptop, tablet, smartphone), demonstrating the ease of switching between them using FN+Q/W/E.

Backlight Control

The K680T features a multicolor backlight with 18 different lighting effects. Use the following key combinations to control the backlight:

- Press **FN + →** to cycle through different backlight effects.
- Press **FN + ←** to cycle through different backlight effects in reverse.
- Press **FN + ↑** to increase backlight brightness.
- Press **FN + ↓** to decrease backlight brightness.

N-Key Rollover

In wired mode, the K680T supports N-key rollover, meaning all simultaneous key presses will be registered accurately. This is particularly beneficial for fast typing and gaming.

Battery Management

The keyboard is equipped with a 1000mAh built-in battery. When the battery is low, the indicator light may flash. Connect the keyboard via the USB Type-C cable to charge it. A full charge takes approximately 3 hours. The keyboard can last up to 10 hours with backlight on, and up to 60 hours with backlight off, with a standby time of 360 hours.

Long Battery Life
恒久航続

With 1000mAh battery, which can allow you to use at least 10 hours, turn off the backlight to use 60 hours, 360 hours of standby time, 3 hours of fast charging time.

1000 mAのリチウム電池を搭載しており、あなたは少なくとも10時間を使うことができます、バックライトをオフして60時間連続使用し、360時間待機することができます、3時間の急速充電時間。



Image: An illustration highlighting the 1000mAh battery capacity and its long-lasting performance, including usage and standby times.

Specifications

Feature	Specification
Model	K680T
Layout	68-key, 60% Compact
Connectivity	Bluetooth 3.0 + USB Wired (Type-C)
Battery Capacity	1000mAh

Feature	Specification
Cable Length	1.6m
Backlight	Multicolor (18 effects)
Dimensions (L x W x H)	340.2 x 108 x 35.2mm (13.39 x 4.25 x 1.39 inches)
Weight	810g (1.9 pounds)
Compatible Devices	Mac, PC, Laptop, Tablet, Smartphone, PS

68 Key Compact Layout

68キーコンパクトレイアウト

K680t retains the keys commonly used in games, and it will give you more space for right mouse activity.

ゲームで一般的に使用されるキーを保持します、そしてそれはあなたに右マウスの活動のためのより多くのスペースを与えるでしょう。



Mini size is 34x10.8x3.5cm(13.4x4.25x1.4 inch), which simplifies the layout, takes into account the practicability, supports the lock of Win key, and is quick to operate.

ミニサイズは34x11x3.5cm(13.4x4.25x1.4 inch)で、レイアウトを簡素化し、実用性を考慮し、Winキーのロックをサポートし、操作が簡単です。

Image: A diagram illustrating the compact 68-key layout of the K680T keyboard with its precise dimensions, emphasizing its space-saving design.

Maintenance

To ensure the longevity and optimal performance of your Lomiluskr K680T keyboard, follow these maintenance guidelines:

- **Cleaning:** Regularly clean the keyboard with a soft, dry cloth. For deeper cleaning, use a can of compressed air to remove dust and debris from between the keycaps.
- **Keycap Removal:** Use the provided keycap puller to carefully remove keycaps for thorough cleaning or switch replacement. Avoid using excessive force to prevent damage.
- **Liquid Spills:** In case of liquid spills, immediately disconnect the keyboard from your device. Turn it upside down to drain any liquid and allow it to dry completely before reconnecting. Do not use a hairdryer as excessive heat can damage components.
- **Storage:** Store the keyboard in a cool, dry place away from direct sunlight and extreme temperatures.

Troubleshooting

If you encounter any issues with your K680T keyboard, please refer to the following common troubleshooting steps:

- **Keyboard Not Responding (Wired):**
 - Ensure the USB Type-C cable is securely connected to both the keyboard and your computer.
 - Try connecting the keyboard to a different USB port on your computer.
 - Test the keyboard on another computer to rule out system-specific issues.
- **Keyboard Not Connecting (Bluetooth):**
 - Ensure the switch on the bottom of the keyboard is set to "BT" mode.
 - Verify that Bluetooth is enabled on your device.
 - Make sure the keyboard is in pairing mode (FN+P, indicator flashing).
 - Delete any previous pairings of the keyboard from your device's Bluetooth settings and attempt to pair again.
 - Ensure the keyboard battery has sufficient charge.
- **Backlight Not Working/Incorrect:**
 - Check if the backlight is turned off (FN + ↓ multiple times).
 - Cycle through backlight effects using FN + → or FN + ←.
 - Ensure the keyboard battery is charged, as low battery can affect backlight functionality.
- **Keys Not Registering:**
 - Clean around the affected key to remove any debris.
 - If a specific key is consistently not working, it might indicate a switch issue.

Warranty and Support

The Lomiluskr K680T Mechanical Keyboard comes with a standard manufacturer's warranty. For specific warranty terms and conditions, please refer to the documentation provided with your purchase or contact the seller directly.

For technical support, troubleshooting assistance, or any inquiries regarding your product, please contact Lomiluskr customer service through the platform where you purchased the product or visit the official Lomiluskr support channels if available.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question