

Millennium Lighting 9332-SN

Millennium Lighting 9332-SN Traditional Vanity Light Instruction Manual

Model: 9332-SN

INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Millennium Lighting 9332-SN Traditional Vanity Light. Please read all instructions carefully before beginning installation and retain this manual for future reference.

The Millennium Lighting 9332-SN is a two-light vanity fixture designed for indoor use, featuring a satin nickel finish and metal construction. It is suitable for damp locations and is UL listed for safety.



Image: The Millennium Lighting 9332-SN Traditional Vanity Light, showcasing its satin nickel finish and two frosted glass shades.

IMPORTANT SAFETY INSTRUCTIONS

WARNING: Risk of electric shock. Disconnect power at the fuse box or circuit breaker before installation or servicing.

- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Contact a qualified electrician if you are unfamiliar with proper electrical wiring connections.
- Use only UL or ETL listed wire connectors.
- This product is intended for indoor use only.
- Do not exceed the maximum wattage specified for the light bulbs.
- **Proposition 65 Warning:** This product may contain chemicals known to the State of California to cause cancer, birth defects, or other reproductive harm. Wash hands after handling.

PACKAGE CONTENTS

Carefully unpack your fixture and check that all parts are included. If any parts are missing or damaged, do not attempt to assemble or install the fixture.

- Light Fixture Assembly (1)
- Glass Shades (2)
- Mounting Hardware Kit (includes mounting strap, outlet box screws, wire connectors, ground screw) (1)

SETUP AND INSTALLATION

Tools Required (Not Included)

- Phillips Head Screwdriver
- Flat Head Screwdriver
- Wire Strippers
- Pliers
- Electrical Tape

Step-by-Step Installation

1. **Turn Off Power:** Before starting installation, ensure the power to the electrical outlet box is turned off at the circuit breaker or fuse box.
2. **Prepare Mounting Strap:** Attach the mounting strap to the outlet box using the provided outlet box screws. Ensure the strap is securely fastened.
3. **Make Electrical Connections:**
 - Connect the bare copper ground wire from the fixture to the ground wire from the outlet box (usually bare copper or green) using a wire connector. Secure the ground wire to the mounting strap with the green ground screw.
 - Connect the white wire from the fixture to the white (neutral) wire from the outlet box using a wire connector.
 - Connect the black wire from the fixture to the black (hot) wire from the outlet box using a wire connector.
 - Wrap all wire connections with electrical tape for added security.
4. **Mount Fixture:** Carefully tuck all wires into the outlet box. Align the fixture's backplate with the

mounting strap and secure it with the provided mounting screws.

- Install Light Bulbs:** Insert the recommended light bulbs (not included) into the sockets. Do not exceed 100 watts per bulb.
- Attach Glass Shades:** Secure the glass shades to the fixture according to the specific design (e.g., by threading a ring or using set screws). Ensure they are snug but do not overtighten.
- Restore Power:** Once installation is complete, restore power at the circuit breaker or fuse box.

OPERATING INSTRUCTIONS

The Millennium Lighting 9332-SN vanity light operates via a standard wall switch (not included). Once installed and power is restored, use the wall switch to turn the light fixture on or off.

- Bulb Type:** This fixture requires two incandescent or compatible LED bulbs.
- Wattage:** Each bulb socket supports a maximum of 100 watts. Do not exceed this limit to prevent overheating and potential damage.

MAINTENANCE

Care and Cleaning

- Always disconnect power before cleaning.
- To clean the fixture, wipe it with a soft, dry cloth.
- Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.
- Clean glass shades with a mild glass cleaner and a soft cloth.

Bulb Replacement

- Ensure power is off at the circuit breaker before replacing bulbs.
- Allow bulbs to cool completely before touching them.
- Unscrew the old bulb and screw in a new bulb of the same type and wattage (max 100W).

TROUBLESHOOTING GUIDE

Problem	Possible Cause	Solution
Fixture does not light	1. Power is off 2. Faulty bulb 3. Incorrect wiring	1. Check circuit breaker/fuse 2. Replace bulb 3. Verify wiring connections (consult electrician if unsure)
Bulbs burn out quickly	1. Incorrect bulb wattage 2. Voltage fluctuations	1. Use bulbs within specified wattage (max 100W) 2. Consult electrician to check household voltage
Light flickers	1. Loose bulb 2. Loose wiring connection	1. Tighten bulb 2. Check and secure wiring connections (power off first)

PRODUCT SPECIFICATIONS

Specification	Detail
Brand	Millennium Lighting
Model Number	9332-SN
Finish	Satin Nickel
Material	Metal
Fixture Type	Vanity Light
Dimensions (H x W)	8.00 inches x 12.00 inches
Wattage (Max)	100 watts per socket
Power Source	Corded Electric
Safety Rating	Damp, UL Listed
Item Weight	5 pounds

WARRANTY AND SUPPORT


Warranty Information



This Millennium Lighting product is covered by a manufacturer's warranty. Please refer to the warranty documentation included with your purchase or contact Millennium Lighting directly for specific terms and conditions.

Customer Support

For technical assistance, missing parts, or warranty claims, please contact Millennium Lighting customer support. Contact information can typically be found on the product packaging or the manufacturer's official website.

Related Documents - 9332-SN

	<p>Millennium Lighting 60011 TRON LED Vanity Light - Specifications and Finishes</p> <p>Detailed specifications for the Millennium Lighting 60011 TRON LED Vanity Light, including dimensions, materials, lamping details, available finishes (Brushed Nickel, Chrome, Matte Black, Modern Gold), and certifications. Learn about this modern LED vanity fixture.</p>
--	---

 <p><i>"Making the Overall Affordable."</i></p>	<p>Millennium Lighting 9605 Moven 5-Light Chandelier - Matte Black, Rubbed Bronze, Satin Nickel</p> <p>Explore the Millennium Lighting 9605 Moven 5-Light Chandelier. Featuring elegant design, handcrafted seeded glass, and available in Matte Black, Rubbed Bronze, or Satin Nickel finishes. Specifications include dimensions, wattage, and UL/CUL listing.</p>
 <p><i>"Making the Overall Affordable."</i></p>	<p>Millennium Lighting 2804 Amberle 4-Light Vanity Fixture Specifications</p> <p>Detailed specifications for the Millennium Lighting 2804 Amberle 4-Light Vanity fixture, including dimensions, finishes (Brushed Nickel, Matte Black), material, glass type, wattage, and UL certification. Product model numbers 2804 BN and 2804 MB.</p>
 <p><i>"Making the Overall Affordable."</i></p>	<p>Millennium Lighting 9704 Ashford 4-Light Vanity Fixture Specifications</p> <p>Detailed specifications for the Millennium Lighting 9704 Ashford 4-Light Vanity fixture, featuring goblet-style clear glass globes and available in multiple finishes including brushed nickel, chrome, matte black, Modern Gold, and rubbed bronze.</p>
 <p><i>Timeless Lighting For Any Space</i> </p>	<p>Millennium Lighting 6203 Knightsdale Three Light Sconce - Specifications</p> <p>Detailed specifications for the Millennium Lighting 6203 Knightsdale Three Light Sconce, including dimensions, finishes (Chrome, Matte Black, Modern Gold), material, lamping details, and certifications. Perfect for adding timeless lighting to any space.</p>
 <p><i>Timeless Lighting For Any Space</i> </p>	<p>Millennium Lighting 6202 Knightsdale Two Light Sconce - Product Specifications</p> <p>Detailed specifications for the Millennium Lighting 6202 Knightsdale Two Light Sconce, including dimensions, finish options (Chrome, Matte Black, Modern Gold), material, lamping details, and certifications. Ideal for interior lighting applications.</p>