

DXQ IP 1080P

LSC Smart Connect Smart Video Indoor IP Camera User Manual

Model: IP 1080P

Brand: DXQ (LSC Smart Connect)

1. INTRODUCTION

This user manual provides comprehensive instructions for the installation, operation, and maintenance of your LSC Smart Connect Smart Video Indoor IP Camera. Please read this manual thoroughly before using the product to ensure proper functionality and safety. This camera is designed for indoor surveillance, offering high-definition video monitoring and two-way audio communication.



Figure 1: LSC Smart Connect Indoor IP Camera

This image displays the LSC Smart Connect Indoor IP Camera. It is a compact, white device with a black circular lens housing on top of a slender stand, which connects to a flat, round base. The camera is designed for discreet indoor placement.

2. PACKAGE CONTENTS

Verify that all items listed below are included in your package. If any items are missing or damaged, please contact your retailer.

- LSC Smart Connect Indoor IP Camera
- USB Cable
- Power Adapter
- User Manual (this document)

Note: A Micro SD card for local storage is not included and must be purchased separately if desired.



Figure 2: Product Packaging

This image shows the retail packaging for the LSC Smart Connect Smart Indoor IP Camera. The box is predominantly blue and white, featuring an image of the camera and a smartphone screen displaying the camera's live feed. Key features like "WIFI 2.4GHz" and "1080p HD" are prominently displayed.

3. PRODUCT FEATURES

The LSC Smart Connect Indoor IP Camera offers a range of features for effective home monitoring:

- **1080p HD Video Quality:** Capture clear and detailed video footage.
- **2.4 GHz Wi-Fi Connectivity:** Easy integration with your existing home Wi-Fi network.
- **Wide Viewing Angle:** A 105° viewing angle provides broad coverage of your indoor space.
- **10m Night Vision:** Monitor your home effectively even in low-light or complete darkness.
- **Two-Way Audio:** Communicate with individuals near the camera using the built-in microphone and speaker.
- **Micro SD Card Support:** Supports up to 128GB Micro SD card for local video storage (card not included).
- **LSC Smart Connect App Control:** Full control and monitoring via the dedicated LSC Smart Connect mobile application.
- **Motion Detection:** Receive alerts and record footage when motion is detected.

4. SAFETY INFORMATION

Please observe the following safety precautions to prevent damage to the product or injury to yourself:

- Do not expose the camera to water or moisture. This product is for indoor use only.
- Do not attempt to disassemble or modify the camera. Unauthorized repairs will void the warranty.
- Use only the provided power adapter and USB cable.

- Keep the camera away from direct sunlight, heat sources, and strong magnetic fields.
- Ensure the camera is placed on a stable surface or securely mounted to prevent falling.
- Keep out of reach of children and pets.

5. SETUP GUIDE

5.1. Prepare for Setup

1. **Download the App:** Search for "LSC Smart Connect" in your smartphone's app store (iOS or Android) and download the application.
2. **Create an Account:** Open the LSC Smart Connect app and register for a new account or log in if you already have one.
3. **Power On:** Connect the USB cable to the camera and the power adapter, then plug the adapter into a power outlet. The camera's indicator light will turn on, indicating it is powered.
4. **Wi-Fi Network:** Ensure your smartphone is connected to a 2.4 GHz Wi-Fi network. The camera does not support 5 GHz Wi-Fi.

5.2. Add Device to App

5. In the LSC Smart Connect app, tap the "+" icon or "Add Device" to begin pairing.
6. Select "Security & Video Surveillance" or "Camera" from the device list.
7. Follow the on-screen instructions to put the camera into pairing mode. This usually involves pressing a reset button on the camera until an indicator light flashes.
8. Enter your 2.4 GHz Wi-Fi network name (SSID) and password when prompted by the app.
9. The app will generate a QR code. Hold your smartphone screen with the QR code in front of the camera lens (approx. 15-20 cm away) until you hear a confirmation sound from the camera.
10. Once the camera connects, it will appear in your device list in the app. You can then rename the camera for easy identification.

5.3. Mounting the Camera

The camera can be placed on a flat surface or mounted to a wall using a wall mount bracket (not included, but compatible with the camera's design). Choose a location that provides the desired viewing angle and is within range of your Wi-Fi network.

- **Tabletop Placement:** Simply place the camera on a stable, flat surface.
- **Wall Mounting:** If using a wall mount bracket, ensure it is securely fastened to the wall before attaching the camera. Position the camera to cover the desired area.

6. OPERATING INSTRUCTIONS

6.1. Live View

Open the LSC Smart Connect app and tap on the camera's name in your device list to access the live video feed. You can view the real-time footage from anywhere with an internet connection.

6.2. Two-Way Audio

While in live view, tap the microphone icon to speak through the camera's speaker. Tap the speaker icon to listen to audio from the camera's surroundings.

6.3. Recording and Playback

- **Manual Recording:** Tap the record icon in the live view interface to start/stop manual recording. Recordings will be saved to your phone or the inserted Micro SD card.
- **Motion-Activated Recording:** Enable motion detection in the camera settings. The camera will automatically record when

motion is detected.

- **Playback:** Access recorded footage via the "Playback" or "History" section in the app. Select the date and time to review events.

6.4. Night Vision

The camera automatically switches to night vision mode in low-light conditions, providing clear black-and-white images up to 10 meters.

6.5. Settings

Access camera settings through the gear icon in the app. Here you can configure:

- Motion detection sensitivity and alert settings.
- Video quality.
- Micro SD card management (format, recording mode).
- Device sharing with other users.

7. MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the camera lens and body. Do not use liquid cleaners or abrasive materials.
- **Software Updates:** Regularly check the LSC Smart Connect app for firmware updates. Keeping your camera's firmware up-to-date ensures optimal performance and security.
- **Power Cycle:** If the camera becomes unresponsive, unplug it from the power source for 10 seconds, then plug it back in.

8. TROUBLESHOOTING

Problem	Possible Cause / Solution
Camera fails to connect to Wi-Fi.	<ul style="list-style-type: none">• Ensure your Wi-Fi network is 2.4 GHz. 5 GHz networks are not supported.• Check Wi-Fi password for correctness.• Move the camera closer to the Wi-Fi router.• Reset the camera and try pairing again.
Poor video quality or lag.	<ul style="list-style-type: none">• Check your internet connection speed.• Reduce video quality settings in the app.• Ensure strong Wi-Fi signal at the camera's location.
Two-way audio not working.	<ul style="list-style-type: none">• Ensure microphone and speaker permissions are granted to the app on your smartphone.• Check volume settings on your phone and in the app.• Ensure there are no obstructions blocking the camera's microphone or speaker.
Micro SD card not recognized.	<ul style="list-style-type: none">• Ensure the card is inserted correctly.• Format the Micro SD card using the option in the LSC Smart Connect app.• Try a different Micro SD card (ensure it's Class 10 or higher).

9. SPECIFICATIONS

Feature	Detail
Model Number	IP 1080P
Video Recording Resolution	1080p HD
Wireless Communication Technology	Wi-Fi (2.4 GHz only)
Viewing Angle	105 degrees
Night Vision Range	10 meters
Audio	Two-way audio
Memory Capacity (Micro SD)	Up to 128 GB (card not included)
Material	Metal
Power	10 Watts
Dimensions (L x W x H)	6 x 6 x 10 cm
Weight	150 grams
Recommended Use	Indoor surveillance, Night Vision
Compatible Devices	Smartphone (iOS, Android)
Mounting Type	Wall mount bracket compatible

10. WARRANTY AND SUPPORT

Specific warranty information for this product is not provided in the available product details. For warranty claims, technical support, or further assistance, please contact the retailer where you purchased the product or refer to the official LSC Smart Connect website for support resources.

Always retain your proof of purchase for warranty purposes.