

GEEKVAPE Aegis Mini 2 (M100)

GeekVape M100 Aegis Mini 2 Kit User Manual

Model: Aegis Mini 2 (M100) | Brand: GEEKVAPE

1. INTRODUCTION

Welcome to the user manual for your GeekVape M100 Aegis Mini 2 Kit. This device is a powerful and durable e-cigarette vaporizer designed for an optimal vaping experience. It features a robust 2500mAh internal battery, capable of delivering up to 100W of power, and is paired with the GeekVape Z Nano 2 Tank, compatible with GeekVape B Series Coils.

The M100 Aegis Mini 2 is built with advanced durability, boasting an IP68 rating for water and dust resistance, along with innovative shock resistance. Its A-lock design prevents accidental firing, ensuring a stable and safe output. The device also features a clear 1.08-inch full screen display for easy operation and monitoring.

Important Safety Note: This product does not contain nicotine or tobacco. Sale is prohibited to persons under 18 years of age. By ordering this product, you certify that you are over 18 years old.

2. PACKAGE CONTENTS

Please check the box for the following items:

- 1 x GeekVape M100 Aegis Mini 2 Mod
- 1 x GeekVape Z Nano 2 Tank (3.5ml)
- 1 x GeekVape B Series 0.2ohm Coil (Pre-installed)
- 1 x GeekVape B Series 0.6ohm Coil (Spare)
- 1 x Drip Tip
- 1 x Coil Tool
- 1 x Spare Parts Pack
- 1 x Spare Glass Tube
- 1 x USB Type-C Cable



Image: The GeekVape M100 Aegis Mini 2 Kit, its packaging, and all included accessories laid out.

3. PRODUCT OVERVIEW

Familiarize yourself with the main components of your GeekVape M100 Aegis Mini 2 Kit.



Image: Front view of the assembled GeekVape M100 Aegis Mini 2 Kit in classic black.



Image: Close-up view of the 510 connection point on the mod and the base of the Z Nano 2 Tank.



Image: A detailed view of the 1.08-inch full screen display showing power, resistance, amperage, voltage, and puff counter.



Image: Several GeekVape B Series Coils, highlighting their mesh design and resistance markings.

4. SETUP GUIDE

4.1. Installing the Coil

1. Unscrew the base of the Z Nano 2 Tank from the main tank section.

2. Carefully push the GeekVape B Series Coil into the designated slot in the tank base. Ensure it is seated firmly.
3. **Prime the Coil:** Before reassembling, apply a few drops of e-liquid to the cotton wicking ports of the new coil. This saturates the cotton and prevents dry hits.
4. Screw the tank base back onto the tank section.

4.2. Filling the E-liquid

1. Locate the top cap of the Z Nano 2 Tank.
2. Twist the top cap a quarter turn counter-clockwise to remove it, revealing the fill ports.
3. Insert the nozzle of your e-liquid bottle into one of the fill ports (avoid the center airflow hole).
4. Slowly fill the tank with e-liquid up to the maximum fill line.
5. Replace the top cap by aligning it and twisting clockwise until secure.
6. **Important:** After filling a new coil, let the tank stand upright for at least 5-10 minutes to allow the e-liquid to fully saturate the coil. This prevents burning the coil.

4.3. Charging the Device

1. Locate the Type-C charging port on the side of the M100 Mod, usually protected by a silicone flap.
2. Open the silicone flap.
3. Connect the provided USB Type-C cable to the device and the other end to a 5V/2A wall adapter or a compatible USB port.
4. The screen will display the charging status. The battery icon will indicate charging progress.
5. Once fully charged, disconnect the cable and close the silicone flap to maintain IP68 rating.



Image: Close-up of the GeekVape M100 Mod showing the Type-C charging port with its protective cover open.

5. OPERATING INSTRUCTIONS

5.1. Power On/Off

- To turn the device **ON**: Press the fire button 5 times rapidly within 2 seconds. The screen will light up.
- To turn the device **OFF**: Press the fire button 5 times rapidly within 2 seconds. The screen will display "System Off".

5.2. Adjusting Wattage

- Once the device is on, use the "+" and "-" adjustment buttons located below the screen to increase or decrease the wattage.
- The wattage range is typically 5W to 100W. Adjust according to your coil's recommended wattage range for optimal performance and coil longevity.

5.3. A-Lock Function

- The M100 features an A-lock switch on the side of the device.
- Slide the switch **down** to lock the device, preventing accidental presses and firing. This is useful when carrying the device in a pocket or bag.
- Slide the switch **up** to unlock the device and resume normal operation.

5.4. Vaping

- With the tank filled and coil primed, and the device powered on and unlocked, press and hold the fire button while inhaling from the drip tip.
- Release the fire button when you finish inhaling.

6. MAINTENANCE

6.1. Coil Replacement

- Coils typically need to be replaced every 1-2 weeks, depending on usage and e-liquid type.
- A burnt taste, reduced vapor production, or diminished flavor are signs that the coil needs replacement.
- Follow the steps in Section 4.1 to replace the coil.

6.2. Tank Cleaning

- To clean the tank, disassemble it by removing the top cap, glass tube, and coil.
- Rinse all components (except the coil) with warm water. For a deeper clean, use a mild dish soap and rinse thoroughly.
- Ensure all parts are completely dry before reassembling.

6.3. Device Cleaning

- Wipe the mod body with a soft, damp cloth to remove any dust or e-liquid residue.
- Keep the charging port clean and free of debris.
- Do not submerge the entire device in water, despite its IP68 rating, unless specifically instructed for cleaning. The rating is for accidental exposure.

7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Device not turning on	Low battery; Device off; Faulty device	Charge the device; Press fire button 5 times rapidly; Contact support if issue persists.
No vapor production	Coil not installed correctly; No e-liquid; Low battery; Wattage too low; Coil burnt out	Ensure coil is seated; Fill tank; Charge device; Increase wattage; Replace coil.

Problem	Possible Cause	Solution
Burnt taste	Coil not primed; Coil burnt out; E-liquid level too low; Wattage too high	Prime new coil; Replace coil; Refill tank; Reduce wattage.
E-liquid leaking from tank	Coil not installed correctly; O-rings damaged/missing; Tank overfilled; Airflow not closed during filling	Reinstall coil; Check/replace O-rings; Do not overfill; Ensure top cap is secure.
"Atomizer Short" or "No Atomizer" error	Coil not making contact; Faulty coil; Tank not screwed on properly	Reseat coil; Try a new coil; Ensure tank is screwed on firmly but not overtightened.

8. SPECIFICATIONS

Feature	Detail
Brand	GEEKVAPE
Model	Aegis Mini 2 (M100) Kit
Color	Classic Black (Noir Classique)
Dimensions (L x W x H)	30 x 10 x 70 mm (approximate for mod)
Weight	100 Grams (approximate)
Battery Capacity	2500 mAh (Internal)
Output Wattage	Max 100 Watts
Charging Port	Type-C, 5V/2A
Tank Volume	3.5 Milliliters (Z Nano 2 Tank)
Coil Compatibility	GeekVape B Series Coils
Display Screen	1.08 inch Full Screen
Durability Rating	IP68 Water & Dust Resistance, Shock Resistance



Image: The GeekVape M100 Aegis Mini 2 Kit being splashed with water, illustrating its IP68 water resistance.

9. SAFETY INFORMATION



Please read and adhere to the following safety guidelines to ensure safe operation of your device:

- Keep the device away from extreme temperatures, direct sunlight, and moisture (beyond its IP68 rating).
- Do not use damaged batteries or chargers.
- Do not disassemble the device beyond what is instructed in this manual.
- Keep out of reach of children and pets.
- Use only genuine GeekVape coils and accessories.
- Dispose of the device and its components responsibly according to local regulations.
- This product is intended for adult smokers and vapers only.

10. WARRANTY AND SUPPORT

For warranty information and customer support, please refer to the warranty card included in your package or visit the official GEEKVAPE website. If you encounter any issues not covered in this manual, please contact the retailer or manufacturer's customer service for assistance.

Please retain your proof of purchase for any warranty claims.

	<p>Geekvape Aegis Legend 2 L200 Mod User Manual</p> <p>Comprehensive user manual for the Geekvape Aegis Legend 2 L200 Mod, covering package contents, features, product parameters, detailed operating instructions, error indicators, troubleshooting, precautions, and authenticity verification methods.</p>
	<p>GEEKVAPE Aegis Mini 2 100W M100 Εγχειρίδιο Χρήσης</p> <p>Εγχειρίδιο χρήσης για το GEEKVAPE Aegis Mini 2 100W M100, με λεπτομέρειες για χαρακτηριστικά, προδιαγραφές, λειτουργία και προφυλάξεις ασφαλείας.</p>
	<p>GEEKVAPE S100 KIT (Aegis Solo 2) User Manual - Comprehensive Guide</p> <p>Official user manual for the GEEKVAPE S100 KIT (Aegis Solo 2). Learn about setup, operation, features, safety precautions, and customer support. Includes detailed instructions and product parameters.</p>
	<p>GeekVape Aegis Solo 3: Návod k použití a specifikace</p> <p>Podrobný návod k použití pro elektronickou cigaretu GeekVape Aegis Solo 3, včetně informací o funkcích, specifikacích, nabíjení a bezpečnostních pokynech.</p>
	<p>Geekvape Aegis S100 Kit User Manual and Instructions</p> <p>Comprehensive user manual for the Geekvape Aegis S100 Kit, detailing parts, assembly, operation, and customer service information. Includes instructions for use and authenticity verification.</p>
	<p>GEEKVAPE Aegis Legend 2 KIT User Manual</p> <p>Comprehensive user manual for the GEEKVAPE Aegis Legend 2 KIT, detailing product features, operation, safety guidelines, and specifications. Available in multiple languages.</p>