INIU BI-B62

INIU Portable Charger 45W Power Bank User Manual

Brand: INIU | Model: BI-B62

Introduction

This user manual provides detailed instructions for the safe and efficient use of your INIU Portable Charger 45W Power Bank. Please read this manual thoroughly before using the product and retain it for future reference.



Image: The INIU Portable Charger 45W Power Bank, featuring a sleek black design and a clear digital display showing battery percentage.

Setup

Package Contents

Verify that all items are present in the package:

- 1 x INIU 45W PD+QC Portable Charger
- 1 x USB-C to USB-A Cable
- 1 x Travel Pouch
- 1 x User Manual



Image: All items included in the INIU Portable Charger package: the power bank, a USB-C to USB-A cable, a travel pouch, and the user manual.

Initial Charging of the Power Bank

Before first use, fully charge your INIU Portable Charger. This ensures optimal battery performance and longevity.

1. Connect the provided USB-C to USB-A cable to the USB-C input/output port (IN/OUT1) on the power bank.
2. Connect the other end of the cable to a compatible USB wall charger (not included). For fastest recharge, use a

30W or higher power adapter.

3. The digital display on the power bank will show the charging percentage. It will display "100%" when fully charged.

A full recharge takes approximately 2.5 hours with a 30W charger.



Image: The INIU Portable Charger connected to a wall adapter via its USB-C port for recharging, illustrating the rapid recharge capability.

Operating Instructions

Charging Your Devices

The INIU Portable Charger features both USB-C (PD 45W) and USB-A (QC 22.5W) output ports for versatile and fast charging.

1. Connect your device's charging cable to the appropriate output port on the power bank (USB-C or USB-A).
2. Connect the other end of the cable to your device.
3. The power bank will automatically begin charging your device. The digital display will show the remaining battery percentage.

Simultaneous Charging: The exclusive SmartSplit technology allows for efficient simultaneous charging of two devices. When both ports are in use, the USB-C port provides up to 25W and the USB-A port provides up to 22.5W.



Image: The INIU Portable Charger connected to both a smartphone and a tablet, demonstrating its ability to charge two devices simultaneously with SmartSplit technology.

Digital Display and Flashlight

The integrated digital display provides a clear, real-time indication of the power bank's remaining battery percentage. To activate the built-in flashlight, double-press the power button located on the side of the power bank. Double-press again to turn it off.



Image: A detailed view of the INIU Portable Charger's ports (USB-C IN/OUT1 and USB-A OUT2) and the illuminated digital display showing battery percentage.

Device Compatibility

The INIU Portable Charger is designed for wide compatibility, supporting fast charging for a variety of devices including laptops, tablets, mobile phones, and small electronic devices. This includes, but is not limited to:

- Laptops (e.g., MacBook Air) with PD 45W

- Smartphones (e.g., iPhone 12-14 Series with PD 30W, Samsung S8 and later with PPS 25W, Android phones with QC 18W)
- Tablets (e.g., iPad Pro 4-7th Gen)
- Gaming devices (e.g., Steam Deck)
- Small devices (e.g., mini drones, GoPro, Smart Watches, AirPods)



Image: The INIU Portable Charger surrounded by various compatible devices, illustrating its broad charging capabilities for different electronics.

Maintenance

Proper maintenance ensures the longevity and performance of your power bank.

- **Cleaning:** Use a soft, dry cloth to clean the surface of the power bank. Avoid using harsh chemicals or abrasive materials.
- **Storage:** Store the power bank in a cool, dry place away from direct sunlight and extreme temperatures.
- **Battery Care:** For optimal battery health, fully charge the power bank at least once every three months if not in regular use. Avoid completely draining the battery for extended periods.
- **Handling:** Do not drop, disassemble, or attempt to repair the power bank yourself. This can void the warranty and pose safety risks.

Troubleshooting

If you encounter issues with your INIU Portable Charger, refer to the following common solutions:

Problem	Possible Cause	Solution
Power bank not charging	Loose cable connection, faulty cable/adapter, power bank battery depleted.	Ensure cables are securely connected. Try a different charging cable or wall adapter. Allow the power bank to charge for a few minutes to see if the display activates.
Device not charging from power bank	Loose cable connection, incompatible cable, power bank battery depleted, device not compatible.	Check cable connections. Use the original charging cable for your device. Ensure the power bank has sufficient charge. Verify device compatibility with the power bank's output specifications.
Slow charging	Cable not supporting fast charging, device not supporting fast charging, multiple devices charging simultaneously.	Use a high-quality cable that supports fast charging. Ensure your device supports PD or QC fast charging. Charging multiple devices simultaneously may reduce individual charging speeds.
Digital display not working	Power bank is off, internal malfunction.	Press the power button once to activate the display. If the issue persists, contact customer support.

For further assistance, please refer to the fullUser Manual (PDF) or contact INIU customer support.

Specifications

Feature	Detail
Model Number	BI-B62
Battery Capacity	15000 Milliamp Hours
Product Dimensions	5.67 x 2.76 x 0.87 inches
Item Weight	13.7 ounces
Connector Type	USB Type A (22.5W Max), USB Type C (45W Max)
Color	Black

Feature	Detail
Special Features	Built-in Holder, Digital Display, Smart-Split Design, Flashlight, Over Charging Protection



Image: The INIU Portable Charger with its physical dimensions (length, width, thickness) clearly indicated.

Warranty and Support

INIU stands behind the quality of its products. Your INIU Portable Charger comes with an industry-leading **3-year refresh care** and a **3 Years Replacement Promise**.

For technical support, warranty claims, or any inquiries, please refer to the contact information provided in the official user manual PDF or visit the INIU official website.

You can download the full user manual here:INIU Portable Charger User Manual (PDF)

© 2024 INIU. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question