Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

Lemorele TC38

Lemorele 8-in-1 USB C Multiport Hub User Manual

Model: TC38

1. Product Overview

The Lemorele 8-in-1 USB C Multiport Hub is a versatile and compact adapter designed to expand the connectivity of your USB-C enabled devices. It transforms a single USB-C port into multiple essential ports, including HDMI, USB 3.0, SD/TF card readers, and USB-C Power Delivery and data ports, enhancing your productivity and entertainment experience.



Figure 1: Lemorele 8-in-1 USB C Multiport Hub with various connections.

This hub is an ideal solution for modern laptops and devices with limited port options, providing seamless integration for external monitors, USB peripherals, and memory cards.

2. Features and Ports

The Lemorele 8-in-1 USB C Multiport Hub offers a comprehensive set of ports to meet your connectivity needs:

- **3 x USB 3.0 Ports:** Experience data transfer speeds up to 5Gbps, which is 10 times faster than USB 2.0. Ideal for connecting external hard drives, USB flash drives, keyboards, and mice.



Figure 2: USB 3.0 ports offering high-speed data transfer.

- **1 x HDMI 4K Port:** Connect to an external monitor, TV, or projector to extend or mirror your display in stunning 4K Ultra HD resolution at 30Hz (compatible with 1080P@60Hz and other resolutions).
- **1 x SD Card Slot & 1 x TF Card Slot:** Read and write data from SD and TF (Micro SD) cards simultaneously with speeds up to 104 MB/s, perfect for photographers and videographers.



Figure 3: SD and TF card slots for quick data access.

- **1 x USB-C Power Delivery (PD) Port:** Supports up to 100W power input, allowing you to charge your laptop or connected devices while using the hub.
- **1 x USB-C Data Port:** Dedicated USB-C port for data transfer, complementing the USB-A data ports.



Figure 4: Power Delivery and USB-C data transfer in action.

3. Compatibility

This USB C adapter is widely compatible with various operating systems and devices that support USB-C video output (DP Alt Mode or Thunderbolt 3/4). Ensure your device's USB-C port supports these features for full functionality.

Compatible Operating Systems:

- Windows (Full Range, including 7/8/10/11)
- macOS (including M1/M2/M3 chips)
- Android
- iOS
- Linux
- Chrome OS

Compatible Devices (Examples):

- **Laptops:** MacBook Pro/Air (M1, M2, M3), iMac, Dell XPS, Asus Ling Yao, HP EliteBook, Lenovo ThinkPad, Microsoft Surface Book, Google PixelBook, Xiaomi Air, Honor MagicBook, Razer Spirit Blade.
- **Tablets:** iPad Pro/Air (M1, M2).
- **Gaming Consoles:** SteamDeck, Nintendo Switch, Xbox, PS4.
- **Streaming Devices:** Chromecast with Google TV.
- **Smartphones:** Huawei (P40, Mate series), Samsung (S8/S9/S10, Note9), OPPO R17 Pro.
- **Peripherals:** Keyboards, Mice, USB drives, card readers, monitors, projectors.



Figure 5: Broad compatibility with various devices.

4. Setup Guide

The Lemorele 8-in-1 USB C Multiport Hub is designed for plug-and-play functionality, requiring no additional software or drivers for most operating systems.

Basic Connection:

1. Connect the USB-C cable of the hub to an available USB-C port on your host device (laptop, tablet, smartphone, etc.).
2. Connect your desired peripherals (monitor, USB drives, SD/TF cards, etc.) to the corresponding ports on the hub.
3. If charging your host device, connect your power adapter to the USB-C PD port on the hub. It is highly recommended to connect your power adapter to the PD port before connecting other high-power devices to ensure sufficient power supply. The connected PD adapter should be greater than 40W.

Display Modes (HDMI):

When connecting an external monitor via the HDMI port, you can configure your display settings for either Mirror Mode or Extend Mode.



Figure 6: Mirror Mode and Extend Mode display configurations.

- **macOS:**

- *Mirror Mode:* Apple Menu > System Preferences > Displays > Arrangement > Check 'Mirror Displays'.
- *Extend Mode:* Apple Menu > System Preferences > Displays > Arrangement > Uncheck 'Mirror Displays'.

- **Windows:**
  - *Mirror Mode:* Settings > System > Display > Multiple Displays (or press Win + P > PROJECT > Duplicate).
  - *Extend Mode:* Settings > System > Display > Multiple Displays (or press Win + P > PROJECT > Extend).

5. Operating Instructions

Once connected, the hub operates automatically. Here are some key operational considerations:

- **USB Data Transfer:** Simply plug your USB devices into the USB 3.0 ports or the USB-C data port. Files can be dragged and dropped between your device and the connected storage.
- **Card Reader Usage:** Insert your SD or TF card into the respective slot. The card will appear as a removable drive on your computer, allowing you to access and manage files.
- **Power Consumption:** Each USB-A port supports a maximum of 7.5W (5V 1.5A). USB peripherals requiring more than 7.5W are not supported. It is recommended to connect only one hard drive/SSD at a time due to limited power output.

6. Maintenance and Care

To ensure the longevity and optimal performance of your Lemorele 8-in-1 USB C Multiport Hub, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry cloth to clean the hub. Avoid using liquid cleaners or aerosols, as they may damage the device.
- **Storage:** Store the hub in a cool, dry place away from direct sunlight and extreme temperatures.
- **Handling:** Handle the hub with care. Avoid dropping it or subjecting it to strong impacts.
- **Heat Dissipation:** The aluminum casing of the hub is designed to dissipate heat and protect the internal circuit board. It is normal for the casing to warm up during operation, with temperatures typically remaining below 52°C.
- **Port Protection:** Avoid forcing connectors into ports. Ensure correct orientation and gentle insertion.

7. Troubleshooting

If you encounter issues with your Lemorele 8-in-1 USB C Multiport Hub, please refer to the following common problems and solutions:

- **HDMI Output Not Working:**
  - Ensure your laptop's USB-C source port is Thunderbolt 3/4 compatible or supports DP Alt Mode.
  - Verify that the HDMI cable is securely connected to both the hub and the display.
  - Try a different HDMI cable or monitor to rule out external issues.
  - For Windows 11, ensure you have the latest drivers installed for your laptop's Type-C port.

- **Devices Not Charging/Power Issues:**
  - Ensure your power adapter connected to the hub's PD port is at least 40W.
  - Connect the power adapter to the hub before connecting other high-power devices.
  - The hub's USB-A ports support a maximum of 7.5W. Devices requiring more power may not function correctly.

- Only connect one hard drive/SSD at a time to avoid power limitations.

- **Nintendo Switch Display Issues:**
  - Ensure the Nintendo Switch is powered (at least 5V2A) when connecting via the hub for display output.
- **Incompatibility with Specific Devices:**
  - The hub is not compatible with Apple USB SuperDrive, Samsung T7 hard drive, and MacBook Pro 2021 (M1 Pro chip).
- **Wireless Interference:**
  - Some users have reported interference with high-end wireless headphones and mice. If this occurs, try connecting these devices directly to your computer or using separate USB inputs if possible.

8. Specifications

Feature	Specification
Brand	Lemorele
Model Number	TC38
Color	BLACK
Material	Aluminum
Dimensions (L x W x H)	13.5 x 4.1 x 1.2 cm
Operating Systems	Windows, macOS, Linux
Interface	USB Type C
Special Features	Plug and Play
Data Transfer Rate	5 Gbps (USB 3.0)
Total Ports	8 (3x USB 3.0, 1x HDMI 4K, 1x SD Card, 1x TF Card, 1x USB-C PD, 1x USB-C Data)
Compatible Devices	Keyboards, Mice, USB Drives, Desktop Computers, Laptops, Card Readers, Monitors, Projectors, Smartphones, Tablets
Manufacturer	Lemorele
Country of Origin	China

9. Warranty and Support

Lemorele is committed to providing high-quality products and excellent customer service. Your purchase is backed by a 100% money-back guarantee, lifetime return and exchange policy.

For any inquiries or assistance, please contact our 24-hour online manual customer service. We are always here to help.

You can also visit the official Lemorele store for more information and products:Lemorele Store

© 2024 Lemorele. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B09GLR39RK

More documents and user manuals: **https://manuals.plus/**