

[Manuals.plus](#) /

› [Beghelli](#) /

› Beghelli Smart Dom-e E27 14W RGB-CCT WiFi LED Bulb User Manual

Beghelli 60012

Beghelli Smart Dom-e E27 14W RGB-CCT WiFi LED Bulb User Manual

Model: 60012

INTRODUCTION

Thank you for choosing the Beghelli Smart Dom-e E27 14W RGB-CCT WiFi LED Bulb. This smart bulb offers advanced lighting control, including adjustable color temperature (warm to cool white), millions of RGB colors, and dimming capabilities. It integrates seamlessly with your home Wi-Fi network and can be controlled via the dedicated Dom-e app or voice assistants like Amazon Alexa and Google Assistant. This manual provides essential information for safe installation, setup, operation, and maintenance of your smart bulb.



Image: The Beghelli Smart Dom-e E27 14W RGB-CCT WiFi LED Bulb, illustrating its ability to display a wide range of colors

and white light options. It features an E27 base and provides 1400 lumens of light output.

IMPORTANT SAFETY INFORMATION

- **Read all instructions:** Before installation and use, carefully read and understand all instructions.
- **Indoor Use Only:** This bulb is designed for indoor use in dry locations. Do not expose to water or moisture.
- **Power Off Before Installation:** Always turn off the power to the light fixture at the circuit breaker before installing or removing the bulb.
- **Correct Base Type:** Ensure the light fixture has an E27 base. Do not force the bulb into an incompatible socket.
- **Operating Temperature:** Do not install in enclosed fixtures that restrict airflow, as this may reduce bulb lifespan.
- **Dimmer Compatibility:** This smart bulb is dimmable via the app or voice control. Do not use with external dimmer switches, as this may cause damage.
- **Cleaning:** Clean the bulb with a soft, dry cloth. Do not use liquid cleaners.
- **Disposal:** Dispose of the bulb according to local regulations for electronic waste.

SETUP GUIDE

1. Physical Installation

1. **Turn off power:** Ensure the power to the light fixture is switched off at the main circuit breaker before proceeding.
2. **Screw in the bulb:** Carefully screw the Beghelli Smart Dom-e E27 bulb into a standard E27 light socket. Do not overtighten.
3. **Restore power:** Turn the power back on at the circuit breaker. The bulb should light up briefly, indicating it's ready for pairing.



Modifica la temperatura, il colore e l'intensità della luce

Image: A person demonstrating the easy physical installation of the smart bulb into a standard lamp fixture.

2. App Download and Connection

The Beghelli Smart Dom-e bulb requires the free Dom-e app for full functionality. Ensure your smartphone is connected to a 2.4 GHz Wi-Fi network.

1. **Download the Dom-e App:** Search for "Dom-e" in the Apple App Store (for iOS 8.0 or later) or Google Play Store (for Android 4.2 or later) and download the application.
2. **Register/Log In:** Open the app and follow the on-screen instructions to create an account or log in.
3. **Add Device:** In the app, select the option to add a new device. Choose "Lighting" or "Smart Bulb" from the device list.
4. **Connect to Wi-Fi:** Follow the app's instructions to connect the bulb to your home 2.4 GHz Wi-Fi network. This usually involves putting the bulb into pairing mode (often by cycling power on/off a few times) and entering your Wi-Fi password in the app.
5. **Name the Bulb:** Once connected, you can assign a name to your bulb (e.g., "Living Room Light," "Bedroom Lamp") for easy identification and voice control.



Image: The product packaging illustrating the three simple steps for setup: download the app, connect to power, and configure via the app.



Image: A smartphone displaying the Dom-e app, prompting the user to add a new smart bulb device.

3. Voice Assistant Integration (Optional)

The Beghelli Smart Dom-e bulb is compatible with Amazon Alexa and Google Assistant for convenient voice control.

1. **Open Voice Assistant App:** Open the Amazon Alexa app or Google Home app on your smartphone.
2. **Enable Skill/Action:**

- For Alexa: Go to "Skills & Games" and search for "Dom-e". Enable the skill.
 - For Google Assistant: Go to "Works with Google" and search for "Dom-e". Link the service.
3. **Link Accounts:** You will be prompted to link your Dom-e account with your Alexa or Google account. Use the same credentials you used for the Dom-e app.
 4. **Discover Devices:** Once linked, ask your voice assistant to "Discover devices" or manually initiate device discovery in the app. Your Beghelli smart bulb should appear.



Image: Examples of Amazon Alexa and Google Assistant devices, highlighting the smart bulb's compatibility for voice control.

OPERATING INSTRUCTIONS

1. Basic On/Off Control

- **Via Dom-e App:** Open the Dom-e app, select your bulb, and tap the power icon to turn it on or off.
- **Via Voice Assistant:** Use commands like "Alexa, turn on [Bulb Name]" or "Hey Google, turn off [Bulb Name]".
- **Via Wall Switch:** The bulb can also be turned on/off using a standard wall light switch, functioning like a regular bulb. Note that frequent use of the wall switch may affect smart functionality or pairing state.

2. Adjusting Color and Brightness

The Beghelli Smart Dom-e bulb offers millions of colors (RGB) and adjustable white light temperature (CCT) from warm (2700K) to cool (6500K).

- **In the Dom-e App:**

- Select your bulb in the app.
- Use the color wheel or color temperature slider to select your desired light color or white shade.
- Adjust the brightness slider to set the desired intensity.

- **Via Voice Assistant:**

- "Alexa, set [Bulb Name] to blue."
- "Hey Google, change [Bulb Name] to warm white."
- "Alexa, dim [Bulb Name] to 50%."
- "Hey Google, make [Bulb Name] brighter."



Image: An illustration showing the difference between warm white (2700K) and cool white (6500K) light settings, both achievable with the smart bulb.



Installare le lampadine Smart è facile come una comune lampadina

Image: A visual representation of the smart bulb displaying a spectrum of RGB colors, demonstrating its ability to create different atmospheric lighting.

3. Scheduling and Scenes

The Dom-e app allows you to create schedules for automatic on/off times and set up custom lighting scenes.

- **Creating Schedules:** In the Dom-e app, navigate to the "Schedule" or "Timer" section for your bulb. Set specific times for the bulb to turn on or off, and choose the days of the week for the schedule to repeat.
- **Creating Scenes:** The app allows you to save specific color, brightness, and color temperature combinations as "Scenes" (e.g., "Movie Night," "Reading," "Party"). You can then activate these scenes with a single tap or voice command.

MAINTENANCE

- **Cleaning:** Ensure the bulb is off and cool before cleaning. Wipe the bulb with a soft, dry, lint-free cloth. Do not use abrasive cleaners, solvents, or liquid sprays directly on the bulb.
- **No User-Serviceable Parts:** The Beghelli Smart Dom-e LED bulb contains no user-serviceable parts. Do not attempt to disassemble or repair the bulb, as this will void the warranty and may cause electric shock.
- **Firmware Updates:** Periodically check the Dom-e app for any available firmware updates for your bulb.

These updates can improve performance, add new features, or fix bugs. Follow the app's instructions for updating.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Bulb does not turn on.	No power to the fixture; Bulb not screwed in properly; Bulb is faulty.	Check circuit breaker and wall switch. Ensure bulb is securely screwed into the socket. Test the bulb in another working fixture.
Bulb is not connecting to Wi-Fi/Dom-e app.	Incorrect Wi-Fi password; Not on 2.4 GHz network; Bulb not in pairing mode; Router too far.	Ensure correct Wi-Fi password. Confirm your phone is on a 2.4 GHz network. Cycle power to the bulb (on/off 3-5 times) to enter pairing mode. Move closer to the Wi-Fi router during setup.
Voice control is not working.	Voice assistant skill/action not enabled; Accounts not linked; Incorrect device name.	Verify the "Dom-e" skill/action is enabled and accounts are linked in your Alexa/Google Home app. Ensure you are using the correct bulb name in your commands. Try rediscovering devices.
Bulb is flickering or unresponsive.	Unstable Wi-Fi connection; Interference; Faulty bulb.	Check Wi-Fi signal strength. Restart your Wi-Fi router. Ensure no other devices are causing interference. If problem persists, contact customer support.

SPECIFICATIONS

Model Name	Smart Dom-e
Model Number	60012
Brand	Beghelli
Bulb Type	LED
Bulb Base	E27
Power Consumption	14 Watts
Incandescent Equivalent	80 Watts
Luminous Flux (White Brightness)	1055 Lumens

Light Color	RGB-CCT (Millions of colors, adjustable warm to cool white 2700K-6500K)
Color Rendering Index (CRI)	80
Beam Angle	200 Degrees
Connectivity Technology	Wi-Fi (IEEE802.11 b/g/n - 2.4 GHz)
Control Method	Dom-e Application, Voice Control (Amazon Alexa, Google Assistant)
Accepted Voltage Frequency	220-240 Volts, 50 Hertz
Rated Lifespan	25,620 Hours
Dimensions (L x W x H)	6 x 6 x 13.4 cm
Weight	90 grams
Material Type	Plastic
Energy Label	A+
Operating System Compatibility	iOS 8.0 or later, Android 4.2 or later

WARRANTY INFORMATION

Beghelli products are manufactured to high-quality standards. For specific warranty terms and conditions, please refer to the warranty card included with your product or visit the official Beghelli website. Keep your purchase receipt as proof of purchase for any warranty claims.

CUSTOMER SUPPORT

If you encounter any issues or have questions regarding your Beghelli Smart Dom-e LED Bulb that are not covered in this manual, please contact Beghelli customer support. Contact details can typically be found on the product packaging, the official Beghelli website, or within the Dom-e application. For more information, visit: www.beghelli.it

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B09JL1VX1C>

More documents and user manuals: **<https://manuals.plus/>**