

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

- › [Labelife](#) /
- › [Labelife D210S Portable Label Maker Instruction Manual](#)

## Labelife D210S

# Labelife D210S Portable Label Maker Instruction Manual

Model: D210S

[Introduction](#)   [Package Contents](#)   [Setup](#)   [Operating](#)  
[Instructions](#)   [Maintenance](#)   [Troubleshooting](#)   [Specifications](#)   [Warranty & Support](#)

## 1. INTRODUCTION

The Labelife D210S Portable Label Maker is designed for easy and efficient labeling in various environments, including home, office, and school. Featuring a QWERTY keyboard and one-touch smart keys, it simplifies the creation of durable, laminated labels. This manual provides detailed instructions for setting up, operating, and maintaining your label maker to ensure optimal performance.



Image: The Labelife D210S Portable Label Maker being used for home, office, and school organization, demonstrating its versatility.

## 2. PACKAGE CONTENTS

Please verify that all items listed below are included in your package:

- 1 x Labelife D210S Label Maker (Green)
- 1 x JM Label Tape JM-231 (Black on White)
- 1 x AC Power Adapter
- 1 x Replacement Cutter Holder
- 1 x User Manual


# Packaging includes:



1 \* Label Maker



1 \* AC Adapter



1 \* User Manual



1 \* JM Label Tape



1 \* Replacement Cutter Holder

Image: A visual representation of the Labelife D210S package contents, showing the label maker, AC adapter, JM label tape, replacement cutter holder, and user manual.

## 3. SETUP

### 3.1 Power Supply Options

The Labelife D210S can be powered using the included AC adapter or 6 AAA batteries (not included). The device cannot be charged; it operates directly from the power source.

- **Using the AC Adapter:** Connect the AC adapter to the power port on the side of the label maker and plug it into a wall outlet.
- **Using AAA Batteries:** Open the battery compartment on the underside of the label maker. Insert 6 AAA batteries,

ensuring the positive (+) and negative (-) terminals are aligned correctly as indicated in the compartment. Note that the electrodes of the upper and lower batteries are in opposite directions. Close the battery compartment securely.

## Two Power Supply Options



**AC Adapter** (Included)  
Cost-effective



**6 AAA Batteries**  
(NOT Included)  
Use anytime and anywhere

Image: The Labelife D210S label maker illustrating its two power supply options: connection to an AC adapter and the open battery compartment for 6 AAA batteries.

### 3.2 Installing Label Tape

Follow these steps to install the label tape cartridge:

1. Open the tape compartment cover on the label maker.
2. Take the label tape cartridge (e.g., JM-231) and ensure the end of the tape passes through both tape guides correctly. Extend approximately 1.5 inches (3cm to 4cm) of label tape.
3. Turn the green gear on the tape cartridge in the direction of the arrow until the carbon ribbon is tight.
4. Install the label tape cartridge into the compartment in the correct direction. Ensure the extended label tape passes through the outlet of the label maker.
5. Close the tape compartment cover.

6. If you install the label tape after turning on the label maker, the device will prompt you to choose the label width. Select "12mm" for the included JM-231 label tape.

## Tips for Installing Label Tape

Kindly follow below tips before every installation to avoid damage.



### Step 1

Kindly make sure the end of tape is through both tape guides correctly. Then extend about 1.5 inch (3cm to 4 cm) label tapes.



### Step 3

When install, make sure the extended label tape passes through the outlet of label maker.



### Step 2

Turn the green gear in the direction of arrow on the tape until tight to tighten the carbon ribbon.

Image: A step-by-step visual guide for installing the label tape, showing how to thread the tape, tighten the carbon ribbon, and correctly place the cartridge into the label maker.

Your browser does not support the video tag.

Video: This video demonstrates the correct procedure for installing both the label tape and batteries into the Labelife D210S label maker.

## 4. OPERATING INSTRUCTIONS

### 4.1 Basic Operation

- **Power On/Off:** Long press the red power button to turn the label maker on or off.
- **Clear Text:** Press the "Clear" one-touch key to erase any previously entered text or formatting.
- **Capital/Lowercase:** Use the "A/a" key to switch between capital and lowercase letters.
- **Typing:** Use the QWERTY keyboard to input your desired text.
- **Symbols & Frames:** Access over 500 symbols and 4 frames using the "Symbol" and "Frame" keys respectively.

- **Settings:** Use the "Settings" key to adjust label margins and other print options.



Image: A close-up view of the Labelife D210S QWERTY keyboard, highlighting its user-friendly layout for easy text input.

Your browser does not support the video tag.

Video: This video demonstrates the ease of use of the Labelife D210S label maker, showing basic text input and printing.

## 4.2 Saving Label Tape

To minimize tape waste, consider the following tips:

- **Set Label Margin to "Narrow":** Navigate to the "Settings" menu and select "Narrow" for the label margin. This reduces the blank space at the beginning and end of each label.
- **Manual Cutting:** Turn on the "Cutting" option in the menu for manual cutting. After printing the first label, the screen will show "Please Cut!". Cut the first label, then print the next. This allows for more precise cutting and reduces wasted tape between labels.
- **Multi-Copy Editing:** If printing several different labels, use the multi-copy editing one-touch key to continuously edit and print up to 55 different labels in one batch. This optimizes tape usage by printing them consecutively.
- **Batch Printing Same Labels:** If you need multiple copies of the same label, print them all at once and then cut them individually. The label maker can print up to 9 labels each time.

# Unique Function to Save Label Tape

Multi-edit key can edit and print up to **55** different labels

**Face Cream:Toner:Essence:Eye Cream:Facial Cleanser**

Image: The Labelife D210S label maker highlighting its multi-edit key feature, which allows continuous editing and printing of up to 55 different labels to save tape.

Your browser does not support the video tag.

Video: This video demonstrates how to use the Labelife D210S label maker to save label tape by adjusting settings and utilizing multi-label editing.

### 4.3 Automatic vs. Fixed Length Labels

The D210S supports both automatic and fixed length label printing:

- **Automatic Length:** The label maker automatically adjusts the label length based on the text entered.
- **Fixed Length:** You can set a specific length for your labels, useful for consistent sizing.

# Print both Automatic Length and Fixed Length Labels

The image illustrates two labeling methods. On the left, under 'Automatic Length Labels', three jars are shown with labels of different lengths: 'Coffee Bean' (yellow), 'Soybean' (cyan), and 'Black Soya Bean' (blue). Above these are icons for each item. On the right, under 'Fixed Length Labels', three jars are shown with labels of uniform length: 'Sugar', 'Salt', and 'Bean'. Above these are icons for each item. A double-headed arrow indicates the comparison between the two methods.

Image: A visual comparison of labels printed with automatic length adjustment versus fixed length settings, demonstrating the flexibility of the Labelife D210S.

## 5. MAINTENANCE

To ensure the longevity and optimal performance of your Labelife D210S label maker, follow these maintenance guidelines:

- **Cleaning the Print Head:** If print quality degrades, gently clean the print head with a cotton swab dampened with isopropyl alcohol. Ensure the device is off and disconnected from power before cleaning.
- **Cleaning the Cutter:** Periodically check the cutter blade for any adhesive residue or tape fragments. Use the included replacement cutter holder to carefully remove and clean the cutter if necessary.
- **Storage:** Store the label maker in a cool, dry place away from direct sunlight and extreme temperatures. Remove batteries if the device will not be used for an extended period.
- **Tape Compatibility:** Only use genuine Labelife JM label tapes to prevent damage and ensure proper functioning.

## 6. TROUBLESHOOTING

If you encounter issues with your Labelife D210S, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Device does not turn on.	Low or dead batteries. Incorrect battery installation. AC adapter not properly connected.	Replace with fresh AAA batteries, ensuring correct polarity. Ensure AC adapter is securely plugged into both the device and a working power outlet.
Poor print quality (faint, incomplete).	Print head is dirty. Tape cartridge is not installed correctly. Low battery power.	Clean the print head with a cotton swab and isopropyl alcohol. Reinstall the tape cartridge, ensuring it is seated properly and the carbon ribbon is tight. Replace batteries or use the AC adapter.
Tape jams or does not feed.	Tape cartridge incorrectly installed. Tape is twisted or caught. Cutter blade is obstructed.	Open the tape compartment and re-install the cartridge. Ensure the tape is not twisted and feeds smoothly. Clean the cutter blade and tape path.
Excessive tape waste.	Default margin settings. Printing single labels repeatedly.	Set label margin to "Narrow" in the settings. Utilize multi-copy editing for different labels or print multiple identical labels in one batch. Turn on "Cutting" for manual cutting after each label.

## 7. SPECIFICATIONS

Feature	Detail
Model Number	D210S
Brand	Labelife
Connectivity Technology	QWERTY Keyboard
Printing Technology	Thermal Transfer
Special Feature	Portable, QWERTY Keyboard

Feature	Detail
Color	Green
Printer Output	Monochrome
Maximum Print Resolution	300 dpi (Black and White)
Maximum Media Size	0.47 inches (12mm)
Compatible Cartridge	JM Label Tape
Power Source	AC Adapter (included) or 6 AAA Batteries (not included)
Product Dimensions	6.7 x 6.2 x 3.15 inches
Item Weight	1.63 pounds
Specific Uses	Enterprise, Home, Office

## 8. WARRANTY & SUPPORT

---

### 8.1 Warranty Information

The Labelife D210S Portable Label Maker comes with a Limited Warranty. Please refer to the warranty card included in your package for specific terms and conditions, including coverage duration and claim procedures.

### 8.2 Customer Support

For technical assistance, troubleshooting, or any questions regarding your Labelife D210S label maker, please contact Labelife customer support. Contact details can typically be found on the official Labelife website or on the warranty card provided with your product.

When contacting support, please have your product model number (D210S) and purchase information readily available.

