

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [staniot](#) /
- › [Staniot H501-WiFi Home Alarm System User Manual](#)

### staniot H501-WiFi

# Staniot H501-WiFi Home Alarm System User Manual

Model: H501-WiFi | Brand: Staniot

## 1. INTRODUCTION

---

Welcome to the Staniot H501-WiFi Home Alarm System. This comprehensive security kit is designed to provide reliable and intelligent protection for your home or office. Featuring an intuitive touch screen panel, seamless app control, and compatibility with smart home assistants, this system offers enhanced security and peace of mind. This manual will guide you through the setup, operation, and maintenance of your new security system.



Figure 1: Staniot H501-WiFi Home Alarm System components including the main panel, door/window sensors, SOS button, motion detector, and remote controls.

## 2. IMPORTANT SAFETY INFORMATION

Please read all safety instructions carefully before installing and operating the system. Failure to follow these instructions may result in damage to the device or personal injury.

- Ensure the system is installed in a dry environment, away from water and excessive humidity.
- Do not attempt to disassemble or repair the device yourself. Refer all servicing to qualified personnel.
- Use only the provided power adapter for the main panel.
- Keep small components and batteries out of reach of children.
- Verify that all sensors are securely mounted to prevent accidental detachment.

- Only connect to a 2.4 GHz WiFi network. 5 GHz networks are not supported.

### 3. PACKAGE CONTENTS

---

Upon unpacking, please verify that all items listed below are included in your package:

- 1 x Security Panel (Main Control Unit)
- 4 x Entry Sensors (Door/Window Sensors)
- 1 x SOS Button
- 2 x Remote Controls
- 1 x Wired Siren
- 1 x PIR Motion Detector
- 1 x Power Adapter for Main Panel
- Mounting Hardware (screws, adhesive pads)
- User Manual (this document)

## Smart Security System Kit




Smart Security Panel × 1



Motion Sensor × 1



Entry Sensor × 4



SOS Button × 1



Remote Control × 2



Wired Siren × 1



Box

## 4. SETUP GUIDE

---

### 4.1. Main Panel Installation

1. **Power On:** Connect the provided power adapter to the main security panel and plug it into a wall outlet. The panel will power on and display the Staniot Home UI 2.0 interface.
2. **Network Connection:**
  - On the panel, navigate to the Wi-Fi settings.
  - Select your 2.4 GHz Wi-Fi network and enter the password.
  - Ensure the panel is connected to the internet for app control and updates.
3. **App Download:** Download the "Smart Life" app from your smartphone's app store (iOS App Store or Google Play Store). Register an account if you don't have one.
4. **Pairing with App:**
  - Open the Smart Life app and follow the on-screen instructions to add a new device.
  - Select "Security & Video Surveillance" -> "Alarm (Wi-Fi)".
  - Follow the app's guide to connect the panel. This usually involves putting the panel into pairing mode.

# 12mm Ultra-thin Body

## Elegant Design



Figure 3: The sleek design of the Staniot security panel, highlighting its ultra-thin profile and connectivity ports.

## 4.2. Sensor and Accessory Installation

The system supports up to 200 accessories. Each accessory comes with adhesive pads or screws for easy installation.

### 1. Entry Sensors (Door/Window):

- Mount the two parts of the entry sensor on a door or window frame, ensuring they are aligned and within 1 cm of each other when the door/window is closed.
- Use the provided adhesive or screws for secure mounting.
- Test by opening and closing the door/window; the sensor's indicator light should flash.



Figure 4: Proper placement and activation of an entry sensor.

## 2. PIR Motion Detector:

- Install the motion detector in a corner or on a wall where it can cover the desired area without obstructions. Avoid direct sunlight or heat sources.
- Mount at a height of approximately 2.2-2.4 meters (7-8 feet) for optimal detection range.
- Test by walking through the detection area; the indicator light should activate.




Figure 5: The motion detector's 110-degree detection range.

3. **SOS Button:** Place the SOS button in an easily accessible location, such as a bedside table or near an exit.
4. **Remote Controls:** No installation needed. Keep them handy for quick arming/disarming.
5. **Wired Siren:** Connect the wired siren to the designated siren port on the main panel. Mount it in a visible location for maximum deterrent effect.

## 4.3. Adding Accessories to the System

After physical installation, you need to add each accessory to the main panel and the Smart Life app.

1. On the main panel, navigate to "Menu" -> "Accessories" -> "Add Accessory".
2. Trigger the accessory (e.g., open an entry sensor, wave in front of the motion detector, press the SOS button). The panel will detect and add the accessory.
3. You can customize the name of each accessory in the Smart Life app for easier identification (e.g., "Front Door Sensor", "Living Room Motion").

# Easy to Install



Figure 6: Simple installation process for the motion sensor.

## 5. OPERATING YOUR SYSTEM

---

### 5.1. Arming and Disarming

The Staniot system offers multiple ways to arm and disarm your security system:

- **Main Panel:** Use the touch screen to select "Away Arm" (full protection), "Stay Arm" (perimeter protection, internal sensors off), or "Disarm".
- **Remote Control:** Press the respective buttons on the remote control for quick arming/disarming.
- **Smart Life App:** Control the system remotely from your smartphone. You can set alarm modes and monitor accessory status.
- **Voice Control (Alexa/Google Assistant):** Integrate with Amazon Alexa or Google Assistant for voice commands.
  - Enable the "Smart Life" skill in your Alexa or Google Home app.
  - Link your Smart Life account.

- Use commands like "Alexa, arm the security system" or "Hey Google, disarm the alarm."




Figure 7: Voice control integration with Alexa and Google Assistant.

## 5.2. Instant App Notifications

When an alarm is triggered, you will receive instant notifications on your smartphone via the Smart Life app. This allows you to monitor your home's security status in real-time, even when you are away.




Figure 8: Real-time alarm notifications on your mobile device.

### 5.3. SOS Function

In case of an emergency, pressing the SOS button will immediately trigger the alarm and send alerts to pre-set emergency contacts via the app.



Figure 9: The SOS button provides immediate assistance in emergencies.

## 6. MAINTENANCE

- **Battery Replacement:** Replace batteries in sensors and remote controls as needed. The Smart Life app may notify you of low battery levels.
- **Cleaning:** Wipe the main panel and sensors with a soft, dry cloth. Avoid using abrasive cleaners or solvents.
- **Firmware Updates (OTA):** The system supports Over-The-Air (OTA) online upgrades. Regularly check for and install updates via the Smart Life app to ensure optimal performance and access to new features.



Figure 10: Seamless online firmware updates for continuous system improvement.

- **System Checks:** Periodically test all sensors and the siren to ensure they are functioning correctly.

## 7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Panel not connecting to Wi-Fi.	Incorrect Wi-Fi password; 5 GHz network selected; weak signal.	Double-check password. Ensure you are connecting to a 2.4 GHz network. Move panel closer to router.
Sensors not triggering alarm.	Sensor battery low; sensor not paired; improper installation.	Replace sensor battery. Re-pair sensor with panel. Ensure proper alignment and proximity for entry sensors.
No app notifications.	App permissions not granted; phone's notification settings disabled; panel not connected to internet.	Check app permissions in phone settings. Enable notifications for Smart Life app. Verify panel's internet connection.
Voice control not working.	Smart Life skill not enabled/linked; incorrect voice commands.	Ensure Smart Life skill is enabled and linked in Alexa/Google Home app. Use precise commands.
Siren not sounding.	Siren not connected; siren volume set too low.	Check siren connection to the main panel. Adjust siren volume settings on the panel.

If you encounter issues not listed here, please refer to the support section or contact customer service.

## 8. SPECIFICATIONS

Feature	Detail
Model Number	H501-WiFi
Brand	Staniot
Dimensions (Panel)	21.59 x 16.51 x 7.37 cm (8.5 x 6.5 x 2.9 inches)
Weight	912 grams (2.01 lbs)
Power Source	Battery Powered (1 Lithium-ion battery included)
Voltage	5 Volts
Connectivity Technology	Wireless (2.4 GHz Wi-Fi only)
Control Method	Application, Touch Screen, Remote Control, Voice Control
Compatible Devices	Smartphone (Smart Life App), Amazon Alexa, Google Assistant
Max Accessories Supported	Up to 200
Material	ABS
Certifications	CE, UKCA, FCC

## 9. WARRANTY AND SUPPORT

---

### 9.1. Warranty Information

Staniot products come with a standard manufacturer's warranty. Please refer to the warranty card included in your package or visit the official Staniot website for detailed warranty terms and conditions. Keep your purchase receipt as proof of purchase for warranty claims.

### 9.2. Customer Support

For technical assistance, troubleshooting, or any questions regarding your Staniot Home Alarm System, please contact our customer support team. We are committed to providing prompt and helpful service.

- **Online Support:** Visit the Staniot official website for FAQs, support articles, and contact forms.
- **Email Support:** Refer to your product packaging or the official website for the customer support email address.
- **Phone Support:** Check the official website for available phone support numbers and operating hours.

Your satisfaction is our primary goal. If you encounter any problems, please contact us first, and we will resolve the issue for you as soon as possible.