

Pia Ricco 12161

Pia Ricco Outdoor Post Light Fixture

Model: 12161 - Instruction Manual

INTRODUCTION

This manual provides essential information for the safe installation, operation, and maintenance of your Pia Ricco Outdoor Post Light Fixture, Model 12161. This modern outdoor lantern is designed for durability and aesthetic appeal in various outdoor settings, featuring a waterproof and anti-rust construction with an E26 socket.

SAFETY INFORMATION

- Always turn off the main power supply at the circuit breaker before beginning any installation, maintenance, or bulb replacement.
- Ensure all wiring connections are secure and comply with local electrical codes. If you are unsure about wiring, consult a qualified electrician.
- Do not exceed the maximum wattage of 60W for the E26 bulb.
- Handle glass components with care to prevent breakage.
- This fixture is rated for wet locations (ETL Certified, IP44 Weather-resistance). Ensure all seals are properly seated during installation to maintain its waterproof integrity.

PACKAGE CONTENTS

Verify that all components are present before installation:

- 1 x Pia Ricco Outdoor Post Light Fixture (Model 12161)
- Mounting Hardware (screws, wire nuts)
- Instruction Manual

Note: E26 bulb is not included.

SPECIFICATIONS

Feature	Detail
Brand	Pia Ricco

Model Number	12161
Dimensions (L x W x H)	5.12" x 5.12" x 16.5"
Weight	3.75 lbs
Material	Die-cast Metal, Clear Glass
Finish	Matte Black
Bulb Base	E26 (Bulb not included)
Max Wattage	60W
Voltage	120 Volts
Compatibility	LED, Incandescent, CFL, Halogen, Dusk to Dawn, Smart Bulbs
Weather Resistance	IP44, Waterproof, Anti-Rust, ETL Certified Wet Location
Mounting Type	Pole Mount / Pier Mount

The fixture's dimensions are 5.12 inches in length, 5.12 inches in width, and 16.5 inches in height, making it suitable for various outdoor applications.



Figure 1: Product dimensions for planning installation.

This fixture is ETL certified for wet locations and meets IP44 standards for weather resistance, ensuring durability against various outdoor elements.



Figure 2: Key features including ETL certification and E26 bulb compatibility.

SETUP (INSTALLATION)

This outdoor post light fixture offers two primary mounting options: pole mount (for 3" diameter lamp posts) or pier mount (for standard 3" post bases). All necessary mounting hardware is included.

2 Mounting Ways



Pole Mount (Not Included)
Fits for 3" Lamp Post



Pier Mount Base (No Included)
Fits Standard 3" Post base



Figure 3: Illustration of the two available mounting methods.

Installation Steps:

1. **Prepare the Mounting Location:** Ensure the existing post or pier base is stable and properly secured. Turn off the power to the post at the circuit breaker.
2. **Connect Wiring:** Carefully pull the electrical wires from the post through the center of the light fixture's base. Connect the wires using the provided wire nuts:
 - Connect the ground wire (usually bare copper or green) from the fixture to the ground wire from the power supply.
 - Connect the neutral wire (white) from the fixture to the neutral wire from the power supply.
 - Connect the live/hot wire (black) from the fixture to the live/hot wire from the power supply.

Ensure all connections are tight and secure.

3. **Mount the Fixture:** Carefully align the fixture base with the mounting holes on your post or pier base. Secure the fixture using the provided screws. Do not overtighten.

- ## Installation Video:

Video 1: A demonstration of the installation process for the outdoor post light fixture.

OPERATING INSTRUCTIONS

- **Standard Operation:** Once installed and powered, use your existing outdoor light switch to turn the fixture on or off.
- **Smart Bulb Integration:** If using a compatible smart E26 bulb, follow the bulb manufacturer's instructions for pairing with your smart home app or system for advanced control options.
- **Dusk-to-Dawn Bulbs:** If using a dusk-to-dawn E26 bulb, the light will automatically turn on at dusk and off at dawn, provided the fixture receives continuous power.

MAINTENANCE

- **Cleaning:** To clean the glass panels and metal frame, first ensure the power is off. Use a soft, damp cloth with a mild, non-abrasive cleaner. Avoid harsh chemicals or abrasive materials that could scratch the finish or glass.
- **Bulb Replacement:** Turn off the power at the circuit breaker. Carefully remove the top lid by unscrewing the two screws. Unscrew the old E26 bulb and replace it with a new one (max 60W). Reattach the top lid, ensuring the rubber washers are in place for a weather-tight seal.
- **Inspection:** Periodically inspect the fixture for any signs of wear, corrosion, or damage to the wiring. Ensure all mounting screws remain tight. Address any issues promptly to prevent further damage or safety hazards.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on	No power to the fixture Faulty bulb Loose wiring connection	Check the circuit breaker and wall switch. Replace the bulb with a new, working E26 bulb. Turn off power, check and tighten all wire connections.
Light flickers	Loose bulb Loose wiring connection Incompatible dimmer switch (if applicable)	Tighten the bulb in the socket. Turn off power, check and tighten all wire connections. Ensure your dimmer switch is compatible with the bulb type (e.g., LED compatible dimmer for LED bulbs).

Water inside the fixture	Improperly sealed top lid Damaged glass or seals	Turn off power, remove and re-seat the top lid, ensuring rubber washers are correctly positioned and screws are snug. Inspect glass panels and seals for cracks or damage. Replace if necessary.
--------------------------	---	---

WARRANTY

The Pia Ricco Outdoor Post Light Fixture (Model 12161) comes with a **1-year manufacturer's warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use. Return and replacement options are feasible for quality issues within this 1-year period. Please retain your proof of purchase for warranty claims.

SUPPORT

For any questions, concerns, or assistance regarding your Pia Ricco Outdoor Post Light Fixture, please do not hesitate to contact Pia Ricco customer support. Refer to the contact information provided with your purchase or visit the official Pia Ricco website for support details.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Email

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Details

Submit question

Open the live page

<https://manuals.plus/asin/B09P54W7M8>

More documents and user manuals: <https://manuals.plus/>