

Versonel VSL90



User Manual

OUTDOOR MOTION SENSOR TRACKING LED FLOODLIGHT SECURITY LIGHT

Model: VSL90 | Brand: Versonel

1. Introduction

The Versonel Nightwatcher VSL90 is an advanced outdoor LED floodlight designed for security and deterrence. It features a patented robotic motion sensor that tracks movement across a wide detection zone, illuminating and following any detected activity. This manual provides essential information for the safe and effective installation, operation, and maintenance of your Nightwatcher VSL90.

2. Safety Information

Please read all instructions carefully before installation and use. Failure to follow these instructions may result in electric shock, fire, or other hazards.

- **Electrical Safety:** This unit requires hardwiring to a 100-240V electrical supply. Installation should be performed by a qualified electrician or a person with adequate knowledge of electrical wiring to prevent electric shock.
- **Power Disconnection:** Always disconnect power at the circuit breaker before installing, servicing, or cleaning the fixture.
- **Mounting:** Ensure the mounting surface is structurally sound and can support the weight of the fixture.
- **Outdoor Use:** The VSL90 is weatherproof (IP65 rated) for outdoor use. Ensure all connections are sealed properly to maintain water resistance.
- **Heat:** The LED light source can become hot during operation. Do not touch the light fixture immediately after it has been on.

3. Package Contents

Verify that all components are present before beginning installation:

- Nightwatcher VSL90 Light Fixture
- Universal Mounting Bracket
- Light Fixture Mounting Screws
- Junction Box Mounting Screws

- Decorative Screw Covers
- EVA Gasket
- Wire Nuts

4. Product Overview

The Versonel Nightwatcher VSL90 integrates a powerful LED floodlight with a sophisticated motion detection and tracking system.



Figure 4.1: Front view of the VSL90 light fixture, showing the LED panel and the spherical PIR sensor below.



Figure 4.2: Side view of the VSL90, illustrating the adjustable light head and the integrated control panel on the side.

The unit features a 1700 Lumen LED light source and three integrated Passive Infrared (PIR) sensor zones. These sensors detect movement up to 39.37 feet (12 meters) across a 210-degree horizontal detection zone. Upon detection, the light automatically rotates to follow the movement, illuminating the area and creating the impression of being watched.



Figure 4.3: Illustration of the VSL90's 210-degree detection zone and range, covering a wide area around a property.



Figure 4.4: Visual representation of the VSL90's robotic movement tracking feature, where the light follows detected motion.

5. Setup and Installation

The VSL90 is designed for easy outdoor installation, replacing an existing floodlight fixture or adding to any location with electrical wiring. This unit must be hardwired.

5.1. Pre-Installation Steps

- 1. Disconnect Power:** Turn off power to the installation area at the circuit breaker.
- 2. Prepare Junction Box:** Ensure you have a suitable 4-inch diameter electrical junction box (not included) for mounting.
- 3. Unpack:** Carefully remove all components from the packaging.

5.2. Mounting Instructions




Figure 5.1: Exploded view of the VSL90 installation components and wiring connections.

1. **Attach Universal Mounting Bracket (E):** Secure the universal mounting bracket to your electrical junction box using the provided junction box mounting screws (D). Ensure the bracket is oriented correctly.
2. **Install EVA Gasket (F):** Place the EVA gasket over the universal mounting bracket. This helps seal the fixture against moisture.
3. **Wire Connections (G):** Connect the household wiring to the light fixture wiring using the provided wire nuts (G). Typically, this involves connecting live to live, neutral to neutral, and ground to ground. Refer to local electrical codes.
4. **Mount Light Fixture (A):** Align the light fixture with the mounting bracket and secure it using the light fixture mounting screws (C).
5. **Attach Decorative Screw Covers (B):** Place the decorative screw covers over the mounting screws for a finished appearance.
6. **Restore Power:** Once installation is complete and all connections are secure, restore power at the circuit breaker.

6. Operating Instructions

The VSL90 features a control panel with four switches (SW1-SW4) to adjust its operation. The LEDs (1-4) indicate the current settings.



Figure 6.1: Detailed view of the VSL90's control panel, showing the four switches (SW1-SW4) and their corresponding functions.

6.1. Control Panel Functions

- **SW1 (Sensor L/M/H):** Adjusts the sensitivity of the motion sensor.
 - **L (Low):** Reduced detection range.
 - **M (Medium):** Standard detection range.
 - **H (High):** Maximum detection range (up to 39.37 feet).
- **SW2 (Light On/Off):** Controls the light operation.
 - **On:** Light will activate upon motion detection.
 - **Off:** Light will remain off, but motion tracking may still occur if SW3 is On.
- **SW3 (Rotation On/Off):** Enables or disables the robotic tracking movement.
 - **On:** The light head will rotate to follow detected motion.
 - **Off:** The light will illuminate but remain stationary.
- **SW4 (Walk Test):** Activates a test mode for verifying sensor coverage.
 - When activated, the light will turn on and track movement for a short period, allowing you to walk

through the detection zone to confirm coverage.

6.2. Initial Setup and Testing

1. After installation, set SW1 to 'M', SW2 to 'On', and SW3 to 'On'.
2. Activate 'Walk Test' (SW4) and walk through the intended detection area to ensure the sensor covers the desired zones and the light tracks your movement.
3. Adjust SW1 (Sensor Sensitivity) as needed to optimize detection range and minimize false triggers.
4. Once satisfied with the coverage, deactivate 'Walk Test' (SW4). The unit will now operate in its normal mode.

7. Maintenance

Regular maintenance ensures optimal performance and longevity of your Nightwatcher VSL90.

- **Cleaning:** Periodically clean the lens of the LED light and the PIR sensor dome with a soft, damp cloth. Do not use abrasive cleaners or solvents.
- **Inspection:** Annually inspect the fixture for any signs of damage, loose wiring, or corrosion. Ensure all mounting screws are tight.
- **Power Cycle:** If the unit behaves erratically, try turning off the power at the circuit breaker for a few minutes and then restoring it. This can reset the system.

8. Troubleshooting

Refer to the following table for common issues and their solutions:

Problem	Possible Cause	Solution
Light does not turn on.	No power; SW2 is Off; Sensor sensitivity too low; Faulty wiring.	Check circuit breaker; Ensure SW2 is On; Adjust SW1 to 'M' or 'H'; Verify wiring connections.
Light does not track movement.	SW3 is Off; Obstruction in sensor view; Sensor malfunction.	Ensure SW3 is On; Clear any obstructions; Perform a 'Walk Test' (SW4).
Light turns on or tracks without apparent motion (false triggers).	Sensor sensitivity too high; Heat sources (e.g., car engines, vents); Small animals; Moving foliage.	Adjust SW1 to 'L' or 'M'; Reposition the fixture to avoid heat sources or moving objects.
Light stays on continuously.	Continuous motion in detection zone; Faulty sensor.	Ensure no constant motion is present; Power cycle the unit. If issue persists, contact support.

9. Specifications

- **Brand:** Versonel
- **Model:** VSL90

- **Color:** White
- **Power Source:** Corded Electric
- **Voltage:** 100-240 Volts
- **Type of Bulb:** LED
- **Lumen Output:** 1700 Lumens
- **Maximum Detection Range:** 39.37 Feet (12 meters)
- **Horizontal Detection Zone:** 210 degrees
- **Mounting Type:** Wall Mount
- **Special Features:** Motion Sensor, Robotic Movement Tracking
- **Weather Resistance:** IP65
- **Product Dimensions:** 7.04 x 5.51 x 6.49 inches
- **Item Weight:** 2.35 pounds



10. Warranty Information

This product is covered by a manufacturer's warranty. Please refer to the warranty card included with your product packaging or visit the official Versonel website for detailed warranty terms and conditions. Keep your purchase receipt as proof of purchase for any warranty claims.

11. Support


For technical assistance, troubleshooting beyond this manual, or inquiries regarding your Versonel Nightwatcher VSL90, please contact Versonel customer support. Contact information can typically be found on the product packaging or the official Versonel brand website.

Related Documents

	<p><u>Versonel VSL90 LED Security Light Quick Installation Guide</u></p> <p>Comprehensive guide for installing the Versonel VSL90 motion-activated LED security light, covering parts, wiring, mounting, and testing procedures.</p>
	<p><u>Versonel VSL95 LED Security Light Quick Installation Guide</u></p> <p>Step-by-step instructions for installing and connecting the Versonel VSL95 LED security light to your Wi-Fi network using the Tuya Smart app.</p>

USE AND CARE GUIDE

MOTORIZED MOTION TRACKING SECURITY LIGHT

CE FCC
Patented Technology

Protect yourself. Please read these instructions carefully prior to installation and retain them for future reference.
Failure to follow any of these instructions could void product warranties.

For questions regarding this product or warranty, please contact Customer Service at:
Email : service@versonel.com or Toll Free at 877-977-7627

[\[pdf\] User Manual Instructions Guide Warranty Label](#)


900 VSL90 cdr wlpc Versonel Product Manuals versonel nghtwatcher vsl90 manual 12 22 1 4 8

14180096 |||

VERSONEL Model VSL90 USE AND CARE GUIDE MOTORIZED MOTION TRACKING SECURITY LIGHT Patented Technology Protect yourself. Please read these instructions carefully prior to installation and retain them for future reference. Failure to follow any of these instructions could void product warranties. Fo...
lang:en score:54 filesize: 1.2 M page_count: 7 document date: 2022-12-15

USE AND CARE GUIDE

MOTORIZED MOTION TRACKING SECURITY LIGHT

CE FCC
Patented Technology

Protect yourself. Please read these instructions carefully prior to installation and retain them for future reference.
Failure to follow any of these instructions could void product warranties.

For questions regarding this product or warranty, please contact Customer Service at:
Email : service@versonel.com or Toll Free at 877-977-7627

[\[pdf\] Instructions Guide Warranty Catalog Label](#)


900 VSL90 cdr wlpc VERSOENEL® Model USE AND CARE GUIDE MOTORIZED MOTION

TRACKING SECURITY LIGHT Patented Technology Protect yourself Please read these instructions 5bb8f36e 970f 4510 b379 121e17bd7d5d images thdstatic catalog Images 5b 5bb8f36e 121e17bd7d5d |||

VERSONEL Model VSL90 USE AND CARE GUIDE MOTORIZED MOTION TRACKING SECURITY LIGHT Patented Technology Protect yourself. Please read these instructions carefully prior to installation and retain them for future reference. Failure to follow any of these instructions could void product warranties. Fo...
lang:en score:54 filesize: 1.2 M page_count: 7 document date: 2022-12-15

USE AND CARE GUIDE

MOTORIZED MOTION TRACKING SECURITY LIGHT

CE FCC
Patented Technology


Protect yourself. Please read these instructions carefully prior to installation and retain them for future reference.
Failure to follow any of these instructions could void product warranties.

For questions regarding this product or warranty, please contact Customer Service at:
Email : tech@nightwatcherproject.com or Toll Free (866) 637-6887

[\[pdf\] User Manual Instructions Guide Warranty Label](#)

900 VSL90 cdr wlpc Nightwatcher Robotic Security Lighting USA Distribution by Versonel versonel vsl90 manual 2 21 22 1 4 8 14180096 |||


VERSONEL Model VSL90 USE AND CARE GUIDE MOTORIZED MOTION TRACKING SECURITY LIGHT Patented Technology Protect yourself. Please read these instructions carefully prior to installation and retain them for future reference. Failure to follow any of these instructions could void product warranties. Fo...
lang:en score:50 filesize: 1.27 M page_count: 7 document date: 2022-02-18



[Versonel VSL90 LED Security Light Quick Installation Guide](#)

Comprehensive guide for installing the Versonel VSL90 motion-activated LED security light, covering parts, wiring, mounting, and testing procedures.

lang:en score:40 filesize: 1.6 M page_count: 1 document date: 2021-11-23




[\[pdf\]](#) Quick Start Guide Guide

900 VSL90 cdr wlpc Versonel Product Manuals versonel nightwatcher vsl90 quick start guide 1 4 8

14180096 |||

Jangyan score:10 filesize: 1.69 M page_count: 1 document_date: 2022-10-15



[\[pdf\]](#) User Manual

900 VSL90 cdr wlpc Versonel Product Manuals versonel vsl90 manual 1 4 8 14180096 |||

2

lang:en score:32 filesize: 7.9 M page_count: 7 document date: 2021-11-30

