

## ZEALOT S57

# ZEALOT S57 Portable Bluetooth Speaker User Manual

Model: S57

---

## 1. PRODUCT OVERVIEW

The ZEALOT S57 is an 80W portable Bluetooth speaker designed for robust audio performance and versatility. It features dual woofers, full-range drivers, and tweeters, enhanced by a DSP chip for a powerful stereo sound experience. With a large 14,400mAh battery, it offers extended playtime and can also function as a power bank for other devices. The speaker includes dynamic RGB lighting, Bluetooth 5.2 connectivity, and an IPX7 waterproof rating, making it suitable for various indoor and outdoor environments. Additional features include dual pairing capability, TF card, AUX, and USB playback options, and a microphone input for karaoke or public address functions.



Image: The ZEALOT S57 Portable Bluetooth Speaker, showcasing its design and integrated handle.

Your browser does not support the video tag.

Video: An overview of the ZEALOT S57 Bluetooth Speaker's features and design.

## 2. PACKAGE CONTENTS

Before using your ZEALOT S57 speaker, please ensure all items are present in the package:

- 1 x ZEALOT S57 Bluetooth Speaker
- 1 x Type-C Charging Cable
- 1 x 3.5mm AUX Cable
- 1 x User Manual (this document)




Caja de Embalaje



Guía del Usuario



Altavoz S57



Línea de Carga



Línea de Sonido

Image: The ZEALOT S57 speaker and its included accessories: Type-C charging cable, 3.5mm AUX cable, and user manual.

## 3. SETUP AND CHARGING

### 3.1 Initial Charge

For optimal battery performance, fully charge the speaker before first use. Connect the provided Type-C charging cable to the speaker's charging port and a compatible USB power adapter (not included).

### 3.2 Powering On/Off

Press and hold the power button ( ) located on the top panel of the speaker to turn it on or off. An audible cue will indicate the power status.

### 3.3 Bluetooth Pairing

1. Turn on the speaker. It will automatically enter Bluetooth pairing mode, indicated by a flashing light.
2. On your device (smartphone, tablet, etc.), enable Bluetooth and search for available devices.
3. Select "ZEALOT S57" from the list of devices.
4. Once connected, the speaker will emit a confirmation tone, and the light will stabilize.



Image: The ZEALOT S57 speaker connected via Bluetooth to a smartphone, illustrating wireless connectivity.

## 4. OPERATING INSTRUCTIONS

### 4.1 Control Panel Functions

The top panel of the speaker features several buttons for controlling playback, volume, and other functions:

- **Power Button** ( ): Press and hold to power on/off.
- **Light Button** ( ): Press to cycle through RGB light modes. Double-click to turn lights off.
- **Mode Button** ( M ): Press to switch between input modes (Bluetooth, TF Card, AUX, USB).
- **Dual Pairing Button** ( ): Press to initiate dual pairing with another S57 speaker.
- **Play/Pause Button** ( ): Press to play or pause audio.
- **Volume Down / Previous Track** ( ): Press to decrease volume. Hold to go to the previous track.
- **Volume Up / Next Track** ( + ): Press to increase volume. Hold to go to the next track.



Image: Close-up view of the control panel buttons on the top of the ZEALOT S57 speaker.

## 4.2 Dual Pairing Function (TWS)

To achieve a true wireless stereo experience, you can pair two ZEALOT S57 speakers:

1. Ensure both S57 speakers are powered on and not connected to any other Bluetooth device.
2. On one speaker, press the Dual Pairing button ( ). It will search for another S57 speaker.
3. The two speakers will connect automatically. A confirmation tone will sound.
4. Connect your device to one of the paired speakers via Bluetooth. Both speakers will now play audio in stereo.



Image: Two ZEALOT S57 speakers demonstrating the dual pairing feature for enhanced stereo sound.

### 4.3 Input Ports and Power Bank Function

The speaker features a protected port panel on the side:

- **USB Port:** For playing audio from a USB drive or charging external devices (power bank function).
- **TF Card Slot:** For playing audio directly from a MicroSD/TF card.
- **AUX Input:** Connect external audio devices using the 3.5mm AUX cable.
- **MIC Input:** Connect a microphone for karaoke or public address.
- **Type-C Charging Port:** For charging the speaker.



Image: Side view of the ZEALOT S57 speaker, showing the protected input ports for USB, TF card, AUX, and microphone.



Image: The ZEALOT S57 speaker charging a smartphone, demonstrating its power bank capability.

Your browser does not support the video tag.

Video: A short demonstration highlighting the 80W output and portable nature of the speaker.

## 5. MAINTENANCE

### 5.1 Cleaning

Wipe the speaker with a soft, damp cloth. Avoid using harsh chemicals or abrasive cleaners. Ensure the port cover is securely closed before cleaning or exposing to water.

### 5.2 Water Resistance (IPX7)

The ZEALOT S57 is IPX7 waterproof, meaning it can be submerged in water up to 1 meter for 30 minutes. Ensure the rubber cover for the ports is fully sealed before exposing the speaker to water. After exposure to water, dry the speaker thoroughly before charging.



Image: The ZEALOT S57 speaker partially submerged in water, illustrating its IPX7 waterproof rating.

Your browser does not support the video tag.

Video: A demonstration of the ZEALOT S57 speaker's IPX7 waterproof capability.

## 6. TROUBLESHOOTING

If you encounter issues with your ZEALOT S57 speaker, refer to the following common solutions:

- **Speaker not turning on:** Ensure the battery is charged. Connect the speaker to a power source using the Type-C cable.
- **Cannot pair via Bluetooth:** Ensure the speaker is in pairing mode (flashing light). Turn off and on your device's Bluetooth. Move the speaker closer to your device.
- **No sound:** Check the volume levels on both the speaker and your connected device. Ensure the correct input mode is selected (Bluetooth, AUX, TF, USB).
- **Poor sound quality:** Ensure the speaker is within Bluetooth range (up to 100 feet/30 meters). Avoid obstructions between the speaker and your device.
- **Dual pairing not working:** Ensure both S57 speakers are powered on and not connected to any other device before initiating dual pairing.
- **Charging issues:** Use the provided Type-C cable. Ensure the charging port is clean and free of debris.

## 7. SPECIFICATIONS

| Feature                      | Specification                    |
|------------------------------|----------------------------------|
| Brand                        | ZEALOT                           |
| Model Number                 | S57                              |
| Speaker Maximum Output Power | 80 Watts                         |
| Connectivity Technology      | Bluetooth 5.2, USB, AUX, TF Card |
| Audio Output Mode            | Stereo                           |
| Water Resistance Level       | IPX7 Waterproof                  |
| Battery Capacity             | 14,400 mAh                       |
| Battery Average Life         | Up to 40 Hours                   |
| Bluetooth Range              | Up to 100 Feet (30 Meters)       |
| Number of Microphones        | 1 (Input)                        |
| Item Dimensions (D x W x H)  | 5.74" x 8.18" x 14.4"            |
| Item Weight                  | 1.91 Kilograms                   |



Image: Diagram showing the dimensions of the ZEALOT S57 Portable Bluetooth Speaker.

## 8. WARRANTY

The ZEALOT S57 Portable Bluetooth Speaker comes with a **1-year limited warranty** from the date of purchase. This warranty covers manufacturing defects and workmanship under normal use. It does not cover damage caused by misuse, accidents, unauthorized modifications, or natural disasters. Please retain your proof of purchase for warranty claims.

## 9. SUPPORT

For any questions, suggestions, or technical assistance regarding the use and sound quality of your ZEALOT S57 Bluetooth speaker, please contact the ZEALOT support team. We are committed to providing excellent customer service and will respond to your inquiries within 24 hours.

Contact information can typically be found on the official ZEALOT website or through your purchase platform.