

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [Rush Charge](#) /
- › [Rush Charge Trident 3-in-1 Wireless Power Bank User Manual](#)

Rush Charge RC40

Rush Charge Trident 3-in-1 Wireless Power Bank User Manual

Model: RC40 | Brand: Rush Charge

1. INTRODUCTION

This manual provides detailed instructions for the safe and efficient use of your Rush Charge Trident 3-in-1 Wireless Power Bank. This compact and portable charger is designed to provide convenient power for a variety of devices, including smartphones, earbuds, and other gadgets, featuring multiple integrated connectors.

Please read this manual thoroughly before using the device and keep it for future reference.

2. PRODUCT OVERVIEW

The Rush Charge Trident is a versatile 4000mAh portable power bank equipped with multiple charging options. Its key features include:

- **Wireless Portable Charging:** Compact design for on-the-go power.
- **4000mAh Li-Ion Battery:** Provides extended battery life for your devices.
- **Cable-Free Design:** Integrated Micro USB, USB-C, and Lightning connectors.
- **Pass-Through Technology:** Allows simultaneous charging of the power bank and an attached device.
- **Pre-Charged:** Ready for use right out of the box.



Figure 2.1: Front view of the yellow Rush Charge Trident 3-in-1 Wireless Power Bank, showing its compact square shape and the Rush Charge logo.

Empower Your Rush

**RUSH
CHARGE**

Trident



Compact Design

LED

LED Battery
Life Display



2.1A High
Speed Charging

30 hours
of extended
battery life.

**Integrated USB Cable with Pass-through Technology which
Charges both devices at once.**

Figure 2.2: Illustration highlighting the compact design, LED battery life display, 2.1A high-speed charging capability, 30 hours of extended battery life, and the integrated USB cable with pass-through technology.

One-Handed Operations

3 Connector's

Pocket-Size

Cable-Free

For The Ones
That GO

Confidence in your daily devices starts here.
Take charge of your busy life with the ultimate 3-in-1 charger.
Introducing the TRIDENT, by Rush Charge.

Figure 2.3: Visual representation of the power bank's three integrated connectors (Micro USB, USB-C, Lightning) and its pocket-sized, cable-free design, demonstrating its portability and versatility.

Official Product Videos

No official product videos from the seller were found that meet the embedding criteria (creator_type: "Seller" and not a "preview" video unless genuinely useful).

3. SETUP

1. **Unboxing:** Carefully remove the Rush Charge Trident from its packaging.
2. **Initial Charge:** Your power bank comes pre-charged. For optimal performance and to ensure maximum battery life, it is recommended to fully charge the device before its first extended use. Connect the integrated USB cable to a USB power adapter (not included) or a computer USB port. The LED indicators will show charging progress.
3. **Familiarization:** Identify the Micro USB, USB-C, and Lightning connectors. Note the LED battery life display on the device.

4. OPERATING INSTRUCTIONS

4.1 Charging Your Device

1. **Select Connector:** Choose the appropriate integrated connector (Micro USB, USB-C, or Lightning) for your device.
2. **Connect Device:** Carefully plug the selected connector into your smartphone, earbuds, or other compatible gadget's charging port.
3. **Charging Indication:** Your device should begin charging automatically. The LED indicators on the power bank will illuminate to show the remaining battery level of the power bank.
4. **Disconnect:** Once your device is charged, carefully disconnect it from the power bank.

4.2 Recharging the Power Bank (Pass-Through Charging)

The Rush Charge Trident features pass-through charging, allowing you to recharge the power bank while simultaneously charging an attached device.

1. **Connect Device:** First, connect your smartphone or device to the power bank using one of the integrated connectors.
2. **Connect Power Bank to Source:** Extend the integrated USB cable from the power bank and plug it into a USB power adapter or a computer USB port.
3. **Simultaneous Charging:** Both your connected device and the Rush Charge Trident will now charge simultaneously.

5. MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the exterior of the power bank. Do not use liquid cleaners or aerosols.
- **Storage:** Store the power bank in a cool, dry place away from direct sunlight and extreme temperatures.
- **Battery Care:** To prolong battery life, avoid fully discharging the power bank frequently. Recharge it when the battery level is low.
- **Connector Care:** Handle the integrated connectors with care to prevent bending or damage.

6. TROUBLESHOOTING

Problem	Possible Cause	Solution
Power bank not charging device.	Power bank battery is depleted. Incorrect connector used. Loose connection. Device not compatible.	Recharge the power bank fully. Ensure the correct Micro USB, USB-C, or Lightning connector is used. Ensure the connector is firmly seated in the device's port. Verify your device is compatible with the power bank's output.
Power bank not recharging.	USB cable not properly connected. Power source issue. Damaged integrated USB cable.	Ensure the integrated USB cable is fully inserted into a working USB port. Try a different USB power adapter or computer USB port. Inspect the integrated USB cable for visible damage. If damaged, contact support.

Problem	Possible Cause	Solution
LED indicators not working.	Power bank is off or fully discharged. Malfunction.	Attempt to recharge the power bank. If the issue persists after charging, contact customer support.

7. SPECIFICATIONS

Feature	Detail
Model Number	RC40
Battery Capacity	4000 Milliamp Hours (mAh)
Connector Types	Micro USB, USB-C, Lightning
Output Current	2.1A (High-Speed Charging)
Product Dimensions	3.5 x 3.75 x 0.63 inches
Item Weight	3.6 ounces
Color	Yellow (as per current product variant)
Special Features	Fast Charging, Portable, Travel, Wireless, Pass-Through Charging
Manufacturer	RUSH CHARGE

8. WARRANTY AND SUPPORT

For product support, troubleshooting assistance, or warranty inquiries, please contact Rush Charge customer service. While specific warranty details are not provided in this manual, standard return policies typically apply for new products.

Please refer to your purchase documentation or the retailer's website for specific return and warranty information applicable to your purchase.

Online Support: Visit the official Rush Charge website for FAQs and support resources. You can often find contact information for customer service there.

Return Policy: As per typical retail policies, a 30-day return period may apply from the date of purchase. Please check with your point of purchase for exact details.

© 2024 Rush Charge. All rights reserved.

This manual is for informational purposes only. Specifications are subject to change without notice.