



Manuals.plus /

› PATPET /

› PATPET P-collar 301S Dog Training Collar User Manual

PATPET P-collar 301S

PATPET P-collar 301S Dog Training Collar User Manual

Model: P-collar 301S (ASIN: B09WYR7N2H)

1. INTRODUCTION

Thank you for choosing the PATPET P-collar 301S Dog Training Collar. This manual provides essential instructions for setting up, operating, and maintaining your training collar system. Please read it thoroughly before use to ensure safe and effective training for your dog(s).

The PATPET P-collar 301S is designed for training dogs weighing 8-100 lbs and features two receivers for training two dogs simultaneously with a single remote. It offers three training modes: beep, vibration, and static stimulation.

Trainer Collars for Beginners



After



Before



Image: Illustrates the potential for improved dog behavior with training collars.

2. SAFETY INFORMATION

- This device is intended for dog training purposes only. Do not use it on aggressive dogs.
- Ensure the collar fits properly. An improperly fitted collar can cause skin irritation or pressure necrosis.
- Do not leave the collar on your dog for more than 12 hours a day.
- Regularly check your dog's neck for any signs of irritation or sores. If found, discontinue use

until the skin heals.

- The remote control is not waterproof. Keep it away from water.

3. PACKAGE CONTENTS

The PATPET P-collar 301S package typically includes:

- 1 x Remote Transmitter
- 2 x Receiver Collars
- 1 x USB Charging Cable (Type-C)
- 1 x Test Light Tool
- 2 x Sets of Contact Points (short and long)
- 2 x Sets of Silicone Caps for Contact Points
- 1 x Wrist Strap for Remote
- 1 x User Manual

4. SETUP

4.1 Charging the Devices

Fully charge both the remote transmitter and receiver collars before first use. The P-collar 301S uses a Type-C charging method and requires approximately 2 hours for a full charge.

Your browser does not support the video tag.

Video: Demonstrates how to open the packaging and charge the remote and receiver collar.

Both are Rechargeable

Long Lasting Battery Life



BEEP



VIBRA



Static
(level 1–16)



Image: Both the remote and receiver are rechargeable, offering long-lasting battery life (10 days work time, 200 days standby time).

4.2 Installing Contact Points and Silicone Caps

Choose the appropriate length of contact points (short for short-haired dogs, long for long/thick-haired dogs) and screw them onto the receiver. For added comfort and to prevent skin irritation, firmly press the silicone caps over the contact points.

Your browser does not support the video tag.

Video: Instructions on how to set up the receiver and test its function before use.

Unique Patented Design



Image: Shows the unique patented design with contact spring sheets, suitable for both long/thick-haired and short-haired dogs.

4.3 Pairing Receivers

The collar set is typically pre-paired by factory setting. If you only use one collar, you may skip this step. To pair new receivers or re-pair existing ones:

1. Ensure the remote's channel button is set to 'Channel 1' for the first receiver.
2. Press and hold the power button on the receiver for 3 seconds until the indicator light flashes.
3. On the remote, simultaneously press both the 'Beep Button' and 'Vibration Button'. The receiver will beep and vibrate, indicating successful pairing.
4. Repeat steps 1-3 for the second receiver, ensuring the remote's channel button is set to 'Channel 2'.

Your browser does not support the video tag.

Video: Detailed instructions on how to pair new receivers with the remote control.

5. OPERATING INSTRUCTIONS

5.1 Training Modes

The PATPET P-collar 301S offers three distinct training modes:

- **Beep Mode:** Delivers an audible tone. Often used as a warning or for positive reinforcement.
- **Vibration Mode:** Provides a gentle vibration. Useful for gaining your dog's attention without static stimulation.
- **Static Stimulation Mode:** Delivers a static pulse with 16 adjustable levels. Use the lowest effective level for your dog.

5.2 Switching Between Dogs

With two receivers, you can easily switch between training Dog 1 and Dog 2 using the channel button on the side of the remote. The remote's display will indicate which channel (1 or 2) is currently active.

5.3 Adjusting Static Levels

The static stimulation level can be adjusted from 1 to 16. Start at the lowest level and gradually increase it until your dog responds with a slight twitch or change in behavior, indicating they feel the stimulation without distress.

6. FITTING THE COLLAR

Proper fit is crucial for the effectiveness and safety of the training collar.

1. Take the collar strap out of the tri-glides buckle.
2. Measure your dog's neck size.
3. After adjusting to the right size, thread the collar strap through the tri-glides buckle and then fasten it.
4. The receiver should be positioned on the underside of your dog's neck, with the contact points touching the skin.
5. **Verification Standard:** When wearing, you should be able to put two fingers just under the collar of the neck. The fit should be snug but not overly tight.
6. Cut off any extra strap with scissors to avoid it being bitten by the dog.

Your browser does not support the video tag.

Video: Demonstrates how to properly adjust and wear the receiver collar on a dog.

Adjustable Collar for 8-100lbs Dogs



8lbs

100lbs



27.5 INCHES TOTAL LENGTH

Image: The collar is adjustable and suitable for dogs from 8 lbs to 100 lbs, with a total length of 27.5 inches.

7. MAINTENANCE

7.1 Waterproofing

The receiver collars are IPX7 waterproof, supporting immersion up to 1 meter underwater for 30 minutes. This makes them suitable for use in rain, during bathing, or swimming. **Note: The remote control is NOT waterproof.**

Your browser does not support the video tag.

Video: Demonstrates how to test the waterproof receiver before use by submerging it in water.

IPX7 Waterproof Receiver Collar

Up to 1000FT Remote Range



Image: The IPX7 waterproof receiver collar is suitable for bathing, swimming, and rainy conditions, with a remote range up to 1000FT.

7.2 Charging Frequency

The devices require charging for approximately 2 hours. With a work time of 10 days and a standby time of 200 days, charge as needed based on usage.

7.3 Regular Inspection

Regularly inspect the contact points and your dog's neck for any signs of wear, damage, or skin irritation. Clean the contact points as needed to ensure proper function and hygiene.

8. TROUBLESHOOTING

- **Collar not responding:** Ensure both the remote and receiver are turned on and fully charged. Check if they are paired correctly.
- **Remote not pairing:** Follow the pairing instructions in Section 4.3 carefully. Ensure the remote is set to the correct channel (1 or 2) for the receiver you are trying to pair.
- **No static stimulation:** Verify the contact points are making proper contact with your dog's skin. Ensure the static level is set appropriately and not too low. Use the test light tool to confirm functionality.
- **Short battery life:** Ensure devices are fully charged. Battery life can vary based on usage frequency and intensity of training modes.

9. SPECIFICATIONS

Feature	Detail
Model	P-collar 301S
Dog Weight Range	8-100 lbs
Number of Receivers	2 (trains 2 dogs with 1 remote)
Training Modes	Beep, Vibration, Static (16 levels)
Waterproof Rating (Receiver)	IPX7 (1 meter for 30 minutes)
Remote Waterproof	No
Charging Type	Type-C
Charging Time	Approx. 2 hours
Work Time	Approx. 10 days
Standby Time	Approx. 200 days
Collar Material	Nylon
Package Dimensions	7.99 x 6.42 x 2.01 inches
Package Weight	14.07 ounces

10. WARRANTY & SUPPORT

10.1 Warranty

The PATPET P-collar 301S comes with a 12-month warranty from the date of purchase. Please retain your proof of purchase for warranty claims.

10.2 Customer Support

For further assistance, troubleshooting, or warranty inquiries, please contact PATPET customer support through the retailer's platform or visit the official PATPET website for contact information.