

## Rush Charge RC25

# Rush Charge Air Portable Charger

Model: RC25

Brand: Rush Charge

## 1. OVERVIEW

---

The Rush Charge Air Portable Charger is a compact and lightweight 2500mAh power bank designed for fast charging Android devices with USB-C compatibility. It provides an additional 19 hours of battery life, making it ideal for on-the-go use. Its cable-free design and pass-through charging technology offer convenience and efficiency.

This portable charger is compatible with a wide range of devices, including Android phones (2018 models and newer), Bluetooth speakers, headphones, gaming controllers, and digital cameras that utilize USB-C.

## 2. KEY FEATURES

---

- **2500mAh Lithium-Ion Battery:** Provides extended power for your devices.
- **Cable-Free Design:** Direct plug-in for convenience, eliminating the need for extra cables.
- **USB-C Compatibility:** Designed for Android devices with USB Type-C ports.
- **Pass-Through Technology:** Allows simultaneous charging of the power bank and your connected device.
- **Compact and Lightweight:** Easy to carry for travel and daily use.
- **Pre-Charged:** Ready to use out of the box.

## 3. SETUP GUIDE

---

### 3.1 Initial Charge

The Rush Charge Air comes pre-charged and ready for immediate use. For optimal performance and to ensure a full charge, it is recommended to fully charge the power bank before its first extended use.

1. Connect the USB-C port of the Rush Charge Air to a compatible USB power adapter (not included) or

a computer's USB port.

2. The LED indicator lights on the power bank will illuminate to show charging progress.
3. Once all four LED lights are solid, the power bank is fully charged.

### 3.2 Connecting to Your Device

The Rush Charge Air features an integrated USB-C connector for direct connection to your Android device.

1. Carefully align the USB-C connector of the Rush Charge Air with the USB-C port on your Android phone or compatible device.
2. Gently insert the connector until it is securely seated. Do not force the connection.
3. Your device should begin charging automatically.



Image: Front view of the Rush Charge Air portable charger, displaying its compact size and the four LED indicator lights that show the battery level.

## 4. OPERATION

---

### 4.1 Charging Your Device

Once connected, the Rush Charge Air will automatically begin charging your compatible Android device. The LED indicator lights on the power bank will show its remaining charge level.

### 4.2 Pass-Through Charging

The Rush Charge Air supports pass-through charging, allowing you to charge both the power bank and your connected device simultaneously. To use this feature:

1. Connect your Android device to the Rush Charge Air.
2. Connect the Rush Charge Air to a power source (e.g., wall adapter, computer USB port) using its USB-C input.
3. Both the power bank and your device will charge concurrently.

### 4.3 Battery Level Indicators

The Rush Charge Air features four LED lights that indicate the remaining battery capacity:

- **4 Lights Solid:** 75% - 100% charged
- **3 Lights Solid:** 50% - 75% charged
- **2 Lights Solid:** 25% - 50% charged
- **1 Light Solid:** 0% - 25% charged (recharge soon)
- **Lights Flashing:** Indicates charging in progress.



Image: The Rush Charge Air portable charger, highlighting its compact design and the visible LED battery indicators.

## 5. CARE AND MAINTENANCE

---

- **Cleaning:** Use a soft, dry cloth to clean the exterior of the power bank. Avoid using harsh chemicals or abrasive materials.
- **Storage:** Store the power bank in a cool, dry place away from direct sunlight, extreme temperatures, and humidity.
- **Battery Longevity:** To prolong the life of the lithium-ion battery, avoid fully discharging it regularly. Recharge the power bank when the battery level is low. If storing for extended periods, charge it to about 50% every few months.
- **Avoid Drops and Impacts:** Protect the device from physical shock, which can damage internal components.
- **Water Exposure:** This device is not waterproof. Keep it away from liquids.

## 6. TROUBLESHOOTING

---

If you encounter issues with your Rush Charge Air, please refer to the table below for common problems and solutions.

Problem	Solution
Device not charging from power bank.	<p>Ensure the power bank is charged (check LED indicators).</p> <p>Verify the USB-C connector is fully inserted into your device.</p> <p>Confirm your device is USB-C compatible.</p> <p>Try restarting your device.</p>
Power bank not charging.	<p>Ensure the charging cable and power adapter are working correctly.</p> <p>Check the USB-C input port for debris.</p> <p>Try a different power source or adapter.</p>
Slow charging.	<p>Ensure the power bank is fully charged.</p> <p>Close unnecessary applications on your device.</p> <p>Avoid using your device heavily while charging.</p>
Power bank gets warm during use.	<p>It is normal for power banks to generate some heat during charging or discharging.</p> <p>If it becomes excessively hot, disconnect it immediately and contact customer support.</p>

## 7. TECHNICAL SPECIFICATIONS

---

Feature	Detail
Model Number	RC25
Battery Capacity	2500 mAh
Battery Type	Lithium Polymer
Input	DC 5V / 2.1A
Output	DC 5V / 2.1A
Connector Type	USB Type C
Item Weight	5 ounces
Package Dimensions	11 x 9 x 0.5 inches
Color	Red



Image: Rear view of the Rush Charge Air portable charger, displaying the brand name and printed technical specifications.

## 8. WARRANTY AND CUSTOMER SUPPORT

---

Rush Charge products are designed for reliability and performance. For information regarding warranty coverage, please refer to the documentation included with your purchase or visit the official Rush Charge website.

If you require technical assistance, have questions about your product, or need to report an issue, please contact Rush Charge customer support. You can typically find contact information on the product packaging, the official brand website, or through the retailer where the product was purchased.

For purchases made on Amazon, you may also refer to the seller information for 'Rush Charge' on the product page for direct support options.

