

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [ieGeek](#) /

› [ieGeek Floodlight Camera ZY-E1 User Manual](#)

ieGeek ZY-E1

ieGeek Floodlight Camera ZY-E1 User Manual

Model: ZY-E1

[Introduction](#) [Components](#) [Setup](#) [Operation](#) [Storage](#) [Alexa](#)
[Integration](#) [Maintenance](#) [Troubleshooting](#) [Specifications](#) [Warranty & Support](#)

1. INTRODUCTION

This manual provides detailed instructions for the installation, operation, and maintenance of your ieGeek Floodlight Camera, Model ZY-E1. This device combines a high-resolution security camera with powerful floodlights to enhance outdoor surveillance and security around your property.

The ieGeek Floodlight Camera features 2K video resolution, 2600 lumens of illumination, advanced motion detection, a 110dB siren, two-way audio communication, and compatibility with Alexa for integrated smart home security. It is designed for wired installation and is rated IP65 for outdoor use.



Image 1.1: The ieGeek Floodlight Camera ZY-E1, a combination of a security camera and two adjustable floodlights.

2. PRODUCT COMPONENTS

Before installation, please ensure all components are present in the package:

- ieGeek Floodlight Camera Unit
- Mounting Bracket
- Mounting Screws and Wall Anchors
- Wire Nuts
- User Manual (this document)

ieGeek

Floodlight Security Camera

2K FHD Customized Brightness



Colorful Night Vision



Siren Alarm



PIR Motion Detect



2600LM Floodlights



2.4G Wi-Fi



Image 2.1: Contents of the ieGeek Floodlight Camera package, including the camera unit, mounting hardware, and user manual.

3. INSTALLATION AND SETUP

The ieGeek Floodlight Camera requires a wired installation to an existing junction box. Professional installation is recommended if you are unfamiliar with electrical wiring.

3.1. Pre-installation Checklist

- Ensure power to the installation area is turned OFF at the circuit breaker.
- Verify you have the necessary tools (screwdriver, drill, ladder, wire strippers).
- Confirm your Wi-Fi network is 2.4GHz. The camera does not support 5GHz Wi-Fi.

3.2. Mounting the Camera

1. Turn off power at the circuit breaker.
2. Remove your existing floodlight or cover plate from the junction box.
3. Attach the mounting bracket to the junction box using the provided screws.
4. Connect the camera's wires to your home's wiring (Live to Live, Neutral to Neutral, Ground to Ground) using the wire nuts.
5. Secure the camera unit to the mounting bracket.
6. Adjust the angle of the floodlights and camera as desired. The camera features a 360° rotatable base for flexible positioning.
7. Restore power at the circuit breaker.

Rotate Light and Camera Freely

Provides a Wider Viewing Angle



Image 3.1: The ieGeek Floodlight Camera installed on an exterior wall, illuminating a driveway.

3.3. App Installation and Wi-Fi Connection

1. Download the "**ieGeek Cam**" or "**CloudEdge**" app from the App Store (iOS) or Google Play Store (Android).
2. Create an account or log in.
3. Follow the in-app instructions to add your new ieGeek Floodlight Camera. This typically involves scanning a QR code on the camera or packaging.
4. Ensure your smartphone is connected to a 2.4GHz Wi-Fi network during the setup process.



Image 3.2: A smartphone screen showing the ieGeek Cam app and options to download from Google Play or the App Store.

4. OPERATING INSTRUCTIONS

The ieGeek Floodlight Camera offers various features accessible through the mobile application to enhance your home security.

4.1. Live View and Recording

- Open the ieGeek Cam or CloudEdge app to access the live feed from your camera.
- You can manually record video or capture screenshots directly from the live view.
- The camera supports 2K FHD video resolution, providing clear and detailed images.

4.2. Motion Detection and Alerts

The camera features a 150° PIR motion sensor to detect movement. You can customize its behavior via the app:

- **Sensitivity Adjustment:** Adjust the PIR detection sensitivity (levels 1-10) to minimize false alarms.
- **Customizable Detection Zones:** Define specific areas within the camera's field of view where motion detection should be active. This helps focus on critical areas and ignore irrelevant movements.
- **Instant Notifications:** Receive real-time alerts on your smartphone when motion is detected.

150° PIR Sensor & 130° View Angle

Up to 25m Colorful Night Vision



Image 4.1: Illustration of the camera's 150-degree PIR motion sensor range and 130-degree viewing angle.



Image 4.2: A smartphone displaying the app interface for setting customized security zones within the camera's view.



Image 4.3: A smartphone screen showing a slider for adjusting motion detection sensitivity within the app.

4.3. Night Vision

The camera provides clear surveillance even in low-light conditions:

- **Color Night Vision:** Equipped with 4 IR lights, the camera intelligently switches to color night vision mode, providing full-color images up to 15 meters (49 feet) in the dark.
- **Infrared Night Vision:** In extremely dark conditions, the camera can utilize infrared for black and white night vision.

Upgraded 2K FHD Colorful Video

Peace of Mind Day and Night




Image 4.4: A comparison showing the clarity and detail of color night vision versus traditional infrared night vision in a parking lot scene.

4.4. Floodlight Control

The integrated 2600 lumens floodlights can be controlled and customized:

- **Motion-Activated:** The lights can be set to turn on automatically when motion is detected.
- **Adjustable Brightness:** Control the brightness of the floodlights via the app.
- **Custom Lighting Plans:** Schedule specific times for the lights to activate or remain off.




Image 4.5: A smartphone screen displaying an interface to adjust the brightness level of the floodlight.



Image 4.6: An illustration of the app's interface for setting a custom security lighting plan, including scheduled on/off times.

4.5. Siren Activation

The camera includes a 110dB siren to deter intruders. It can be activated manually through the app when an event is detected.

Motion Activated Lights & Alarm



Image 4.7: A person reacting to the bright floodlight and audible alarm of the security camera.

4.6. Two-Way Audio

Communicate with visitors or deter unwanted guests using the built-in microphone and speaker. This feature allows for real-time conversation through the app.

Customized Security Zones

For Door, Garden, Car or Pets



Image 4.8: A person speaking into their phone, with a speech bubble indicating communication through the camera, demonstrating the two-way audio feature.

5. VIDEO STORAGE OPTIONS

Your ieGeek Floodlight Camera offers flexible video storage solutions:

- **Free Cloud Storage:** The camera provides a free lifetime cloud storage service for 6-second event recordings with 7 days of loop coverage.
- **Micro SD Card Storage:** Supports a Micro SD card (up to 128GB) for 24/7 continuous recording or event-

triggered recording. The card slot is typically located on the camera unit.



Image 5.1: Visual representation of the available storage options: cloud storage and local Micro SD card storage.

6. ALEXA INTEGRATION

The ieGeek Floodlight Camera is compatible with Amazon Alexa, allowing for voice control and integration into your smart home ecosystem.

- **Voice Commands:** Use voice commands to view your camera feed on compatible Alexa-enabled devices (e.g., "Alexa, show me the front door").
- **Smart Home Routines:** Integrate the camera into Alexa routines for automated actions.



Image 6.1: An Alexa-enabled smart display showing the live feed from the ieGeek Floodlight Camera, demonstrating Alexa compatibility.

7. MAINTENANCE

To ensure optimal performance and longevity of your ieGeek Floodlight Camera, follow these maintenance guidelines:

- **Cleaning:** Periodically wipe the camera lens and floodlight covers with a soft, damp cloth to remove dust, dirt, or water spots. Avoid abrasive cleaners.
- **Weather Resistance:** The camera has an IP65 waterproof rating, meaning it is protected against dust and low-pressure water jets. While designed for outdoor use, avoid directing high-pressure water directly at the unit.
- **Firmware Updates:** Regularly check the app for available firmware updates to ensure your camera has the latest features and security enhancements.

2600 Lumens, Turn Night to Day

Time to Replace Your Traditional Light




Image 7.1: The ieGeek Floodlight Camera being subjected to water spray, illustrating its IP65 waterproof design.

8. TROUBLESHOOTING

If you encounter issues with your ieGeek Floodlight Camera, refer to the following common solutions:

- **Camera Offline:**

- Check your Wi-Fi connection and ensure it is 2.4GHz.
- Restart your Wi-Fi router.

- Ensure the camera is receiving power.
- Relocate the camera closer to your Wi-Fi router if the signal is weak.

- **Motion Detection Not Working:**

- Verify motion detection is enabled in the app settings.
- Adjust the detection sensitivity.
- Check the customized detection zones to ensure the area of interest is covered.

- **Poor Video Quality:**

- Ensure the camera lens is clean.
- Check your internet upload speed.
- Adjust video quality settings in the app if available.

- **Siren Not Activating:**

- Ensure the siren feature is enabled and manually triggered in the app.

For further assistance, please contact ieGeek customer support.

9. SPECIFICATIONS

Feature	Detail
Model Name	ZY-E1
Video Capture Resolution	3 MP (2K FHD)
Field Of View	130 Degrees
Night Vision Range	15 Meters (49 feet)
Floodlight Brightness	2600 Lumens
Siren Volume	110dB
Connectivity Technology	Wired installation, 2.4Ghz Wi-Fi
Controller Type	CloudEdge or ieGeek Cam Phone APP, works with Alexa
Storage Options	Free Cloud (6s/7 days loop), Micro SD Card (Max. 128GB)
Water Resistance Level	IP65 Waterproof
Power Source	Corded Electric (AC 100V~240V)
Item Dimensions (L x W x H)	10.04 x 8.43 x 5.98 inches
Item Weight	2.88 pounds
UPC	734931269914

10. WARRANTY AND SUPPORT

ieGeek is committed to providing reliable products and excellent customer service.

- **Warranty:** Your ieGeek Floodlight Camera comes with a 2-year quality guarantee from the date of purchase.
- **Returns:** A 30-day free returns policy is applicable for eligible purchases.
- **Customer Support:** For any questions, technical assistance, or warranty claims, please contact our professional after-sales team.

After-Sales Email: service@iegeek.com



Image 10.1: Summary of ieGeek's after-sales support, including 24/7 team, 30-day returns, and 2-year quality guarantee.

© 2023 ieGeek. All rights reserved.

Related Documents - ZY-E1

 USER MANUAL <small>Official Email: service@iegeek.com</small>	<p><u>ieGeek ZS-GX4S PTZ Battery Security Camera User Manual</u></p> <p>User manual for the ieGeek ZS-GX4S PTZ Battery Security Camera, covering camera introduction, app installation, account registration, Wi-Fi connection, battery charging, installation guides, PIR motion sensor notes, and FAQs.</p>
 USER MANUAL <small>After-sales Email: service@iegeek.com</small>	<p><u>ieGeek PTZ Outdoor Security Camera User Manual</u></p> <p>User manual for the ieGeek PTZ Outdoor Security Camera, providing setup instructions, features, and troubleshooting.</p>
 USER MANUAL <small>ZY-C2</small> <small>Official Email: service@iegeek.com</small>	<p><u>ieGeek ZY-C2 PTZ Battery Security Camera User Manual</u></p> <p>This user manual provides comprehensive instructions for the ieGeek ZY-C2 PTZ Battery Security Camera, covering setup, installation, features, and troubleshooting.</p>

 USER MANUAL <small>Official Email: service@iegeek.com</small>	<p><u>ieGeek DQ201 PTZ Battery Security Camera User Manual</u></p> <p>Comprehensive user manual for the ieGeek DQ201 PTZ Battery Security Camera, covering introduction, app installation, camera setup, charging, installation guides, PIR motion sensor notes, and FAQs.</p>
 USER MANUAL <small>Official Email: service@iegeek.com</small>	<p><u>ieGeek Floodlight Camera ZY-E1 User Manual</u></p> <p>User manual for the ieGeek Floodlight Camera ZY-E1, covering installation, setup, features, and troubleshooting.</p>
 User manual <small>ZS-GX3S</small>  <small>Sales Email: service@iegeek.com Official website: http://www.iegeek.com</small>	<p><u>ieGeek ZS-GX3S Wire-free Battery Camera User Manual</u></p> <p>User manual for the ieGeek ZS-GX3S wire-free battery camera, covering setup, Wi-Fi connection, charging, installation, and troubleshooting.</p>

Documents - ieGeek – ZY-E1



USER MANUAL

Official Email: service@iegeek.com

[\[pdf\] User Manual](#)

ieGeek ZY E1 2K Floodlight Camera with 2600 Lumens 110dB Siren User Manual V1 0 v 1679586702
 cdn shopify s files 1 0549 9053 6917 |||

...

lang: **score:22** filesize: 9.43 M page_count: 30 document date: 2022-11-18



[\[pdf\]](#) User Manual

ieGeek Floodlight Camera Outdoor 2K Wired Home Smart Security Cameras 2 4G WiFi Flood Light with Motion Sensor Wiring 2600 Lumens Cam Color Night Vision Siren Way Audio Works Alexa Black ZY E1 User Manual B0C788G55L B0BV2GTRJM B0B5QMF1DK C1OK1Rxd5L m media amazon images I |||

...
lang: score:17 filesize: 5.62 M page_count: 28 document date: 2022-10-19

USER MANUAL

Official Email: service@iegeek.com



[\[pdf\]](#)

Download Floodlight Camera ZY E1 Support ieGeek v 1661495353 cdn shopify s files 1 0549 9053 6917
|||

...
lang: score:16 filesize: 5.35 M page_count: 32 document date: 2022-03-04

USER MANUAL

Official Email: service@iegeek.com