

[Manuals.plus](#) /

› [umeiluce](#) /

› UMEILUCE Modern LED Rings Chandelier Round Pendant Light User Manual

umeiluce danquan

UMEILUCE Modern LED Rings Chandelier Round Pendant Light User Manual

Model: danquan

1. INTRODUCTION

Thank you for purchasing the UMEILUCE Modern LED Rings Chandelier Round Pendant Light. This manual provides important information regarding the safe installation, operation, and maintenance of your new lighting fixture. Please read this manual thoroughly before installation and retain it for future reference.

This modern LED pendant light features a creative ring shape, dimmable functionality, and adjustable color temperature, making it suitable for various indoor environments such as living rooms, dining rooms, bedrooms, and offices.

2. SAFETY INFORMATION

- **Electrical Safety:** Always turn off the main power supply at the circuit breaker before beginning any electrical installation or maintenance. Consult a qualified electrician if you are unsure about wiring procedures.
- **Installation:** Ensure the mounting surface can support the weight of the fixture. This fixture is designed for indoor use only.
- **Handling:** Handle the fixture with care to avoid damage to the LED components or acrylic parts.
- **Cleaning:** Use a soft, dry cloth for cleaning. Avoid abrasive cleaners or solvents that may damage the finish or electrical components.
- **Integrated LED:** This fixture uses integrated LED chips. Do not attempt to replace individual LEDs.

3. PACKAGE CONTENTS

Verify that all components are present and undamaged before proceeding with installation.

- LED Rings Chandelier Fixture (1)

- Remote Control (1)
- Mounting Hardware (screws, wire nuts, etc.)
- Instruction Manual (this document)

4. SETUP AND INSTALLATION

This fixture is designed for ceiling mount installation and does not require assembly of the main light body. Professional installation is recommended.

4.1 Before You Begin

- Read all instructions carefully.
- Ensure the power is turned OFF at the circuit breaker.
- Gather necessary tools (screwdriver, wire strippers, ladder, etc.).

4.2 Mounting the Fixture

1. Carefully unpack the fixture and all components.
2. Attach the mounting bracket to the junction box in the ceiling using the provided screws. Ensure the bracket is securely fastened.
3. Connect the electrical wires: Connect the live (black) wire from the fixture to the live (black) wire from the ceiling, the neutral (white) wire from the fixture to the neutral (white) wire from the ceiling, and the ground (green or bare copper) wire from the fixture to the ground wire from the ceiling. Secure connections with wire nuts.
4. Carefully tuck the wires into the junction box.
5. Attach the fixture canopy to the mounting bracket, securing it with the provided screws or nuts.
6. Adjust the suspension cables to achieve the desired hanging height. The cable length is adjustable from 1 inch to 59 inches. Secure the cables once the desired length is set.



Image: The UMEILUCE LED Chandelier installed in a dining room, demonstrating its appearance when mounted.

5. OPERATING INSTRUCTIONS

Once installed, restore power to the fixture at the circuit breaker. The UMEILUCE LED Chandelier is operated using the included remote control.

5.1 Remote Control Functions



Image: The UMEILUCE LED Chandelier shown with its accompanying remote control, highlighting the control method.

- **Power On/Off:** Press the **ON/OFF** button to turn the light fixture on or off.
- **Brightness Adjustment:** Use the **Brightness Up (+)** and **Brightness Down (-)** buttons to adjust the light intensity from 10% to 100%.
- **Color Temperature Adjustment:** Use the **Color Temperature Up (K+)** and **Color Temperature Down (K-)** buttons to change the light color from warm white (3000K) to cool white (6000K).
- **Memory Function:** The fixture typically retains the last brightness and color temperature settings when turned off and on again.

6. MAINTENANCE

- **Cleaning:** To clean the fixture, ensure the power is off. Use a soft, dry, or slightly damp cloth. Do not use harsh chemicals, abrasive cleaners, or sprays directly on the fixture.
- **Inspection:** Periodically check the fixture for any signs of damage or loose connections. If any issues are found, turn off the power and consult a qualified electrician.
- **LED Lifespan:** The integrated LED light source is designed for long-term use and does not require replacement under normal operating conditions.

7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on.	No power to the fixture. Loose wiring connection. Remote control battery depleted.	Check circuit breaker and wall switch. Turn off power, check wiring connections. Replace remote control battery.
Remote control not working.	Battery depleted or incorrectly inserted. Obstruction between remote and fixture.	Replace battery, ensure correct polarity. Ensure clear line of sight to the fixture.
Light flickers or dims unexpectedly.	Loose wiring. Incompatible dimmer switch (if not using remote).	Turn off power, check wiring connections. Ensure only the provided remote is used for dimming.

If the problem persists after attempting these solutions, please contact customer support.

8. SPECIFICATIONS

- **Brand:** umeiluce
- **Model:** danquan
- **Product Dimensions:** 31.4"L x 31.4"W x 60"H (Adjustable cable length: 1" to 59")
- **Material:** Aluminum, Acrylic
- **Color:** White
- **Light Source Type:** Integrated LED
- **Wattage:** 40 Watts
- **Brightness:** 3200 Lumens
- **Efficiency:** 80 lumens/watt
- **Color Temperature:** 3000K-6000K (Adjustable)
- **Voltage:** 110 Volts (AC)
- **Control Method:** Remote Control
- **Mounting Type:** Ceiling Mount
- **Indoor/Outdoor Usage:** Indoor Only
- **Assembly Required:** No (main fixture)
- **Item Weight:** 6.1 pounds
- **UPC:** 774829336250

9. WARRANTY AND SUPPORT

For warranty information, please refer to the documentation provided at the time of purchase or contact your retailer. Specific warranty terms may vary.

If you encounter any issues or require technical assistance, please contact the retailer from whom you purchased this product or the manufacturer directly. Please have your model number (danquan) and purchase details ready when contacting support.