

BUFFALO BRXL-PUS6U3B

BUFFALO MediaStation 6X Portable Blu-ray Drive User Manual

Model: BRXL-PUS6U3B

INTRODUCTION

The BUFFALO MediaStation 6X Portable Blu-ray Drive (Model: BRXL-PUS6U3B) is a versatile external optical drive designed for use with both Windows and Mac computers. This compact and lightweight device allows you to play and burn Blu-ray discs, DVDs, and CDs, providing a comprehensive solution for your optical media needs. It features USB 3.2 (Gen 1) connectivity with both Type-A and Type-C adapters for broad compatibility.

PACKAGE CONTENTS

Verify that all items are present in the package:

- BUFFALO MediaStation 6X Portable Blu-ray Drive
- USB 3.2 (Gen 1) Type-A Cable
- USB Type-A to Type-C Adapter
- User Manual (this document)

SETUP

Connecting the Drive

The drive is bus-powered, meaning it draws power directly from your computer's USB port. No external power adapter is required.

1. Locate an available USB port on your computer (USB Type-A or Type-C).
2. Connect the provided USB 3.2 (Gen 1) Type-A cable to the drive.
3. If your computer has a USB Type-C port, attach the USB Type-A to Type-C adapter to the Type-A end of the cable, then connect it to your computer. If your computer has a USB Type-A port, connect the cable directly.
4. The operating system should automatically detect and install the necessary drivers for the drive.



Image: The BUFFALO MediaStation drive connected to a laptop, illustrating the simple plug-and-play setup.

Software Installation

The drive includes CyberLink Media Suite software for playback and burning of Blu-ray discs, DVDs, and CDs on PC. For Mac users, third-party software may be required for Blu-ray playback and burning.

1. Refer to the included software documentation or the manufacturer's website for instructions on downloading and installing the CyberLink Media Suite.
2. Ensure your computer meets the minimum system requirements for the software.



**BURN & READ
BD/DVD/CD**



**PLAYBACK AND BURNING
SOFTWARE INCLUDED**

PC software included to save money and hassle

Image: The BUFFALO MediaStation alongside a laptop, highlighting that playback and burning software is included for convenience.

OPERATING INSTRUCTIONS

Playing Discs

1. Press the eject button on the front of the drive to open the disc tray.
2. Carefully place the Blu-ray, DVD, or CD onto the disc tray with the label side facing up.
3. Gently push the disc tray back into the drive until it clicks shut.
4. Your operating system or media playback software should automatically detect the disc. Follow the on-screen prompts to play the content.

Burning Discs

To burn data or media to a Blu-ray, DVD, or CD, you will need compatible burning software (e.g., CyberLink Media Suite).

1. Insert a blank, recordable disc (BD-R, BD-RE, DVD-R, DVD+R, CD-R, CD-RW, M-DISC) into the drive as described above.
2. Open your disc burning software.

3. Select the type of project you wish to create (e.g., data disc, video disc, audio CD).
4. Add the files or media you want to burn to the project.
5. Follow the software's instructions to start the burning process. Ensure the process is not interrupted.



Image: The BUFFALO MediaStation with its disc tray extended, showing a Blu-ray disc ready for insertion or removal.

Supported Media Types and Speeds



PLAY AND CREATE DISCS ACROSS MULTIPLE FORMATS

Versatility of the drive allows you to play and record
on all major platforms with ease

Image: Visual representation of the drive's compatibility with Blu-ray, DVD, CD, and M-DISC formats.

Read/Write Speeds

Media Type	Read Speed	Write Speed
Blu-ray	6x	6x
DVD	8x	8x
CD	24x	24x
M-DISC	Supported	Supported



FAST READ AND WRITE SPEEDS

8x Read / Write Speed for Blu-ray
6x Read / Write speed for DVD

Image: The BUFFALO MediaStation with a graphic indicating its fast read and write capabilities.

MAINTENANCE

To ensure optimal performance and longevity of your BUFFALO MediaStation drive, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry, lint-free cloth to wipe the exterior of the drive. Do not use liquid cleaners or abrasive materials. Avoid touching the optical lens inside the disc tray.
- **Disc Handling:** Always handle discs by their edges. Avoid touching the recording surface. Store discs in their cases when not in use to prevent scratches and dust accumulation.
- **Storage:** Store the drive in a cool, dry place away from direct sunlight and extreme temperatures.
- **Ventilation:** Ensure the drive's ventilation openings are not blocked during operation to prevent overheating.

TROUBLESHOOTING

If you encounter issues with your BUFFALO MediaStation drive, refer to the following common problems and solutions:

Common Issues and Solutions

Problem	Possible Cause / Solution
Drive not recognized by computer	<ul style="list-style-type: none">• Ensure the USB cable is securely connected to both the drive and the computer.• Try a different USB port on your computer.• Try a different USB cable if available.• Restart your computer.• Check Device Manager (Windows) or System Information (Mac) to see if the drive is listed.
Disc not playing or burning	<ul style="list-style-type: none">• Ensure the disc is clean and free of scratches or smudges.• Verify that the disc is inserted correctly (label side up).• Check if your playback/burning software is compatible with the disc format and is up-to-date.• For Blu-ray playback, ensure you have compatible software and codecs installed.• Try a different disc to rule out a faulty disc.
Slow read/write speeds	<ul style="list-style-type: none">• Ensure you are using a USB 3.0/3.2 port for optimal performance. Connecting to a USB 2.0 port will result in slower speeds.• Close other applications that might be consuming system resources.• Ensure your computer's drivers are up-to-date.
Drive eject button not working	<ul style="list-style-type: none">• If a disc is currently being accessed by software, you may need to eject it through the software interface first.• Ensure the drive is properly connected and powered.

If the issue persists after trying these solutions, please contact BUFFALO customer support.

SPECIFICATIONS

Product Specifications

Feature	Detail
Brand	BUFFALO

Feature	Detail
Model Number	BRXL-PUS6U3B
Hardware Platform	Mac, PC
Operating System Compatibility	macOS, Windows
Item Weight	15.2 ounces (approx. 431g)
Product Dimensions (LxWxH)	5.8 x 5.4 x 0.6 inches (approx. 14.7 x 13.7 x 1.5 cm)
Hardware Interface	USB 3.2 (Gen 1)
Optical Storage Write Speed (Max)	6x (Blu-ray), 8x (DVD), 24x (CD)
Special Features	M-DISC Support, USB Bus Powered, CyberLink Media Suite (for PC)

WARRANTY AND SUPPORT

Manufacturer's Warranty

This BUFFALO MediaStation 6X Portable Blu-ray Drive comes with a 2-year manufacturer's warranty. Please retain your proof of purchase for warranty claims. The warranty covers defects in materials and workmanship under normal use.

Customer Support


For technical assistance, troubleshooting, or warranty inquiries, please contact BUFFALO's US-based support team:






- Visit the official BUFFALO website for support resources and contact information.
- Refer to the contact details provided in your product packaging.

You can also visit the [BUFFALO Store on Amazon](#) for more product information and support links.

© 2024 BUFFALO Inc. All rights reserved.
Product specifications are subject to change without notice.

Related Documents - BRXL-PUS6U3B

	<p>Buffalo BRXL-16U3 Series Quick Setup Guide</p> <p>Quick setup guide for the Buffalo BRXL-16U3 Series external optical drive, providing essential information for installation and initial use. Features DVD and CD support and compliance with standards like GB/T26572-2011.</p>
---	--

 <p>Buffalo FireWire/USB/eSATA Hard Drive HD-HSQ(V2) User Manual</p> <p>Table of Contents:</p> <ul style="list-style-type: none"> 1. Introduction 2. Recommended Usage 3. Software 4. Troubleshooting 5. Specifications <p>1007-1007-0001</p>	<p>BUFFALO HD-HSQ(V2) User Manual: FireWire, USB, eSATA External Hard Drive Guide</p> <p>Comprehensive user manual for the BUFFALO HD-HSQ(V2) external hard drive. Learn about setup, connectivity (FireWire, USB, eSATA), software utilities, and troubleshooting for this high-performance storage solution.</p>
 <p>Buffalo MiniStation External Hard Drive HD-PUSU3-WR User Manual</p> <p>Americas: www.buffaloamericas.com Europe: www.buffalo-europe.com</p>	<p>Buffalo MiniStation External Hard Drive HD-PUSU3-WR User Manual</p> <p>User manual for the Buffalo MiniStation External Hard Drive HD-PUSU3-WR, covering specifications, software installation, formatting, SecureLockMobile encryption, TurboPC EX speed optimization, Backup Utility, and regulatory compliance information.</p>
 <p>User Manual of Product 1: Sony E-P2 10-100mm F4.0-5.6 ASPH. 1:1. Power Zoom Lens (SEL10100G)</p> <p>User Manual of Product 2: Sony DCR-PC100 10P 6-Megapixel 3.0" LCD 30 fps 7.1:1 Power Lens</p>	<p>Buffalo J300-A Rice Cooker Instruction Manual and Technical Specifications</p> <p>This document provides comprehensive instructions for the Buffalo J300-A Rice Cooker, including safety guidelines, operating procedures, cleaning and maintenance advice, troubleshooting tips, detailed technical specifications, and the declaration of conformity.</p>
 <p>Buffalo LinkStation 200 Series Network Attached Storage Setup Guide</p>	<p>Buffalo LinkStation 200 Series NAS Setup Guide: Installation & Configuration</p> <p>Comprehensive setup guide for Buffalo LinkStation 200 Series Network Attached Storage (NAS) devices, including models like LS210 and LS220. Learn hardware setup, software installation (NAS Navigator2), configuration, Windows/macOS drive mapping, and backup solutions with NovaBackup and Time Machine.</p>
 <p>Buffalo Waffle Maker Instruction Manual</p> <p>Model: DK229</p>	<p>Buffalo DK229 Waffle Maker Instruction Manual</p> <p>Detailed guide for the Buffalo DK229 Waffle Maker, covering safe operation, installation, maintenance, troubleshooting, and technical specifications.</p>