

[Manuals.plus](#) /

› [SYLVANIA](#) /

› SYLVANIA 1 Amp Smart Charger 6V/12V User Manual

SYLVANIA 1 Amp Smart Charger

SYLVANIA 1 Amp Smart Charger 6V/12V User Manual

Model: 1 Amp Smart Charger

1. INTRODUCTION

The SYLVANIA 1 Amp Smart Charger is designed to charge and maintain 6V and 12V lead-acid, lithium-ion, GEL, EFB, AGM, and calcium batteries. This charger features a 9-stage automatic charging cycle and a float mode for long-term battery maintenance. It is suitable for motorcycles, lawnmowers, and small cars, including vehicles with Start/Stop functionality.



The SYLVANIA Smart Charger is compatible with various 6V and 12V battery types, including Lead Acid, Lithium-Ion, GEL, EFB, AGM, and Calcium. It also supports vehicles with Start/Stop functionality. Always examine your battery's label to confirm its type.

2. PRODUCT FEATURES

- **9-Stage Full Auto Charging:** Automatically charges the battery to 100% through a comprehensive 9-stage cycle.
- **Digital Display:** Features a backlit LCD display that shows voltage and charging progress, visible in low light conditions.
- **Single-Button Operation:** Simplifies mode selection for vehicle or motorcycle batteries.
- **Float Mode:** Automatically transitions to a long-term maintenance mode once the battery is fully charged, preventing overcharging.
- **Cold Weather Charging Mode:** Optimizes charging performance and protects batteries in cold temperatures.

8 BATTERY CHARGING MODES

12V			$\leq 14.6V$	$\leq 6A$
12V	 		$\leq 14.8V$	$\leq 6A$
12V	LFP 		$\leq 14.4V$	$\leq 6A$
6V			$\leq 7.2V$	$\leq 3A$
6V	 		$\leq 7.4V$	$\leq 3A$
6V	LFP 		$\leq 7.2V$	$\leq 3A$
12V			$\leq 14.6V$	$\leq 3A$
12V	 		$\leq 14.8V$	$\leq 3A$

Suggested for:



SYLVANIA

The SYLVANIA 1 Amp Smart Charger features a compact design with a single mode button. It supports 6V and 12V batteries and includes advanced functions such as 9-stage full automatic charging, cold weather mode, and float mode for optimal battery maintenance.

3. PACKAGE CONTENTS

Verify that all items are present in the package:

- SYLVANIA 1 Amp Smart Charger Unit
- Alligator Clips (for standard battery terminals)
- O-Ring Terminals (for semi-permanent connection or motorcycle batteries)
- User Manual


COMPATIBLE BATTERY TYPES

1 AMP SMART CHARGER

6V/12V

For motorcycles, lawnmower, and small cars

1-2 amps



Examine your battery's label to determine what type it is. If you can't read or find the label, consult your vehicle's manual, or contact an automotive professional for help.



Compatible with vehicles that have Start / Stop functionality.

Suggested for:



SYLVANIA

The SYLVANIA Smart Charger package includes the main charger unit, a set of alligator clips for standard battery terminals, and O-ring terminals for semi-permanent connection or motorcycle batteries. A user manual is also included.

4. SETUP AND CONNECTION

1. Ensure the charger is unplugged from the AC power outlet before making any connections to the battery.
2. Identify the positive (+) and negative (-) terminals on your battery. The positive terminal is usually marked with a plus sign and is larger than the negative terminal.
3. Connect the red (+) alligator clip or O-ring terminal to the positive (+) battery terminal.
4. Connect the black (-) alligator clip or O-ring terminal to the negative (-) battery terminal. For vehicles, if connecting to the chassis, ensure it is away from the battery and fuel lines.
5. Once the battery connections are secure, plug the charger into a standard 120V AC power outlet.
6. The charger will automatically begin its diagnostic and charging process.



9-Stage Full Auto Smart Charging

Affordably bring your battery back to life with our 9-stage charging and monitoring cycle.



SYLVANIA

Proper connection of the charger to your vehicle's battery is crucial for safe and effective charging. Ensure the charger is securely connected to the battery terminals before plugging it into a power outlet.

5. OPERATING INSTRUCTIONS

5.1. Selecting Charging Mode

The charger features a single mode button to cycle through different charging programs. Press the 'MODE' button to select the appropriate program for your battery type and conditions.

PRODUCT INCLUDES



**LCD BACKLIT DISPLAY
SHOWS VOLTAGE AND
CHARGING PROGRESS**

**ALL SYLVANIA
SMART CHARGERS INCLUDE:**
Alligator Clips, O-Rings, Charger,
and User Manual

The charger offers various modes for different battery types and conditions. Select the appropriate mode (e.g., 12V for cars, 6V for motorcycles, LFP for Lithium Iron Phosphate batteries, or Cold Weather mode for low temperatures) using the mode button.

Available modes typically include:

- **12V Car Mode:** Standard charging for 12V vehicle batteries.
- **12V Cold Weather Mode:** Optimized charging for 12V batteries in temperatures below 5°C (41°F).
- **12V LFP Mode:** Specific charging profile for 12V Lithium Iron Phosphate batteries.
- **6V Motorcycle Mode:** Standard charging for 6V motorcycle batteries.
- **6V Cold Weather Mode:** Optimized charging for 6V batteries in cold temperatures.
- **6V LFP Mode:** Specific charging profile for 6V Lithium Iron Phosphate batteries.

5.2. Charging Process

Once a mode is selected, the charger will initiate its 9-stage charging process. The backlit LCD display will show the current voltage and charging progress. When the battery reaches full charge, the charger will automatically switch to float mode to maintain the battery without overcharging.

Charging times vary based on battery size and discharge level. For example, a 1 Amp charger may take approximately 49 hours to fully charge a small car battery from 50% charge.

Compatibility

Designed for 6V/12V sealed lead, acid, gel, calcium, EFB, AGM, and lithium batteries. Compatible with vehicles that have Start / Stop functionality.



Estimated charging times vary depending on the battery size and its initial charge level. For the 1 Amp SYLVANIA Smart Charger, a small car battery at 50% charge may take approximately 49 hours to fully charge.

6. MAINTENANCE

- Keep the charger clean and dry. Wipe with a soft, damp cloth. Do not use harsh chemicals or abrasive cleaners.
- Inspect cables and connectors regularly for any signs of damage, wear, or corrosion. Replace if necessary.
- Store the charger in a cool, dry place when not in use.
- Ensure battery terminals are clean and free of corrosion for optimal connection.

7. TROUBLESHOOTING

Charger not turning on or displaying information:

Ensure the charger is securely plugged into a working AC outlet. Check battery connections for proper polarity and secure contact. The battery may be too deeply discharged (below 1.5V) for the charger to initiate. Consult a professional if the issue persists.

Battery not charging or charging slowly:

Verify that the correct charging mode is selected for your battery type and voltage. Ensure all connections are clean and tight. A very large or deeply discharged battery will take a long time to charge with a 1 Amp charger. Consider the estimated charging times provided in the manual.

Charger enters float mode too quickly:

This may indicate a faulty battery that cannot hold a charge, or an incorrect mode selection. Have the battery tested by a professional.

8. SPECIFICATIONS

Product Dimensions	3.54 x 3.15 x 8.44 inches
Item Weight	13.7 ounces
Input Voltage	120 Volts AC
Output Voltage	6 Volts DC / 12 Volts DC
Current Rating	1 Amp
Max Battery Capacity (Charging)	30Ah

Max Battery Capacity (Maintenance)	100Ah
Cable Length	7 ft
Screen Type	LCD Screen
ASIN	B0BKMLLTNN
GTIN	04059089342651

PRODUCT FEATURES

Voltage	6V/12V
Charger Rate	Up to 2 amps
Screen	LCD SCREEN
Max Battery Capacity Charging Mode / Maintenance Mode	30aH 100aH
Cable Length	7ft
Float Mode Prevents Overcharging	✓
9-Stage Full Auto Brings Battery Back to Life	✓
Cold Weather Mode Protects Battery in Cold Weather	✓
Start/Stop Compatible Suitable with Start/Stop System	✓

SYLVANIA

This table provides a quick overview of the SYLVANIA Smart Charger's key technical specifications and features, such as its 6V/12V voltage output, 1 Amp current rating, and various charging modes.

9. SAFETY INFORMATION

Always follow these safety guidelines when operating the charger:

- Read all instructions before use.
- Use the charger in a well-ventilated area.
- Do not expose the charger to rain or excessive moisture.
- Avoid charging frozen batteries.

- Do not operate the charger if it has received a sharp blow, been dropped, or otherwise damaged.
- Keep out of reach of children.
- Always disconnect the AC power before disconnecting the battery leads.

10. WARRANTY AND SUPPORT

For warranty information or technical support, please refer to the contact details provided in the product packaging or visit the official SYLVANIA website. Keep your purchase receipt as proof of purchase for warranty claims.