

zhllmq 007-9Y

zhllmq 9-Light Modern Black Crystal Chandelier Instruction Manual

Model: 007-9Y

INTRODUCTION

Thank you for purchasing the zhllmq 9-Light Modern Black Crystal Chandelier. This fixture is designed to provide elegant and efficient lighting for high ceilings, living rooms, staircases, foyers, and entryways. Featuring a modern design with black metal and bubble crystal pendants, it incorporates an integrated LED light source that is dimmable. Please read this manual thoroughly before installation and use to ensure safe and proper operation.

SAFETY INFORMATION

WARNING: To reduce the risk of fire, electric shock, or personal injury, always follow these safety precautions:

- Always disconnect power at the main circuit breaker before installation, removal, or servicing.
- Consult a qualified electrician if you are unsure about the installation process.
- Ensure all electrical connections are made in accordance with local codes and ordinances.
- Do not install this fixture in wet or damp locations. It is designed for indoor use only.
- Handle crystal components with care to prevent breakage.
- Do not exceed the specified voltage (AC110-135V).
- Keep packaging materials away from children.

PACKAGE CONTENTS

Verify that all components are present and undamaged before beginning installation. If any parts are missing or damaged, contact customer support.

- Chandelier Canopy (1)
- Bubble Crystal Pendants with Integrated LED (9)
- Adjustable Hanging Wires (9)
- Mounting Hardware Kit (screws, wire nuts, etc.)



Image 1: Overview of the zhllmq 9-Light Modern Black Crystal Chandelier.

SETUP AND INSTALLATION

Installation of this chandelier requires basic electrical knowledge. If you are not confident in your ability to install it safely, it is highly recommended to hire a qualified professional electrician.

1. Prepare for Installation:

- Turn off power at the circuit breaker.
- Unpack all components and lay them out on a clean, soft surface to prevent scratches.
- Review the provided hardware accessories and instructions.

2. Mount the Canopy:

- Attach the mounting bracket to the junction box in your ceiling.

- Secure the chandelier canopy (15.74" diameter) to the mounting bracket.

3. Adjust Pendant Lengths:

- The hanging wires have a maximum length of 79.92 inches (203 cm).
- Adjust each pendant's cable length by pushing the small pin on the canopy's cable grip and sliding the wire to the desired height. This allows for custom configurations, such as a spiral pattern.
- The crystal column itself is 11.81 inches (30 cm) in height.



Image 2: Example of the chandelier installed in a high-ceiling foyer, showcasing adjustable pendant lengths.

4. Electrical Connections:

- Connect the fixture's wires to your household electrical wires according to standard wiring practices (e.g., black to black, white to white, ground to ground).
- Use the provided wire nuts to secure connections.

5. Final Assembly:

- Tuck all wires neatly into the canopy and secure the canopy to the ceiling.
- Ensure all pendants hang freely and are at their desired lengths.

6. Restore Power:

- Turn the power back on at the circuit breaker.
- Test the chandelier to ensure it functions correctly.

Your browser does not support the video tag.

Video 1: An official video demonstrating the appearance and features of the Black Crystal Foyer Chandelier.

OPERATING INSTRUCTIONS

This chandelier features an integrated LED light source with the following characteristics:

- **Light Output:** 54W, 4320 lumens.
- **Color Temperature:** 6000K (Natural White Light).
- **Dimmable Functionality:** The fixture supports dimming from 5% to 100% brightness. A compatible dimmer switch (not included) must be installed for this feature to work.
- **Control:** The light can be controlled via a standard wall switch or a compatible dimmer switch.



Image 3: Illustration of the chandelier's dimmable range, from 5% to 100% brightness.

MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your chandelier.

- **Cleaning:**
 - Ensure power is off before cleaning.
 - Dust the metal and crystal components with a soft, dry cloth.
 - For stubborn marks on crystal, use a slightly damp cloth with a mild glass cleaner, then wipe dry immediately. Avoid abrasive cleaners.
- **Bulb Replacement:** This fixture uses integrated LED chips and does not require traditional bulb replacement. If the LED light source fails, contact customer support for assistance.

TROUBLESHOOTING

If you encounter issues with your chandelier, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	No power to the fixture.	Check circuit breaker and wall switch.
	Loose wiring connection.	Ensure all wire connections are secure (power off first).
	Faulty wall switch or dimmer.	Test the wall switch or dimmer; replace if necessary.
Light flickers or dims unexpectedly.	Incompatible dimmer switch.	Ensure a compatible LED dimmer switch is used.
	Loose wiring.	Check all wiring connections (power off first).
Some pendants are not lighting up.	Loose connection to individual pendant.	Check connections for the specific pendant (power off first).
	Faulty LED component in pendant.	Contact customer support for replacement parts if an LED component is faulty.

SPECIFICATIONS

Brand	zhllmq
Model Number	007-9Y
Number of Lights	9
Color	Black
Material	Aluminum, Crystal, Metal
Light Source	Integrated LED

Wattage	54W
Brightness	4320 Lumens
Color Temperature	6000K (Natural White)
Dimmable	Yes (5%-100% with compatible dimmer switch, not included)
Voltage	AC110-135V
Canopy Diameter	15.74 inches (40 cm)
Max Hanging Wire Length	79.92 inches (203 cm)
Crystal Column Height	11.81 inches (30 cm)
Indoor/Outdoor Use	Indoor Use Only

WARRANTY AND SUPPORT

The zhllmq 9-Light Modern Black Crystal Chandelier comes with a limited manufacturer's warranty. For specific warranty details, claims, or technical support, please contact zhllmq customer service directly. Keep your purchase receipt as proof of purchase.

Manufacturer: zhllmq

For assistance, please refer to the contact information provided with your purchase or visit the official zhllmq store page on Amazon: [zhllmq Store](#)

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question