

Cecotec TotalPure 1050

Cecotec TotalPure 1050 Portable Ozone Air Purifier User Manual

Model: TotalPure 1050 | Brand: Cecotec

1. INTRODUCTION

This manual provides essential information for the safe and effective operation of your Cecotec TotalPure 1050 Portable Ozone Air Purifier. This device is designed to generate ozone to help eliminate odors, viruses, and bacteria from the environment. Please read these instructions thoroughly before first use and retain them for future reference.

2. SAFETY INSTRUCTIONS

- Do not operate the device in the presence of people, pets, or plants. Ozone should be used in unoccupied spaces.
- Ensure adequate ventilation after ozone treatment before re-entering the treated area.
- Keep the device away from water and moisture. Do not immerse in liquids.
- Do not block the air inlets or outlets during operation.
- Use only the provided USB charging cable or a compatible certified cable.
- Keep out of reach of children.
- Do not attempt to disassemble or repair the device yourself. Contact qualified service personnel.
- Avoid prolonged exposure to high concentrations of ozone.

3. PRODUCT OVERVIEW

The Cecotec TotalPure 1050 is a compact and portable ozone generator. Familiarize yourself with its components:

- **Power Button/Mode Selector:** Located on the top surface.
- **LED Indicator Light:** Surrounds the power button, indicating operating mode and battery status.
- **USB Charging Port:** Located on the front face, below the main button.
- **Air Inlets/Outlets:** Located around the device for ozone dispersion.



Figure 3.1: The Cecotec TotalPure 1050 Portable Ozone Air Purifier in operation, illustrating ozone (O₃) being released to neutralize pollutants.



Figure 3.2: Front view of the device, showing the power button with LED indicator and the USB charging port.



Figure 3.3: Side view of the air purifier, highlighting its compact and portable design.

4. SETUP

1. **Unpack:** Carefully remove the device from its packaging.
2. **Initial Charge:** Before first use, fully charge the device. Connect the USB charging cable to the USB port on the front of the purifier and plug the other end into a compatible USB power adapter (not included) or a computer USB port. The LED indicator will show charging status.
3. **Placement:** Place the device in the desired area for treatment. Ensure the area is unoccupied by people, pets, or plants during operation.



Figure 4.1: Connecting the USB cable to the device for charging. The USB port is located on the front panel.

5. OPERATING INSTRUCTIONS

The TotalPure 1050 features a single button for operation and two distinct operating modes.



Figure 5.1: Detail of the power button and its surrounding LED indicator, which controls the device's functions.

1. **Power On:** Press and hold the power button for approximately 3 seconds until the LED indicator illuminates.
2. **Select Mode:**
 - **Mode 1 (Intermittent):** A single short press of the power button will activate this mode. The device will operate in bursts of 20 minutes, repeating every 6 hours. This mode is suitable for continuous maintenance of air quality in small, enclosed spaces like wardrobes or pantries.
 - **Mode 2 (Continuous):** A second short press of the power button will activate this mode. The device will operate continuously for 40 minutes. This mode is ideal for more intensive treatment of odors or contaminants in areas like bathrooms or small rooms.
3. **LED Indicator:** The LED light around the button indicates the current operating mode and battery status. Refer to the troubleshooting section for specific light patterns.
4. **Power Off:** Press and hold the power button for approximately 3 seconds to turn off the device.

Important: Always ensure the area is unoccupied during ozone generation. Allow for ventilation before re-entering the treated space.



Figure 5.2: The air purifier positioned on a nightstand, demonstrating its discreet placement in a living space.



Figure 5.3: Examples of placement for the air purifier, including inside a refrigerator to eliminate food odors and within a drawer for fabric freshness.

6. MAINTENANCE

Regular maintenance ensures optimal performance and longevity of your device.

- **Cleaning:** Wipe the exterior of the device with a soft, dry cloth. Do not use abrasive cleaners, solvents, or immerse the device in water.
- **Storage:** When not in use for extended periods, store the device in a cool, dry place, away from direct sunlight. Ensure it is fully charged before storage to preserve battery life.
- **No Filter Replacement:** This device does not use replaceable filters.

7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Device does not turn on.	Low battery or no charge.	Charge the device using the USB cable. Ensure the charging cable and adapter are functioning correctly.
LED indicator is flashing.	Low battery warning.	Recharge the device immediately.
No ozone smell or perceived effect.	Device not operating, or area is too large for the device's capacity.	Ensure the device is powered on and in the correct operating mode. For larger areas, consider using the device in smaller, enclosed spaces.
Device turns off unexpectedly.	Low battery.	Recharge the device.

8. SPECIFICATIONS

- Model:** TotalPure 1050
- Item Model Number:** 01790
- Brand:** Cecotec
- Ozone Output:** 20 mg/hour
- Power:** 3 Watts
- Battery Capacity:** 1800 mAh
- Charging:** USB
- Product Dimensions:** 25.9D x 14W x 5H Centimeters
- Item Weight:** 420 g
- Controller Type:** Button Control
- Special Feature:** Portable design with USB charging, timer with two modes, and low battery warning indicator

9. WARRANTY AND SUPPORT

Cecotec products are manufactured to high-quality standards. For information regarding warranty coverage, technical support, or service, please refer to the warranty card included with your purchase or visit the official Cecotec website. Please have your model number (TotalPure 1050) and item model number (01790) available when contacting support. For further assistance, you may visit the [Cecotec brand page on Amazon](#) or the official Cecotec website.

