

[Manuals.plus](#) /

› [JUMMICO](#) /

› JUMMICO Electric Height Adjustable Desk 160 x 70 cm with USB Charging Port - User Manual

JUMMICO 0183

JUMMICO Electric Height Adjustable Desk

MODEL: 0183 (160 x 70 cm) - USER MANUAL

Brand: JUMMICO

1. Introduction

The JUMMICO Electric Height Adjustable Desk is designed to promote a healthier and more productive work environment by allowing seamless transitions between sitting and standing positions. This manual provides essential information for assembly, operation, maintenance, and troubleshooting to ensure optimal use of your desk.



Image: JUMMICO Electric Height Adjustable Desk in a modern office setting.

Key Features:

- **Ergonomic Design:** Seamlessly switch between sitting and standing to reduce fatigue and improve posture. Height is continuously adjustable from 73 cm to 118 cm.
- **Electric Height Adjustment & USB Charging:** Easy one-touch height adjustment with two memory presets. Includes a convenient USB charging port for devices.
- **Stable Construction:** Features a robust metal frame with wide T-shaped feet for enhanced stability. Industrial-grade steel and durable laminate ensure longevity.
- **Thoughtful Design:** Integrated cable management hub, headphone/bag hook, low standby power consumption, and quiet operation (below 55 dB).

2. Setup and Assembly

Follow these steps carefully to assemble your JUMMICO Electric Height Adjustable Desk. An installation video is provided for visual guidance.

Your browser does not support the video tag.

Video: JUMMICO Electric Standing Desk Installation Guide. This video demonstrates the step-by-step assembly process of the desk.

Assembly Steps:

1. **Unpack and Identify Parts:** Carefully unpack all components and compare them with the parts list in your included manual. Ensure all hardware is present.
2. **Assemble the Crossbar:** Connect the two halves of the crossbar (B9) using the provided screws (f M4) and align them properly.

3. **Attach Lifting Columns:** Secure the lifting columns (B1, B2) to the crossbar (B9) using the specified screws (a).
4. **Install Feet:** Attach the feet (B7) to the bottom of the lifting columns using screws (b).
5. **Assemble Desktop Panels:** Connect the desktop panels (B3, B4, B5, B6) using the wooden dowels (e) to ensure a seamless fit.
6. **Secure Desktop to Frame:** Place the assembled desktop onto the frame. Use the provided screws (d) to secure the desktop panels to the frame, ensuring all connection plates (B14, B15) are used.
7. **Connect Drive Rod:** Insert the drive rod (B10) between the two lifting columns and connect it to the motor mechanism.
8. **Install Control Panel:** Mount the control panel (B16) to the underside of the desk using screws (d) and connect the necessary cables.
9. **Connect Power Adapter:** Plug the power adapter (B17) into the control panel and then into a power outlet.
10. **Cable Management:** Use the provided cable ties (g) to organize and secure all cables neatly under the desk.
11. **Install Headphone Hook:** Attach the headphone hook (B12) to the desired location on the desk frame.
12. **Insert Cable Pass-Through:** Place the cable pass-through cover (B13) into the designated hole on the desktop.



Upgraded Desk Frame Construction



Image: Detailed view of the desk frame construction, highlighting features like cable clips and reinforced beams.

3. Operating Instructions

Your JUMMICO Electric Height Adjustable Desk features an intuitive control panel for easy height adjustments and additional functionalities.

Your browser does not support the video tag.

Video: JUMMICO Electric Standing Desk in use, demonstrating height adjustment and ergonomic benefits.



Image: Multi-function intelligent keypad with labeled buttons.

- **LED Display:** Shows the current desk height in centimeters.
- **Up/Down Buttons (+/-):** Press and hold to smoothly adjust the desk height upwards or downwards. Release the button to stop at the desired height.
- **Memory Presets (1/2):**
 - a. Adjust the desk to your desired height.
 - b. Press the 'M' button, then press '1' or '2' to save the current height to that memory slot.

c. To recall a saved height, simply press '1' or '2'. The desk will automatically move to the programmed position.

- **Sedentary Reminders (Clock Icon):** Activate this feature to receive periodic reminders to change your working position. Consult the full manual for specific settings.
- **USB Charging Port:** Located on the side of the control panel, this port allows you to conveniently charge your electronic devices.

Safety Features:

- **Anti-Collision Function:** The motor system is equipped with an anti-collision feature. If the desk encounters an obstacle during adjustment, it will stop and slightly reverse to prevent damage.
- **Overheat Protection:** The motor includes overheat protection to prevent damage from prolonged or excessive use. If activated, allow the motor to cool down before resuming operation.

4. Maintenance

Proper maintenance ensures the longevity and optimal performance of your JUMMICO Electric Height Adjustable Desk.

- **Cleaning:** Wipe the desktop and frame with a soft, damp cloth. Avoid abrasive cleaners or harsh chemicals that could damage the surface.
- **Cable Management:** Periodically check and re-secure cables to prevent tangling or damage.
- **Tighten Screws:** Over time, screws may loosen. Periodically check and tighten all assembly screws to maintain stability.
- **Avoid Overloading:** Do not exceed the maximum weight capacity of the desk (60 kg) to prevent damage to the motor and frame.

5. Troubleshooting

If you encounter any issues with your desk, refer to the following common troubleshooting tips. If the problem persists, please contact customer support.

- **Desk Not Moving:**
 - Check if the power cable is securely connected to both the desk and the power outlet.
 - Ensure there are no obstructions preventing movement.
 - If an error code is displayed, refer to the full manual for specific code meanings and solutions.
- **Desk Movement is Uneven or Jerky:**
 - Perform a reset procedure (usually involves pressing and holding the down button until the desk reaches its lowest point, then releasing and pressing again until it moves slightly up). Refer to your full manual for exact reset instructions.
 - Ensure the desk is not overloaded and weight is evenly distributed.
- **Noise During Operation:**
 - A slight motor hum is normal. If the noise is excessive, check for loose components or obstructions.
 - The desk is designed for quiet operation (below 55 dB).

6. Specifications



Wide Height Range

Height adjustable from **73** to **118**cm

50min Sitting
10min Standing



Image: Wide height range of the JUMMICO desk, from 73 cm to 118 cm.

Feature	Detail
Brand	JUMMICO
Model Number	0183
Color	White
Product Dimensions (L x W x H)	160 x 70 x 73-118 cm

Material	Wood (Laminate top), Metal (Frame)
Special Features	Height Adjustable, Electric, USB Charging Port, Anti-Collision
Item Weight	25 Kilograms
Noise Level	Below 55 dB
Max Load Capacity	60 kg

7. Warranty and Support

JUMMICO products are manufactured with quality and customer satisfaction in mind. This product comes with a manufacturer's warranty against defects in materials and workmanship.

- **Warranty Information:** Please refer to the warranty card included with your product for specific terms and conditions.
- **Customer Support:** For technical assistance, replacement parts, or any other inquiries, please contact JUMMICO customer service through the retailer where you purchased the product or visit the official JUMMICO website.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

