Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

DOINOW T1

DOINOW T1 Electric Cordless Screwdriver

User Instruction Manual

1. Product Overview

The DOINOW T1 Electric Cordless Screwdriver is a versatile and compact tool designed for various household and office repair tasks. It features an intelligent LCD screen displaying real-time information, precise torque control, and a comprehensive set of magnetic bits. Its ergonomic design and integrated LED light enhance usability in diverse environments.



Figure 1: DOINOW T1 Electric Cordless Screwdriver with its included magnetic bit set and charging cable.

2. Package Contents

Verify that all items listed below are included in your package:

- 1x Cordless Electric Screwdriver
- 1x Portable Case
- 1x USB-C Charging Cable
- 1x User Manual
- 30x Screwdriver Bits (various types and sizes)



Figure 2: All components included in the DOINOW T1 Electric Cordless Screwdriver package.

3. Setup

3.1. Charging the Battery

The screwdriver is equipped with a built-in 2200mAh Lithium-ion battery. Before first use, or when the battery is low,

charge the device using the provided USB-C charging cable. The LCD screen will display the battery status, indicating charging progress.

- Connect the USB-C cable to the charging port on the screwdriver.
- Connect the other end of the cable to a compatible USB power adapter (not included).
- A full charge takes approximately 120 minutes. The battery indicator on the LCD screen will show full bars when charging is complete.



Figure 3: The screwdriver's USB-C charging port and battery life indicator on the LCD screen.

3.2. Inserting Screwdriver Bits

The screwdriver uses 1/4" (6.35mm) magnetic bits. Select the appropriate bit for your task and insert it firmly into the chuck.

- Choose the desired magnetic bit from the 30 included accessories.
- Push the bit firmly into the hexagonal chuck at the front of the screwdriver until it is securely seated. The magnetic connection will hold the bit in place.



Figure 4: A selection of the 30 magnetic CR-V bits provided with the screwdriver.

4. Operating Instructions

4.1. Powering On/Off and Direction Control

The screwdriver is activated by pressing the trigger. A red button on the top allows for easy direction changes.

- To activate the screwdriver, press the main trigger located on the handle.
- To select the rotation direction (forward for screwing, reverse for unscrewing), use the red direction push button located near the top of the handle. The LCD screen will indicate the selected direction.
- Release the trigger to stop operation.



Figure 5: The red button for switching between screw (forward) and unscrew (reverse) modes.

4.2. Adjusting Torque

The DOINOW T1 offers 6 electric torque settings, ranging from 1.5 to 4.0 N.m, and a manual torque option of 6 N.m. This allows for precise control suitable for various materials and tasks.

- Rotate the adjustment knob at the rear of the screwdriver to cycle through the 6 torque levels.
- The selected torque level will be displayed on the LCD screen.

- Choose a lower torque setting for delicate materials or small screws to prevent damage. Use higher torque for larger screws or tougher materials.



Figure 6: Internal view of the adjustable torque mechanism and its display.

4.3. Using the LED Light

The screwdriver features an auto-on, shadow-free round LED light to illuminate your work area, ensuring visibility even in dimly lit spaces.

- The LED light automatically activates when the trigger is pressed.
- The light will remain on for approximately 10 seconds after the trigger is released to provide continued illumination.

4.4. Applicable Scenarios

This screwdriver is ideal for a wide range of tasks, including:

- Furniture assembly and disassembly.
- Installing and repairing air conditioners, faucets, and light fixtures.
- Working on desktop computers and other electronics.
- General home, office, and apartment repairs.



Figure 7: Examples of the screwdriver being used for furniture assembly, appliance repair, and general household tasks.

5. Maintenance

Proper maintenance ensures the longevity and optimal performance of your DOINOW T1 Electric Cordless Screwdriver.

- **Cleaning:** Regularly wipe the screwdriver body with a soft, dry cloth to remove dust and debris. Do not use abrasive

cleaners or immerse the device in water.

- **Bit Care:** Keep the magnetic bits clean and dry. Store them in the provided portable case to prevent loss and corrosion.
- **Battery Storage:** If storing the screwdriver for an extended period, ensure the battery is partially charged (around 50%) to maintain battery health. Recharge it every 3-6 months.
- **General Storage:** Store the screwdriver in a cool, dry place, away from direct sunlight and extreme temperatures.

6. Troubleshooting

If you encounter issues with your screwdriver, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Screwdriver does not turn on.	Low or depleted battery.	Charge the battery fully using the USB-C cable.
Screwdriver lacks power/torque.	Incorrect torque setting; Low battery.	Adjust torque to a higher setting; Recharge the battery.
Bit slips or does not engage screw.	Incorrect bit type/size; Worn bit; Bit not fully inserted.	Ensure correct bit for screw head; Replace worn bits; Re-insert bit firmly into chuck.
LED light not working.	Device malfunction.	Contact customer support if charging and trigger activation do not resolve the issue.

If the problem persists after trying the suggested solutions, please contact DOINOW customer support for further assistance.

7. Specifications

Feature	Specification
Brand	DOINOW
Model Name	T1
Material	Aluminum Alloy; CRV-Steel
Color	Maountain Gray
Power Source	Battery Powered (Lithium Ion)
Battery Capacity	2200mAh
Rated Voltage	3.6 Volts
Wattage	7.4 Watt-hours
Max Torque	6 N.m (Manual); 1.5-4.0 N.m (Electric)

Feature	Specification
No-load Speed	220 RPM
Head Size	1/4" (6.35mm) Hex
LED Screen	Digital display for power and torque setting
LED Light	6-ring shadowless LED lights
Item Dimensions (L x W x H)	6.89 x 2.17 x 6.89 inches
Item Weight	1.83 Pounds
Included Components	1x Cordless Electric Screwdriver, 1x Portable Case, 1x USB-C Charging Cable, 1x User Manual, 30x Screwdriver Bits

8. Warranty and Support

DOINOW provides a **2-year free warranty and replacement** for this product. For any inquiries, technical support, or warranty claims, please contact DOINOW customer service through the following channels:

- **Email:** support@doinowtools.com
- **Online Support:** Visit the official DOINOW website for FAQs and additional resources.

Please retain your purchase receipt as proof of purchase for warranty purposes.

© 2023 DOINOW. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0BWY29F8N

More documents and user manuals: **https://manuals.plus/**