

[Manuals.plus](#) /

> [Pyhodi](#) /

> Pyhodi Solar Power Bank User Manual

Pyhodi Fugacalpw03u7ba9t

Pyhodi Solar Power Bank User Manual

Model: Fugacalpw03u7ba9t

1. PRODUCT OVERVIEW

The Pyhodi Solar Power Bank is a high-capacity 30000mAh portable charger designed for outdoor enthusiasts. It combines multiple charging technologies, including solar, wired, and wireless charging, to keep your devices powered in various environments. Its durable construction ensures reliability in challenging conditions.



The Pyhodi Solar Power Bank, featuring a robust design with an integrated solar panel and wireless charging area.



The power bank showcasing its powerful LED light and multiple output ports for versatile charging.

2. PRODUCT FEATURES AND COMPONENTS

- **High Capacity Battery:** 30000mAh lithium battery for extended power supply.
- **Solar Panel:** Enlarged monocrystalline silicon 1.8W solar panel for emergency charging.
- **Wireless Charging:** 10W wireless charging capability.
- **Multiple Output Ports:** Four output ports (3x USB-A, 1x USB-C) supporting simultaneous charging of up to 5 devices.
- **Fast Charging:** Supports PD fast charging.
- **LED Light with SOS Function:** Integrated powerful LED light for illumination and an SOS signaling mode.
- **Durable Construction:** Made from ABS and silicone materials, making it waterproof, dustproof, and

unbreakable.



Detailed view of the wireless charging pad and the LED light panel.



The solar panel on the back of the power bank, along with the included USB cable and lanyard.

3. SETUP

Before first use, it is recommended to fully charge the power bank using a wall adapter via the USB-C input port. This ensures the internal battery is calibrated and ready for optimal performance.

1. **Initial Charging:** Connect the provided USB cable to the power bank's input port and a compatible USB wall adapter (not included).
2. **Indicator Lights:** Observe the charging indicator lights (if present) to monitor the charging progress. The lights will typically stop blinking or turn solid when fully charged.
3. **Lanyard Attachment:** Attach the included lanyard to the designated loop on the power bank for convenient carrying.

4. OPERATING INSTRUCTIONS

4.1 Charging the Power Bank

- **Via USB:** Connect the power bank to a USB wall charger or computer using the USB cable. The input is 5V/2A.
- **Via Solar Panel:** Place the power bank in direct sunlight. The solar panel will convert sunlight into electrical energy to charge the internal battery. Solar charging is primarily for emergency use and supplemental charging due to its slower speed (1.8W).

RECHARGE VIA SOLER POWER



The power bank utilizing its solar panel for charging in an outdoor environment.

4.2 Charging Your Devices

- **Wired Charging:** Connect your device to one of the power bank's output ports (USB-A or USB-C) using a compatible charging cable. The output ports are: USB(A3): 5V/3A; USB(A1)/(A2): 5V/3A, 9V/2A, 12V/1.5A.
- **Wireless Charging:** Place your Qi-compatible device (e.g., smartphone) on the wireless charging pad located on the power bank's surface. Ensure the device is centered for optimal charging. The wireless charging output is 10W.

10W Wireless Charger

Get up to a 10W wireless charge for a wide range of compatible devices anywhere



LED flashlight in high brightness, SOS function
4 Output Ports

Wireless charging in progress, with a smartphone placed on the power bank's charging pad.



adopt ABS and silicone material

Perfect for hiking, camping, fishing, beaches, travel.

Demonstration of wireless charging while holding the power bank.

4.3 Using the LED Light and SOS Function

The power bank features a powerful LED light for illumination and an SOS signaling mode.

- **To Turn On/Off LED:** Press and hold the power button for approximately 3 seconds.
- **To Activate SOS Mode:** While the LED light is on, quickly double-press the power button. The light will flash in an SOS pattern (three short, three long, three short flashes).
- **To Exit SOS Mode:** Double-press the power button again.

5. MAINTENANCE

- **Cleaning:** Wipe the power bank with a soft, dry cloth. Do not use harsh chemicals or abrasive cleaners.
- **Storage:** Store the power bank in a cool, dry place away from direct sunlight and extreme temperatures. For

long-term storage, ensure the battery is charged to approximately 50-70% to preserve battery life.

- **Water Resistance:** While waterproof, avoid prolonged submersion in water. Ensure all port covers are securely closed when exposed to water or dust.

6. TROUBLESHOOTING

Problem	Possible Cause	Solution
Power bank not charging	Loose cable connection; faulty cable/adaptor; power bank fully charged.	Check all connections; try a different cable/adaptor; check battery indicator.
Device not charging from power bank	Power bank low on charge; incorrect cable; device not compatible; loose connection.	Recharge power bank; use original device cable; ensure device is compatible; check connections.
Wireless charging not working	Device not Qi-compatible; device not centered; thick phone case; foreign objects.	Ensure device supports Qi wireless charging; reposition device; remove phone case; remove metal objects.
Solar charging is slow	Insufficient sunlight; solar panel is small and designed for emergency/supplemental use.	Place in direct, strong sunlight; use USB charging for faster results.

7. SPECIFICATIONS

Feature	Detail
Model Number	Fugacalpw03u7ba9t
Battery Capacity	30000mAh (Lithium Battery)
Solar Panel	Monocrystalline Silicon 1.8W
Input	5V / 2A
Output USB (A3)	5V / 3A
Output USB (A1)/(A2)	5V/3A, 9V/2A, 12V/1.5A
Wireless Charging Output	10W
Product Dimensions	160 x 75 x 26 mm (6.30 x 2.95 x 1.02 inches)
Weight	Approx. 490g / 17.28oz

Feature	Detail
Material	ABS, Silicone
Color	Yellow
Compatible Devices	OS X Phone and Tablet, other brands of mobile phones, MP3, MP4, and other digital products

8. PACKAGE CONTENTS

The following items are included in the package:

- 1 x Pyhodi Solar Power Bank
- 1 x USB Cable
- 1 x Lanyard
- 1 x User Manual (this document)





The USB cable and lanyard included with your power bank.

9. WARRANTY AND SUPPORT

For warranty information and customer support, please refer to the seller's policy on the platform where the product was purchased or contact the manufacturer directly. Keep your purchase receipt as proof of purchase.

For technical assistance or inquiries, please visit the official Pyhodi website or contact their customer service department.