

ALOADECOR A7084D8004A

ALOADECOR 14-Light 31" Glam Empire Crystal Chandelier
Instruction Manual

Model: A7084D8004A

Safety Information	What's in the Box	Specifications	Setup & Installation	Operation	Maintenance
		Troubleshooting	Warranty & Support		

1. SAFETY INFORMATION

Please read and understand all instructions before beginning assembly and installation. Failure to do so could lead to electric shock, fire, or other injuries that could be fatal or cause serious damage.

- **WARNING:** Risk of electric shock. Disconnect power at the main circuit breaker or fuse box before installation or servicing.
- **WARNING:** This fixture is intended for indoor use only.
- **WARNING:** Professional installation is recommended.
- Ensure all electrical connections are in accordance with local codes and ordinances, as well as the National Electric Code (NEC).
- Use only the recommended bulb type and wattage. (14 x 4W G9 LED Bulbs, 4000K - Bulbs not Included). Maximum compatible wattage: 40 Watts per bulb.
- Do not connect this fixture to an ungrounded electrical system.
- Do not attempt to alter the fixture in any way.
- Keep flammable materials away from the light fixture.

2. WHAT'S IN THE BOX

Carefully unpack the contents and ensure all parts are present and undamaged. If any parts are missing or damaged, do not attempt to assemble or install the fixture. Contact customer support for assistance.

- Chandelier Fixture (with Crystal Beads Accents)
- Mounting Hardware
- Shade (Crystal)

- Steel Wire (Adjustable length)
- *Note: G9 LED Bulbs are not included and must be purchased separately.*



Image 1: ALOADECOR 14-Light 31 inch Glam Empire Crystal Chandelier. This image shows the complete chandelier fixture with its crystal bead accents and the soft gold finish.

3. PRODUCT SPECIFICATIONS

Brand	ALOADECOR
Model Name	A7084D8004A
Product Dimensions	31.5"L x 31.5"W x 5.1"H
Material	Crystal, Iron
Color	Soft Gold

Light Source Type	LED (G9 base)
Number of Light Sources	14
Bulb Requirement	14 x 4W G9 LED Bulbs, 4000K (Not Included)
Maximum Compatible Wattage	40 Watts per bulb
Voltage	110 Volts (AC)
Installation Type	Flush Mount
Power Source	Hardwire
Adjustable Drop Length	10" - 65" (Steel wire length: 59")
Item Weight	27.5 Pounds
Indoor/Outdoor Usage	Indoor
Assembly Required	No

Product Size



DIMMING INFORMATION



This fixture is dimmable when used with compatible wall dimmer and dimmable light bulbs.

NOT INCLUDED

BULB INFORMATION



14 x G9 Bulbs

The fixture used 14*G9 (Bi-Pin) bulbs.

NOT INCLUDED

Image 2: Detailed product dimensions including the 32-inch diameter, 5-inch height, and 78-inch adjustable wire. Bulb information specifies 14 x G9 (Bi-Pin) bulbs are required and not included. Dimmability is also noted.

4. SETUP & INSTALLATION

Important: Professional installation is recommended for this hardwired fixture. Ensure power is disconnected at the circuit breaker before proceeding.

4.1 Pre-Installation

1. Turn off electricity at the main fuse box or circuit breaker.
2. Carefully unpack all parts from the carton.
3. Identify and inspect all parts against the "What's in the Box" section.
4. Determine the desired hanging height for the chandelier. The steel wire length is adjustable from 10" to 65".

4.2 Mounting the Fixture

1. Attach the mounting bracket to the junction box in the ceiling using the provided screws.
2. Connect the electrical wires:
 - Connect the bare copper ground wire from the fixture to the ground wire from the junction box.
 - Connect the white wire from the fixture to the white (neutral) wire from the junction box.
 - Connect the black wire from the fixture to the black (hot) wire from the junction box.
 - Secure all connections with wire nuts and electrical tape.
3. Carefully tuck all wires into the junction box.
4. Attach the canopy of the chandelier to the mounting bracket, securing it with the decorative nuts.
5. Adjust the steel suspension wires to achieve the desired hanging height.

4.3 Bulb Installation

1. Insert 14 G9 LED bulbs (not included) into the sockets. Ensure bulbs are securely seated.



Image 3: The ALOADECOR chandelier suspended from the ceiling, showcasing its adjustable hanging mechanism and overall appearance when installed.

5. OPERATION

Once installed and bulbs are in place, restore power at the circuit breaker.

- **Turning On/Off:** Operate the chandelier using your wall switch.
- **Dimming:** This fixture is dimmable when used with a compatible wall dimmer and dimmable G9 LED light bulbs (both not included). Consult a qualified electrician for dimmer installation.
- **Light Color:** The light color (e.g., soft white, warm white, daylight) depends on the G9 LED bulbs you choose. The product is designed for 4000K bulbs for a soft white light.

6. CLEANING & MAINTENANCE

Regular cleaning will help maintain the appearance and performance of your chandelier.

- **Cleaning:** Wipe the fixture with a soft, dry cloth.
- **Avoid:** Do not use any cleaners, abrasive materials, or solvents, as these can damage the finish and crystal components.
- **Bulb Replacement:** Ensure power is off before replacing bulbs. Allow bulbs to cool completely before handling.



Image 4: A close-up view of the faceted crystal glass beads that wrap the steel frame of the chandelier, emphasizing the intricate detail and reflective quality.

7. TROUBLESHOOTING

If you experience issues with your chandelier, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
---------	----------------	----------

Problem	Possible Cause	Solution
Light does not turn on.	• Power is off at the circuit breaker. • Loose wire connections. • Bulbs are faulty or not installed correctly.	• Check the circuit breaker and ensure power is on. • Verify all wire connections are secure (ensure power is off first). • Replace bulbs or ensure they are fully screwed into sockets.
Light flickers.	• Loose bulb. • Incompatible dimmer switch or bulbs.	• Tighten bulbs. • Ensure dimmer and bulbs are compatible with each other and the fixture.
Chandelier hangs unevenly.	• Uneven adjustment of suspension wires.	• Adjust the steel suspension wires to balance the fixture.

If the problem persists after attempting these solutions, please contact customer support.

8. WARRANTY & SUPPORT

8.1 Warranty Information

This ALOADECOR chandelier comes with a **1-year warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use. It does not cover damage resulting from improper installation, accident, misuse, abuse, or unauthorized modifications.

8.2 Customer Support

For technical assistance, warranty claims, or to report missing/damaged parts, please contact ALOADECOR customer support through the retailer where the product was purchased or visit the official ALOADECOR store on Amazon:

[Visit the ALOADECOR Store on Amazon](#)

Please have your model number (A7084D8004A) and proof of purchase available when contacting support.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0C3CQ67TZ>

More documents and user manuals: <https://manuals.plus/>