

## TESSAN 636DV

# TESSAN 65W GaN Universal Travel Adapter (Model 636DV) Instruction Manual

## 1. INTRODUCTION

---

This manual provides instructions for the safe and efficient use of your TESSAN 65W GaN Universal Travel Adapter, Model 636DV. This device is designed to provide power to your electronic devices in various countries worldwide.

Key features include:

- **65W USB-C Universal Travel Adapter:** Features 3 USB-C ports and 2 USB-A ports. A single USB-C port can deliver a maximum output of 65W. This adapter supports efficient charging.
- **All-in-1 Universal Travel Plug:** This adapter integrates EU, UK, AU, and US plug types. It is compatible with power outlets in numerous countries and regions, including Europe, the United States, the United Kingdom, Germany, Asia, Thailand, Australia, China, Japan, Israel, Italy, and Colombia.
- **Compact Design:** Measuring 7.7 x 5.4 x 5.3 cm, this international travel adapter is designed for portability. It can charge up to 6 devices simultaneously.
- **Dual Fuse Protection:** The adapter includes two overload fuses. A spare fuse is provided for replacement if needed. This dual fuse system enhances safety.

## 2. PRODUCT OVERVIEW

---

The TESSAN Universal Travel Adapter combines multiple international plug types and USB charging ports into a single compact unit. It features one AC outlet, three USB-C ports, and two USB-A ports.

# All in 1

USA/UK/EU/Australia/China/Canada/Ireland/  
Thailand/Japan/Italy/Colombia/Maldives



1 AC



3 USB C



2 USB A



Image: The TESSAN Universal Travel Adapter, illustrating its 'All in 1' capability with various international plug types (USA, UK, EU, Australia, China, Canada, Ireland, Thailand, Japan, Italy, Colombia, Maldives) and its 1 AC outlet, 3 USB-C ports, and 2 USB-A ports.

## 3. SETUP

1. **Identify the Correct Plug:** Based on your travel destination, slide out the appropriate plug type (US, EU, UK, or AU) from the adapter body. Ensure only one plug type is extended at a time.
2. **Connect to Power Outlet:** Insert the extended plug into the wall socket.
3. **Connect Devices:** Plug your electronic devices into the AC outlet or the available USB-C/USB-A ports.

## 4. OPERATING INSTRUCTIONS

The adapter allows simultaneous charging of up to 6 devices (1 AC, 3 USB-C, 2 USB-A). The total DC output is 65W.

- **AC Outlet:** Use for devices requiring a standard wall plug. Ensure the device's voltage is compatible with the local power supply (100-250V).
- **USB-C Ports:** These ports support fast charging. One USB-C port can deliver up to 65W, suitable for laptops, tablets, and smartphones.
- **USB-A Ports:** These ports are suitable for charging various USB-powered devices like smartphones, smartwatches, and power banks.



Image: The TESSAN Universal Travel Adapter plugged into a wall socket, simultaneously charging a laptop, a tablet, and a smartphone, demonstrating its multi-device charging capability.

# USB C Charging Port 65W MAX

USB C fast charging saves time



Image: The TESSAN Universal Travel Adapter with a USB-C cable connected to a smartphone, displaying a '75% Charged' notification and indicating '65W MAX' charging capability.

## 5. SAFETY INFORMATION & IMPORTANT NOTES

**Important Note: This device is NOT a voltage converter.** It is suitable only for dual-voltage or global devices with an input voltage range of 100-250V. It does not perform voltage conversion or frequency modification. Using it with devices that are not dual-voltage or do not match the local voltage can damage your device or the adapter.

- Always check the voltage requirements of your devices before plugging them into the adapter.
- Do not exceed the maximum power rating of the adapter (e.g., 1000W at 100V, 2500W at 250V).
- Avoid using the adapter in wet environments.

- Keep out of reach of children.

## Applicable Power and Equipment

# 100V~250V 50/60HZ



Note: This is NOT a CONVERTER.



Image: The TESSAN Universal Travel Adapter highlighting its applicable power range of 100V-250V, 50/60Hz, and explicitly stating: "Note: This is NOT a CONVERTER." It also shows icons of devices (hair dryer, straightener, electric shaver) that should not be used if they are not dual-voltage.

# Double Fuses

Security protection for travel



Image: A transparent view of the TESSAN Universal Travel Adapter, showcasing its internal components, specifically highlighting the two 10A fuses for double protection.

## 6. MAINTENANCE

### 6.1 Fuse Replacement

The adapter is equipped with two 10A overload fuses. If the adapter stops functioning, one of the fuses may have blown. A spare fuse is included for replacement.

1. Locate the fuse compartment on the adapter.
2. Carefully open the compartment.
3. Remove the blown fuse and replace it with the spare 10A fuse.

4. Close the compartment securely.

## 6.2 Cleaning

To clean the adapter, disconnect it from the power outlet and all devices. Wipe the exterior with a dry, soft cloth. Do not use liquid cleaners or immerse the adapter in water.

## 7. TROUBLESHOOTING

---

- **Adapter not powering on:**
  - Ensure the adapter is fully plugged into the wall outlet.
  - Check if the fuse needs replacement (refer to Section 6.1).
- **Device not charging:**
  - Verify that your device is properly connected to the adapter.
  - Confirm that your device is dual-voltage and compatible with the local power supply.
  - Check if the charging cable is functional.
  - Ensure the total power draw does not exceed the adapter's maximum rating.
- **Slow charging:**
  - Ensure you are using a high-quality charging cable.
  - If multiple devices are connected, the power output may be distributed, leading to slower charging for individual devices.
  - For optimal fast charging, use a single USB-C port for high-power devices.

## 8. SPECIFICATIONS

---

Feature	Specification
Model Number	636DV
Brand	TESSAN
Input Voltage	100-250V AC
Input Frequency	50/60Hz
AC Outlet Output	Max 10A (1000W at 100V, 2500W at 250V)
USB-C Output	3 ports, up to 65W max per port (total DC output 65W)
USB-A Output	2 ports, 5V/2.4A (12W max)
Total DC Output	65W
Plug Types	Type A (US), Type C (EU), Type G (UK), Type I (AU)
Dimensions	7.7 x 5.4 x 5.3 cm
Color	White

## Indispensable for Travel

Compact design make travel more convenient



Image: The TESSAN Universal Travel Adapter placed next to a laptop and earbuds, with dimensions (7.7cm, 5.4cm, 5.3cm) highlighted, emphasizing its compact and portable design for travel.

### 9. WARRANTY AND SUPPORT

For warranty information or technical support, please refer to the product packaging or contact TESSAN customer service through their official website or the retailer where the product was purchased. Please retain your proof of purchase for warranty claims.

