

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

Manuals.plus /

› [Schonbek](#) /

› Schonbek Baronet BN1236N-401O 7-Light Bath Vanity & Wall Light Instruction Manual

Schonbek BN1236N-401O

Schonbek Baronet BN1236N-401O 7-Light Bath Vanity & Wall Light Instruction Manual

Model: BN1236N-401O

INTRODUCTION

This manual provides detailed instructions for the installation, operation, and maintenance of your Schonbek Baronet BN1236N-401O 7-Light Bath Vanity & Wall Light. Please read all instructions carefully before beginning installation and retain this manual for future reference.

The Schonbek Baronet fixture features a durable stainless steel frame adorned with hundreds of crystal octagons, available with Optic or Radiance Crystals. This fixture is designed for indoor use only.

IMPORTANT SAFETY INFORMATION

- **WARNING:** Risk of electric shock. Disconnect power at the fuse box or circuit breaker before installation or servicing.
- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with proper electrical wiring connections.
- This fixture is intended for indoor use only. Do not expose to water or moisture.
- Ensure the mounting surface can support the weight of the fixture.
- Do not exceed the maximum wattage specified for the bulbs.
- Wear safety glasses and gloves during installation.
- Keep children away from the work area during installation.

PACKAGE CONTENTS

Verify that all components are present before beginning installation:

- Lighting Fixture
- Mounting Hardware
- Instruction Sheets (this manual)
- Manufacturer Warranty Certificate

- Certificate of Authenticity

Note: Light bulbs (7 x E12 base, G16.5 shape 120V, 40W max incandescent or LED) are sold separately and are not included in the package.

SETUP AND INSTALLATION

Tools Required (Not Included): Screwdriver, wire strippers, electrical tape, safety glasses, gloves.

1. Prepare for Installation:

- Turn off power at the main circuit breaker or fuse box.
- Carefully unpack the fixture and all components. Place them on a clean, soft surface to prevent scratches.

2. Mounting the Fixture:

- Attach the mounting bracket to the electrical junction box using the provided screws. Ensure the bracket is securely fastened.
- Connect the fixture's wires to the house wires:
 - Connect the black wire (hot) from the fixture to the black wire from the junction box.
 - Connect the white wire (neutral) from the fixture to the white wire from the junction box.
 - Connect the green or bare copper wire (ground) from the fixture to the ground wire from the junction box.

Secure all connections with wire nuts and electrical tape.

- Carefully tuck all wires into the junction box.
- Align the fixture with the mounting bracket and secure it with the provided screws.

3. Crystal Assembly:

The crystal octagons require assembly and pinning. Refer to the included instruction sheets for detailed diagrams on how to attach each crystal element to the fixture frame. Handle crystals carefully to avoid breakage or fingerprints.



Image: The Schonbek Baronet 7-Light Bath Vanity Light with Clear Optic Crystals, showcasing its intricate design and crystal arrangement.

4. **Install Bulbs:**

Screw in 7 E12 base, G16.5 shape 120V light bulbs (max 40W incandescent or LED, sold separately) into the sockets. Do not overtighten.

5. **Restore Power:**

Once installation is complete, turn the power back on at the main circuit breaker or fuse box.

OPERATING INSTRUCTIONS

This fixture operates via a standard wall switch (not included). If connected to a compatible dimmer switch, the light output can be smoothly and continuously dimmed.

- **Turning On/Off:** Use the wall switch connected to the fixture to turn the light on or off.
- **Dimming (Optional):** If a compatible dimmer switch is installed, adjust the dimmer control to achieve the desired brightness level. Ensure that the installed bulbs are dimmable.

CARE AND MAINTENANCE

Proper care will ensure the longevity and beauty of your Schonbek Baronet fixture.

- **Cleaning the Fixture Frame:**

Wipe the stainless steel frame with a soft, dry, or slightly damp cloth. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.

- **Cleaning the Crystals:**

The crystals can be cleaned with a soft, lint-free cloth. For a deeper clean, a mild glass cleaner can be sprayed onto the cloth (not directly onto the crystals or fixture) and then gently wiped. Ensure no liquid drips into electrical components.

CRYSTAL SELECTIONS



RADIANCE CRYSTAL

Our finest crystal offering in cut, color, and clarity, Radiance™ by Schonbek is characterized by optical purity and prism



OPTIC CRYSTAL

Created to enhance internal light refraction, the Optic Crystal used in Schonbek luminaires catapults new designs into the future



Image: A close-up view of the precision-engineered Optic Crystals, highlighting their facets and clarity.

- **Bulb Replacement:**

Always turn off power at the circuit breaker before replacing bulbs. Allow bulbs to cool completely before touching. Replace with E12 base, G16.5 shape 120V bulbs, not exceeding 40W per bulb.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on.	No power to the fixture. Loose wire connections. Faulty bulb(s). Faulty wall switch.	Check circuit breaker/fuse. Verify all wire connections are secure (power off). Replace bulb(s). Test wall switch or consult an electrician.

Problem	Possible Cause	Solution
Light flickers or dims improperly.	Loose bulb. Incompatible dimmer switch or bulbs. Loose wire connection.	Tighten bulb(s). Ensure dimmer and bulbs are compatible (dimmable LED bulbs with LED dimmer). Check wire connections (power off).
Crystals appear dull or dirty.	Dust or residue buildup.	Clean crystals as per the "Care and Maintenance" section.

SPECIFICATIONS

- **Model Number:** BN1236N-401O
- **Brand:** Schonbek
- **Dimensions (L x W x H):** 35"L x 6.5"W x 6.5"H
- **Weight:** 18 Pounds
- **Material:** Stainless Steel frame, Crystal shade
- **Finish:** Polished Stainless Steel
- **Crystal Type:** Clear Optic Crystals (as per current product variant)
- **Number of Lights:** 7
- **Bulb Base:** E12
- **Bulb Type:** G16.5 shape 120V (Incandescent or LED)
- **Max Wattage per Bulb:** 40W
- **Total Wattage:** 280 watts (if using 40W bulbs)
- **Voltage:** 120 Volts
- **Brightness:** 1960 Lumen (total, if using 40W incandescent equivalent)
- **Installation Type:** Flush Mount
- **Indoor/Outdoor Usage:** Indoor use only
- **Certifications:** UL, cUL, CSA rated for indoor locations
- **Control Method:** Wall Switch

WARRANTY INFORMATION

This Schonbek Baronet fixture is covered by a **5-year manufacturer's warranty**. Please refer to the included Manufacturer Warranty Certificate for full terms and conditions. Retain your proof of purchase for warranty claims.

CUSTOMER SUPPORT

If you have any questions regarding the installation, operation, or maintenance of your Schonbek Baronet fixture, please contact Schonbek customer service. Refer to the contact information provided on your warranty certificate or visit the official Schonbek website for support.

Website: www.schonbek.com

