

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

LENCENT PA055W-120W

LENCENT 120W International Travel Adapter User Manual

Model: PA055W-120W

PRODUCT OVERVIEW

The LENCENT 120W International Travel Adapter is a versatile all-in-one solution designed for global travelers. It features multiple interchangeable plugs and supports a wide voltage range, making it compatible with electrical outlets in over 200 countries. Equipped with advanced GaN III technology, this adapter provides efficient and fast charging for a variety of devices, including phones, tablets, and laptops, while incorporating multiple safety protections.



Image: Front view of the LENCENT 120W International Travel Adapter, showcasing its USB-A and three USB-C ports, along with the 120W GaN III Tech branding.

SETUP AND PLUG TYPES

This universal travel adapter comes with 4 interchangeable plugs to ensure compatibility in various regions. To select the correct plug type, simply slide the corresponding slider on the side of the adapter until the desired prongs extend fully.

- **Type C (EU Plug):** Used in Europe, France, Germany, and many other countries.
- **Type G (UK Plug):** Used in the United Kingdom, Dubai, and other regions.
- **Type I (AUS Plug):** Used in China, Australia, and other countries.
- **Type A (USA Plug):** Used in the USA, Japan, and other regions.

Universal Travel Adapter

Applicable to more than 200 countries

EU Plug (Type C)



UK Plug (Type G)



US Plug (Type A)



AUS Plug (Type I)



Image: Visual representation of the LENCENT Universal Travel Adapter demonstrating its compatibility with EU (Type C), UK (Type G), US (Type A), and AUS (Type I) plug types.

Important Note:

This adapter is NOT a voltage converter. Ensure your device is compatible with the local voltage (100V-250V) before plugging it in, especially for high-power devices like hair dryers or straighteners. Using devices not compatible with the local voltage may cause damage to the device or the adapter.

OPERATING INSTRUCTIONS

The LENCENT 120W International Travel Adapter allows you to charge up to 5 devices simultaneously through its combination of AC outlet and USB ports. It utilizes advanced GaN III technology for efficient and fast charging.

Charging Devices

- **AC Outlet:** The universal AC outlet supports devices up to 10A / 2500W Max.
- **USB-C Ports (C1, C2, C3):** Three PD3.0 Type C ports deliver up to 100W individually. These are ideal for fast charging laptops (e.g., MacBook), tablets, and compatible smartphones.
- **USB-A Port (A1):** One QC USB-A port provides up to 18W, suitable for phones, smartwatches, and other smaller devices.

Charge 5 Devices at Once



Image: The LENCENT adapter connected to multiple devices (laptop, phone, earbuds) demonstrating its 5-in-1 charging capability.

Fast Charging Capabilities

The 120W USB-C output supports USB PD 3.0, QC 4+, and PPS protocols, ensuring optimized charging speeds for a wide range of compatible devices. For example, an iPhone 15 Pro can be charged to 88% in approximately 30 minutes using a USB-C port.

120W Super Fast Charging PD 3.0



Image: A graphic illustrating the 120W super fast charging capability with PD 3.0, showing power levels from 18W to 120W.

MAINTENANCE AND SAFETY

The LENCENT travel adapter is built with multiple safety features to ensure reliable charging and protect your devices.

- Dual 10A Fuse:** The adapter includes a dual 10A fuse for overload protection. A spare fuse is typically included for easy replacement.
- Fireproof Material:** Constructed from fireproof materials for enhanced safety.
- Short-Circuit Protection:** Prevents damage from electrical shorts.
- Over-Voltage Protection:** Safeguards devices from excessive voltage.
- Over-Temperature Protection:** Monitors and regulates internal temperature to prevent overheating.



Image: A visual showing the dual 10A fuse and icons representing short-circuit and over-temperature protection.

TROUBLESHOOTING

- No Power Output:** Check if the adapter is securely plugged into the wall outlet. Verify that the correct country-specific prongs are fully extended. If the adapter has a fuse, check if it needs replacement.
- Slow Charging:** Ensure your device and charging cable support fast charging protocols (PD3.0, QC4+, PPS). Using non-compatible cables or devices may result in slower charging speeds.
- Adapter Feels Loose in Outlet:** Some outlets may have looser connections. Ensure the adapter is firmly seated. If

the issue persists across multiple outlets, contact support.

- **Device Not Charging:** Confirm that your device's power requirements are within the adapter's specifications (100V-250V, Max 2500W). Remember, this adapter is not a voltage converter.

SPECIFICATIONS

Feature	Detail
Model Number	PA055W-120W
Input Voltage	100-250V~, 50/60Hz, 10A Max
Max Power Output	2500W Max
USB-C Output (C1/C2/C3)	5V=3A, 9V=3A, 12V=3A, 15V=3A, 20V=5A (100W Max per port)
USB-A Output (A1)	5V=3A, 9V=2A, 12V=1.5A (18W Max)
Total DC Output	120W Max
Product Dimensions	3.62 x 2.13 x 2.13 inches
Item Weight	9.9 ounces (280 Grams)
Technology	GaN III

WARRANTY AND SUPPORT

LENCENT products are manufactured with high-quality standards. For any product-related inquiries, technical support, or warranty claims, please contact LENCENT customer service. Refer to the product packaging or the official LENCENT website for the most current contact information.

This product is covered by a standard manufacturer's warranty. Please retain your proof of purchase for warranty service.