

BANTI CA-B-SDE-SS

BANTI 55"x24" Adjustable Height Standing Desk with Drawers

Model: CA-B-SDE-SS

INTRODUCTION

The BANTI Height Adjustable Electric Standing Desk is designed to enhance your workspace by allowing seamless transitions between sitting and standing positions. This ergonomic design aims to alleviate neck, shoulder discomfort, and back pain often associated with prolonged sitting. It features two large drawers for organized storage, contributing to a tidy desktop environment.



Image: BANTI 55x24 Standing Desk with Drawers, showcasing its design and features.

Safety Information

To ensure safe operation and prevent potential hazards, please adhere to the following guidelines:

- Do not exceed the maximum weight recommendation of 176 pounds (80 kg).
- Ensure the desk is properly anchored to the floor to prevent tipping.
- Follow all assembly instructions carefully.

Package Contents

Before beginning assembly, verify that all components are present:

- 1 Installation Instruction Manual
- 2 Drawers
- Headphone Hook
- Installation Tools (Allen wrench, screws, etc.)
- Monitor Stand (integrated shelf)

Assembly Instructions

For a detailed visual guide, please refer to the official installation video below. The following steps summarize the assembly process.

Your browser does not support the video tag.

Video: Official BANTI Standing Desk Assembly Instructions. This video provides a step-by-step guide for assembling your new standing desk, including frame setup, desktop attachment, and initial calibration.

Step 1: Frame Installation

1. Place the packaging box on the floor to protect the desk components during assembly.
2. Identify Leg A and Leg B. Insert the motor rod into Leg A and Leg B, ensuring the motor faces upwards.
3. Attach the crossbar to the legs. Ensure the side with four larger holes faces towards the end of the pillars and the side facing the floor is correctly oriented.
4. Insert screws to secure the crossbar to the legs. Do not fully tighten the screws yet.
5. Attach the foot pads to the bottom of the legs.
6. Fully tighten all screws for the frame assembly.

Step 2: Desktop Installation

1. Attach the metal plates to the underside of the desktop sections using screws.
2. Insert wooden dowels into the designated holes on the desktop sections.
3. Assemble the desktop sections, ensuring the dowels align correctly.
4. Use the packaging box to support the desktop during installation to maintain balance.
5. Carefully place the assembled desktop onto the frame, aligning the pre-drilled holes.
6. Secure the desktop to the frame using the provided screws.
7. Install the headphone hook and cable management clips.
8. Connect the motor cable to the control box and the power adapter. Ensure the controller is placed on the same side as the motor.
9. Insert the fabric drawers into the storage shelf.

Step 3: Initial Reset (Before First Use)

After installation, a reset procedure is required for proper function:

1. Peel off any protective film from the control panel.
2. Press and hold the 'Up' (↑) and 'Down' (↓) buttons simultaneously for 5 seconds.
3. The desk will move to its lowest position and then slightly upward, indicating the reset is complete.

OPERATING INSTRUCTIONS

Height Adjustment

Use the 'Up' (↑) and 'Down' (↓) buttons on the control panel to adjust the desk height. The desk has a height adjustment range of 27.36 inches to 45.06 inches.

Convenient Controller



Up/Down Buttons



2 Memory Presets

Image: The desk's control panel with Up/Down buttons and memory presets.

Memory Presets

The control panel features two memory presets (1 and 2) to save your preferred sitting and standing heights. To set a memory position:

1. Adjust the desk to your desired height.
2. Press and hold the '1' or '2' button for 3 seconds until you hear a beep or see the display flash, indicating the height is saved.
3. To recall a saved height, simply press the corresponding '1' or '2' button.

Anti-Collision Function

The motorized system includes an anti-collision function. If the desktop encounters an obstruction during height adjustment, it will automatically stop and slightly rebound in the opposite direction to prevent damage to the desk or objects.




Image: Illustration of the anti-collision technology, showing the desk stopping upon encountering an obstacle.

MAINTENANCE

To maintain the appearance and functionality of your BANTI Standing Desk:

- Wipe surfaces with a damp cloth. Avoid harsh chemicals or abrasive cleaners.
- Regularly check all screws and connections to ensure they remain tight.
- Keep the motor and electrical components free from dust and moisture.

TROUBLESHOOTING

If you encounter any issues with your desk, please try the following:

- **Desk not moving:** Check all cable connections, especially the power adapter and motor cable. Ensure the power outlet is functional. Perform the reset procedure (Step 3 in Assembly Instructions).
- **Uneven height:** Perform the reset procedure. If the issue persists, check for any obstructions or damage to the lifting columns.
- **Unusual noises:** Ensure all screws are tightened. If the noise persists, discontinue use and contact customer support.

For further assistance, please contact BANTI customer support.

SPECIFICATIONS



Feature	Detail
Brand	BANTI
Model Number	CA-B-SDE-SS
Product Dimensions	24"D x 55"W x 27.6"H
Color	Maple
Base Material	Alloy Steel
Top Material Type	Wood
Special Features	Adjustable, Adjustable Height, Easy assembly, Ergonomic, Sturdy
Minimum Height	27.6 Inches
Maximum Weight Recommendation	176 Pounds
Number of Drawers	2
Lifting Mechanism	Electric
Required Assembly	Yes
Recommended People for Assembly	2

WARRANTY AND SUPPORT

This BANTI product comes with a limited warranty. For specific warranty details or to inquire about extended protection plans, please refer to your purchase documentation or contact BANTI customer support.

For any questions, technical support, or service requests, please visit the [BANTI Store on Amazon](#) or contact the seller directly.

Related Documents - CA-B-SDE-SS

	<p>BANTI Standing Desk Assembly Instructions</p> <p>Comprehensive assembly instructions for the BANTI 48"x24" Standing Desk with Monitor Stand and Double Storage Shelves. Includes detailed steps, parts list, and troubleshooting for height-adjustable desks.</p>
	<p>Assembly Instructions for BANTI Electric Standing Desk</p> <p>Detailed assembly instructions, user guide, and technical specifications for the BANTI electric height-adjustable standing desk. Includes parts list, safety precautions, operation details, and troubleshooting.</p>
