

Xech Quest PRO

XECH Quest PRO Table Lamp User Manual

Model: Quest PRO (X-305)

INTRODUCTION

The XECH Quest PRO is a versatile 4-in-1 desk essential designed to enhance your workspace. It integrates a dimmable LED table lamp, a 15W wireless charger, a pen stand, and dual USB charging ports into a single, compact unit. This manual provides instructions for setup, operation, maintenance, and troubleshooting to ensure optimal use of your device.

PRODUCT OVERVIEW

The XECH Quest PRO combines multiple functionalities for a clutter-free and efficient desk environment.

- **4-in-1 Design:** Table lamp, wireless charger, pen stand, and USB charging hub.
- **15W Wireless Charging:** Fast charging for compatible smartphones.
- **Dual USB Ports:** One USB-C output and one USB-A output for wired charging.
- **Dimmable LED Lamp:** Two color modes (4500K-6500K) with adjustable brightness.
- **Flexible Gooseneck:** Allows for precise light positioning.
- **Integrated Pen Stand:** Keeps stationery organized.
- **Multi-Layer Protection:** Includes overload, over-voltage, and short-circuit protection.

What's in the Box

- 1 x Quest PRO Wireless Charging Pad
- 1 x USB C Power Cable
- User Manual



Image: The XECH Quest PRO Table Lamp, showcasing its multi-functional design.

SETUP INSTRUCTIONS

1. **Unpack the Device:** Carefully remove all components from the packaging.
2. **Connect Power:** Insert the provided USB-C power cable into the USB-C input port on the back of the Quest PRO unit. Connect the other end of the USB-C cable to a compatible 5V 3A or 9V 3A power adapter (adapter

sold separately).



Image: Connecting the USB-C power cable to the XECH Quest PRO.

3. **Placement:** Place the Quest PRO on a stable, flat surface, such as a desk or table. Ensure adequate ventilation around the device.

OPERATING INSTRUCTIONS

Lamp Operation

1. **Power On/Off:** Lightly touch the power icon (circle with a vertical line) on the lamp head to turn the lamp on or off.



Image: Touch sensor for lamp control and flexible gooseneck, demonstrating light modes.

2. **Adjust Brightness:** While the lamp is on, press and hold the power icon to smoothly dim or brighten the light. Release when the desired brightness is achieved.
3. **Change Color Mode:** Briefly tap the power icon (without holding) to cycle between the two available color temperature modes (4500K - 6500K).
4. **Adjust Lamp Position:** The flexible gooseneck allows you to bend and position the lamp head to direct light precisely where needed.

Charging Features

1. **Wireless Charging:** Place your Qi-compatible smartphone or device on the wireless charging pad located at the base of the unit. Ensure the device is centered on the pad for optimal charging. The charging indicator light will illuminate to confirm charging.



Image: Multiple devices charging simultaneously on the XECH Quest PRO.

2. **USB Charging:** Connect your devices using their respective USB cables to the USB-A or USB-C output ports located within the pen stand. These ports provide up to 2.1A maximum output.



Image: Smartphone on the wireless charging pad, demonstrating video viewing while charging.

3. **Simultaneous Charging:** The Quest PRO can charge up to three devices simultaneously (one wirelessly, two via USB ports).

Pen Stand / Organizer

Utilize the integrated pen stand to store pens, pencils, markers, scissors, and other small stationery items, helping to keep your desk tidy.



Image: The pen stand and stationery holder with deeper pockets for organization.

SAFETY INFORMATION

- Do not disassemble, repair, or modify the product.
- Keep the device away from water, moisture, and high temperatures.
- Avoid dropping or subjecting the device to strong impacts.
- Use only the provided USB-C cable and a compatible power adapter (5V 3A / 9V 3A).

- Do not place metal objects on the wireless charging pad, as this may interfere with charging or cause overheating.
- Ensure proper ventilation when using the device.
- This product is designed for indoor use only.

MAINTENANCE

- **Cleaning:** Disconnect the power before cleaning. Use a soft, dry cloth to wipe the surface of the device. Do not use liquid cleaners or abrasive materials.
- **Storage:** When not in use for extended periods, store the device in a cool, dry place away from direct sunlight.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Lamp does not turn on.	No power connection or faulty power adapter.	Ensure the USB-C cable is securely connected and the power adapter is functional. Use a 5V 3A or 9V 3A adapter.
Wireless charging is not working or intermittent.	Device not properly aligned, phone case too thick, or incompatible device.	◦ Ensure your device is Qi-compatible and centered on the charging pad. ◦ Remove thick phone cases or cases with metal components. ◦ Check if the charging indicator light illuminates. ◦ Ensure the power adapter meets the 5V 3A / 9V 3A requirement.
USB charging ports are not working.	Loose cable connection, faulty USB cable, or power adapter not providing sufficient power.	◦ Ensure USB cables are securely connected to both the device and the Quest PRO. ◦ Try a different USB cable. ◦ Verify the power adapter is providing sufficient power (5V 3A / 9V 3A).
Lamp brightness or color mode cannot be adjusted.	Incorrect operation of the touch sensor.	For brightness, press and hold the touch sensor. For color mode, tap the touch sensor briefly.

SPECIFICATIONS

Feature	Detail
Brand	Xech
Model Name	Quest PRO Lamp with Wireless Charger
Model Number	X-305

Feature	Detail
Connector Type	USB Type C (Input)
Input Voltage	9 Volts (DC)
Current Rating	3 Amps
Wireless Output	15W Fast Charging
USB Output	2.1A Max (USB-A, USB-C)
Total USB Ports	2 (1x USB-A, 1x USB-C)
Lamp Wattage	3W
Number of LEDs	20
Colour Temperature	4500K - 6500K
Lumens	20-400 (approx.)
Special Features	Automatic Off, Charging Indicator, Fast Charging, Wireless Charging
Mounting Type	Tabletop Mount
Enclosure Material	Plastic
Item Weight	150 Grams
Country of Origin	India
Certification	BIS

WARRANTY AND SUPPORT

Warranty: The XECH Quest PRO comes with a 1-year warranty. Customers can register their warranty on the brand's official website or contact customer support via WhatsApp or phone call for assistance.

Contact Information:

- **Manufacturer:** XECH TECHNOLOGIES PVT LTD
- **Address:** JAI SHREE RAM COMPLEX BLDG NO-F-4/2, 2nd FLOOR GALA NO 201,NEXT MONGINIS CAKE FACTORY, ANJUR MANKOLI ROAD, DAPODE VILLAGE, BHIWANDI -421302
- **Email Support:** support@xech.com