

[Manuals.plus](#) /

› [CANMEIJIA](#) /

› CANMEIJIA Wall Sconce 2-Light (Model CMJ-BD-001) Instruction Manual

CANMEIJIA CMJ-BD-001

CANMEIJIA Wall Sconce 2-Light Instruction Manual

Model: CMJ-BD-001

INTRODUCTION

Thank you for choosing the CANMEIJIA Wall Sconce 2-Light fixture. This modern lighting solution is designed to enhance various indoor spaces such as bedrooms, living rooms, bathrooms, kitchens, hallways, and porches. Featuring a matte black finish and milky white glass shades, this fixture provides versatile illumination. Please read this manual thoroughly before installation and use to ensure safe and proper operation.

SAFETY INFORMATION

- **Always turn off power at the circuit breaker** before beginning any installation, maintenance, or bulb replacement. Failure to do so may result in electric shock or serious injury.
- Consult a qualified electrician if you are unsure about the wiring process or have any electrical concerns.
- This fixture is designed for **indoor use only**. Do not install in wet or damp locations, as it is not water resistant.
- Use only E26 base bulbs. Do not exceed the maximum wattage of **60W per light**.
- Ensure all connections are secure and properly insulated.
- Keep packaging materials away from children.

PACKAGE CONTENTS

Verify that all components are present and undamaged before proceeding with installation.

- 2 x Wall Sconce Fixtures (Matte Black)
- 2 x Milky White Glass Shades
- 1 x Mounting Hardware Kit (screws, wire nuts, mounting plate)
- 1 x User Manual (this document)

What's included in the package?

Package Included:

2 * Clear Glass shade

2 * Sconces Kit

1* User Manual

Tisp:

Wall sconces suitable for bedroom,bathroom,livingroom,laundry

Image: Contents included in the package.

SPECIFICATIONS

Brand	CANMEIJIA
Model Number	CMJ-BD-001
Color	Matte Black
Material	Iron (Fixture), Glass (Shade)
Style	Modern
Light Fixture Form	Sconce
Indoor/Outdoor Usage	Indoor Use Only
Power Source	AC/DC (Hardwired)
Bulb Base	E26 Standard Medium Base
Max Wattage per Bulb	60W
Number of Light Sources	2
Dimmable	Yes (with compatible dimmer bulb and switch, not included)
Mounting Type	Wall Mount, Surface Mount
Water Resistance Level	Not Water Resistant
Approximate Dimensions (per sconce)	Height: 11.6 cm (4.57 in), Depth from wall: 6.2 cm (2.44 in), Shade Diameter: 12 cm (4.72 in), Total Width: 23 cm (9.05 in)

SCONCES SIZE



E26 BASE

RECOMMENDED BULBS
(Bulbs are not included)



Image: Sconce dimensions.



Image: Detailed specifications of the wall sconce.

SETUP AND INSTALLATION

This wall sconce is designed for easy installation. It can be mounted with the light shades pointing upwards or downwards to suit your aesthetic preference. Always ensure the power is off at the circuit breaker before starting.

1. **Prepare the Installation Area:** Turn off the main power supply at the circuit breaker. Ensure the wall surface is clean and dry.
2. **Attach Mounting Plate:** Secure the mounting plate to the junction box in your wall using the provided screws.
3. **Wire Connections:** Connect the fixture's wires to your household electrical wires. Typically, connect the black wire from the fixture to the black (live) wire from the wall, the white wire from the fixture to the white (neutral) wire from the wall, and the ground wire from the fixture to the ground wire from the wall. Use wire nuts to secure connections.
4. **Mount the Fixture:** Carefully align the fixture base with the mounting plate and secure it with the provided screws.
5. **Install Glass Shades:** Gently attach the milky white glass shades to the fixture. Ensure they are securely fastened.
6. **Insert Bulbs:** Screw in E26 base bulbs (not included) into the sockets. Do not exceed 60W per bulb.
7. **Restore Power:** Turn the power back on at the circuit breaker.



Image: Key components of the sconce, including the E26 base and glass shade.

E26 Standard Base

Compatible with E26 bulbs, such as Incandescent/CFL/LED/Halogen E26 Bulbs



OPERATING INSTRUCTIONS

Once installed, operating your CANMEIJIA Wall Sconce is straightforward.

- **Power On/Off:** Use your standard wall switch to turn the light fixture on or off.
- **Bulb Compatibility:** This fixture uses E26 standard medium base bulbs. You can choose incandescent, CFL, LED, or halogen bulbs, provided they do not exceed 60W per socket.
- **Dimmable Functionality:** If you wish to use the dimmable feature, ensure you install dimmable E26 bulbs and connect the fixture to a compatible dimmer switch (both sold separately).
- **Light Direction:** The fixture can be installed with the glass shades pointing either upwards or downwards, allowing you to customize the light distribution in your room.



Image: Sconce installed with light directed downwards (left) and upwards (right).

MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your wall sconce.

- **Cleaning:** Ensure the power is off before cleaning. Wipe the fixture with a soft, dry cloth. For the glass shades, a slightly damp cloth can be used, followed by a dry cloth to prevent water spots. Avoid using abrasive cleaners, solvents, or polishes, as these can damage the finish.
- **Bulb Replacement:** Always turn off the power before replacing bulbs. Allow old bulbs to cool completely before handling.
- **Durability:** The matte black metal finish is designed to be resistant to oxidation, fading, and rusting, ensuring long-lasting durability.

Sturdy Cylindrical Glass Shade

Clear cylindrical glass shade can better reflect light to creates a warm and comfortable atmosphere.

E26 BASE

Compatible with Incandescent/LED/Halogen/CFL Bulb
(Bulbs Not Include)



Halogen Bulb



LED BulbUL



CFL Bulb



Unique Design



Image: The durable metal finish of the wall sconce.

TROUBLESHOOTING

If you encounter issues with your wall sconce, refer to the following common problems and solutions:

- **Light Does Not Turn On:**

- Check if the power is on at the circuit breaker.
- Ensure the wall switch is in the 'ON' position.
- Verify that the bulb is screwed in correctly and is not burnt out. Replace if necessary.
- Check all wire connections for proper contact and security.

- **Light Flickers:**

- Ensure the bulb is fully screwed into the socket.
- If using a dimmable bulb with a dimmer switch, ensure both are compatible and correctly installed.
- Check for loose wire connections.

- **Bulb Burns Out Quickly:**

- Ensure the bulb wattage does not exceed the maximum 60W rating for the fixture.
- Check for voltage fluctuations in your electrical system.

WARRANTY AND SUPPORT

While specific warranty details are not provided in this manual, CANMEIJIA products are typically covered by a manufacturer's warranty against defects in materials and workmanship. Please retain your proof of purchase.

For any questions, technical assistance, or to report missing/damaged parts, please contact the seller or CANMEIJIA customer support through the platform where you purchased the product. Provide your model number (CMJ-BD-001) and purchase details for faster service.

You can visit the [CANMEIJIA Store](#) for more information and product offerings.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question