

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [MageGee](#) /

› [MageGee MK98 Wireless Mechanical Keyboard Instruction Manual](#)

MageGee MK98

MageGee MK98 Wireless Mechanical Keyboard Instruction Manual

Model: MK98

1. SETUP

1.1 Unboxing and Initial Inspection

Carefully remove the keyboard and all accessories from the packaging. Ensure all components are present:

- MageGee MK98 Wireless Mechanical Keyboard
- USB-C to USB-A Cable
- 2.4GHz USB Receiver
- Keycap/Switch Puller (if included)
- Spare Switches (if included)

1.2 Charging the Keyboard

Before first use, it is recommended to fully charge the keyboard. Connect the provided USB-C cable to the keyboard's USB-C port and the other end to a powered USB-A port on your computer or a wall adapter. The keyboard features a built-in 4000mAh battery.

1.3 Adjusting Keyboard Height

The keyboard is designed with adjustable rear feet to provide ergonomic comfort. Flip out the feet on the underside of the keyboard to select your preferred typing angle.

2. OPERATING INSTRUCTIONS

2.1 Connection Modes

The MageGee MK98 keyboard supports three connection modes: 2.4GHz Wireless, Bluetooth, and USB-C Wired.

- **2.4GHz Wireless Mode:** Locate the 2.4GHz USB receiver (often stored in a compartment on the keyboard's underside). Plug the receiver into an available USB-A port on your computer. Short press **Fn + 4** on the keyboard to switch to 2.4G mode.
- **Bluetooth Mode:** The keyboard supports connecting up to three Bluetooth devices. Short press **Fn + 1**, **Fn + 2**, or **Fn + 3** to select a Bluetooth channel. The keyboard will enter pairing mode. On your device (computer, tablet,

smartphone), search for Bluetooth devices and select