BAOFENG DR-1801

BAOFENG DR-1801 DMR Digital/Analog Ham Radio Instruction Manual

Your comprehensive guide to setup, operation, and maintenance.

Introduction

The BAOFENG DR-1801 is an advanced dual-band DMR (Digital Mobile Radio) designed for amateur radio enthusiasts. It supports both digital and analog modes, offering versatility in communication. Key features include AES256 encryption for secure transmissions, dual standby, dual display, and a robust 2200mAh battery for extended operation. This manual provides essential information for setting up, operating, and maintaining your DR-1801 radio.

What's in the Box

Upon unboxing your BAOFENG DR-1801, please verify that all the following components are included:

- Portable Radio (BAOFENG DR-1801)
- 2200mAh Battery
- High Gain Antenna
- Desktop Charger
- Belt Clip
- Hand Strap
- User's Manual
- Programming Cable
- 771 Antenna
- 12V Car Charger



Image: The BAOFENG DR-1801 radio shown with all standard accessories, including the radio unit, battery, antennas, desktop charger, car charger, programming cable, belt clip, and hand strap.

Setup

1. Battery Installation

1. Align the 2200mAh battery with the battery compartment on the back of the radio.
2. Slide the battery upwards until it clicks securely into place. Ensure it is firmly attached to prevent accidental disconnection.



Image: The BAOFENG DR-1801 radio with its 2200mAh battery detached, illustrating the battery's connection points and the radio's battery compartment.

2. Antenna Attachment

1. Screw the provided antenna clockwise onto the antenna connector located on the top of the radio until it is finger-tight. Do not overtighten.

3. Charging the Battery

Before first use, fully charge the battery. The 2200mAh battery typically charges in approximately 4 hours.

- **Using the Desktop Charger:** Place the radio (with battery installed) into the desktop charging cradle. Ensure the charging indicator light illuminates.
- **Using the 12V Car Charger:** Connect the car charger to your vehicle's 12V power outlet and then to the radio's charging port.

4. Programming the Radio

The BAOFENG DR-1801 can be programmed via PC using the included programming cable. This allows for customization of channels, frequencies, and other advanced settings. Refer to the official BAOFENG website for the latest programming software and detailed instructions.

Operating Instructions

1. Power On/Off

To power on the radio, rotate the volume knob clockwise until you hear a click. To power off, rotate it counter-clockwise until it clicks.

2. Mode Selection (Digital/Analog)

The DR-1801 supports both digital (DMR) and analog communication. You can switch between these modes as needed. The LCD screen will indicate the current operating mode.



Image: The BAOFENG DR-1801's LCD screen displaying examples of both analog and digital frequency readouts, indicating the current operational mode.

3. Channel Management

The radio features 1024 channels. You can navigate through channels using the up/down arrow keys or by entering frequencies directly in VFO (Variable Frequency Oscillator) mode.

4. SMS Function

The DR-1801 includes an SMS function for sending and receiving text messages between compatible DMR radios. This can be useful for discreet communication or when voice communication is not feasible.



Image: Two BAOFENG DR-1801 radios demonstrating the SMS function, with text messages visible on their screens.

5. Emergency Alarm

The radio is equipped with an emergency alarm function. Consult the full user manual for specific instructions on how to activate and configure this feature for critical situations.

6. AES256 Encryption

For enhanced communication security, the DR-1801 supports AES256 encryption. This feature helps protect your

transmissions from unauthorized interception, ensuring privacy in sensitive communications.



Image: The BAOFENG DR-1801 radio displayed alongside a graphic highlighting its AES256 encryption capability, symbolizing secure communication.

7. Dual Band, Dual Standby, Dual Display

The radio operates on dual frequency bands (VHF/UHF), allows monitoring of two different frequencies simultaneously (dual standby), and displays both frequencies on its screen (dual display).

8. DMO True 2 Time Slot

Direct Mode Operation (DMO) with True 2 Time Slot allows two independent conversations to occur on a single frequency channel simultaneously. This doubles communication efficiency and optimizes frequency resource usage without requiring a repeater.

9. Other Functions

The DR-1801 integrates various other functions including VOX (Voice Operated Transmit), High/Low Power selection, TOT (Time-Out Timer), DTMF (Dual-Tone Multi-Frequency), CTCSS (Continuous Tone-Coded Squelch

System), and DCS (Digitally Coded Squelch).



Image: The BAOFENG DR-1801 radio in an outdoor setting, accompanied by icons illustrating its diverse features such as VOX, SMS, High/Low Power, TOT, Wired Copy, Call Experience, Emergency Alarm, and Digital Encryption.

10. Communication Range

The effective communication range varies based on terrain and environmental conditions:

- **Open Area:** Up to 6.2 Miles
- **Community Area:** Up to 4 Miles
- **Urban Area:** Up to 1.8 Miles



Image: The BAOFENG DR-1801 radio displayed with graphical representations of its communication range in open, community, and urban environments.

Maintenance

Battery Care

- To maximize battery life, avoid fully discharging the battery frequently.
- Store the battery in a cool, dry place when not in use for extended periods.
- If the radio will not be used for a long time, remove the battery.

General Cleaning

- Clean the radio's exterior with a soft, damp cloth. Do not use harsh chemicals or abrasive cleaners.
- Ensure the radio is not exposed to excessive dust or moisture. Note that the radio is not water resistant.

Troubleshooting

Difficulty with Programming

Some users may find programming the DR-1801 challenging. Ensure you are using the correct and latest programming software from the official BAOFENG website. Verify that the programming cable drivers are correctly installed on your computer. Online communities and video tutorials can also provide helpful guidance.

Radio Not Powering On

- Check if the battery is properly installed and fully charged.
- Ensure the volume knob is rotated clockwise past the 'off' position.

No Audio or Poor Reception

- Verify the antenna is securely attached.
- Check the volume level.
- Ensure you are on the correct frequency/channel and in the appropriate mode (digital/analog).
- Adjust squelch settings if necessary.

Specifications

Feature	Detail
Brand	BAOFENG
Model Number	DR-1801/TD-H6
Item Weight	1.59 pounds
Product Dimensions	1.4 x 2.4 x 5.2 inches
Battery Capacity	2200mAh Lithium Ion (included)
Number of Channels	1024
Frequency Range	144-148MHz, 420-450MHz
Talking Range Maximum	6.2 Miles (Open Area)
Voltage	7.4 Volts (DC)
Special Features	AES256, Digital and analog compatible, Long Range, Tier I & Tier II compliant DMR radio
Water Resistance Level	Not Water Resistant



Image: The BAOFENG DR-1801 radio with its physical dimensions (length, width, depth) and total weight clearly labeled.

Warranty and Support

The BAOFENG DR-1801 comes with a 1-year warranty provided exclusively through "Shiqun Electronics Co., Ltd." For warranty claims, technical support, or further assistance, please contact Shiqun Electronics Co., Ltd. directly. Refer to your purchase documentation for specific contact details.

© 2023 BAOFENG. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question