

[Manuals.plus](#) /

› [Flamaker](#) /

› Flamaker Electric Standing Desk User Manual

Flamaker 0060B

Flamaker Electric Standing Desk User Manual

Model: 0060B

INTRODUCTION

This manual provides essential information for the assembly, operation, and maintenance of your Flamaker Electric Standing Desk. Please read it thoroughly before use to ensure proper functionality and safety. This desk is designed to offer a versatile workspace, allowing seamless transitions between sitting and standing positions to promote a healthier work environment.



An overview of the Flamaker Electric Standing Desk, showcasing its spacious white desktop and sturdy T-shaped metal legs, suitable for a modern home office setup.

SAFETY INSTRUCTIONS

To ensure safe operation and prevent damage, please adhere to the following safety guidelines:

- Ensure all connections, especially electrical ones, are secure before operating the desk.
- Keep hands, clothing, and any objects clear of moving parts (legs, frame) during height adjustment to prevent pinching or damage.
- Do not exceed the maximum weight capacity of **132 lbs (60 kg)**. Overloading can damage the motor and frame.
- Avoid placing liquids directly on the control panel or near motor components to prevent electrical hazards.
- Unplug the desk from the power source before cleaning, maintenance, or if it will not be used for an extended period.
- This desk is designed for indoor use only. Do not expose it to moisture or extreme temperatures.
- Only use the provided power adapter and components. Unauthorized modifications may void the warranty and pose safety risks.

INCLUDED COMPONENTS

Please verify that all parts are present and undamaged before beginning assembly. If any parts are missing or damaged, contact customer support immediately.

- Desktop sections (3 pieces)
- Desk legs (2)
- Crossbar/Frame
- Motor and Control Box
- Control Panel
- Power Adapter
- Headphone Hook
- Cable Management Accessories (e.g., cable snatches, ring hidere)
- Assembly Hardware (various screws, Allen wrench)

Durable Quite Motor

Each motor can be used more than 10000 times



This image illustrates the key internal components of the Flamaker Electric Standing Desk, including the durable motor, the central crossbar, and the robust T-shaped leg structures, highlighting the quiet operation and efficient lifting mechanism.

SETUP AND ASSEMBLY

Assembly is required for this product. It is recommended that **two people** assemble the desk for ease and safety. The desktop consists of three separate pieces that will be joined during assembly. Follow the steps below carefully:

1. **Unpack and Organize:** Unpack all components from the packaging and lay them out on a clean, flat, and soft surface to prevent scratches. Identify each part using the components list.
2. **Assemble the Frame:** Attach the desk legs to the central crossbar/frame using the provided hardware. Ensure all connections are firm but do not overtighten initially.
3. **Install Motor and Control Box:** Secure the motor and control box to the designated positions on the frame. Refer to the assembly diagrams for precise placement.

4. **Assemble Desktop:** Join the three desktop pieces together and then carefully align and attach the assembled desktop to the frame. Ensure all screws are tightened securely to create a stable surface.
5. **Mount Control Panel:** Install the control panel into its designated slot on the desktop or frame, ensuring it is easily accessible.
6. **Connect Wiring:** Connect all necessary cables: the motor cable to the control box, the control panel cable to the control box, and finally, the power adapter to the control box. Ensure all connections are snug.
7. **Attach Accessories:** Install the headphone hook and utilize the cable management accessories (snatches, ring hiders) to organize your cables neatly.
8. **Final Check:** Double-check all screws and connections to ensure they are tight and secure before plugging in the desk.



The fully assembled Flamaker Electric Standing Desk, ready for use in a home office environment.

OPERATING INSTRUCTIONS

Your Flamaker Electric Standing Desk is equipped with an intuitive control panel for easy height adjustment and memory functions.

Height Adjustment

The desk features an electric lifting mechanism for smooth and quiet height adjustments.

- **To Raise:** Press and hold the "Up" button (▲) on the control panel. The desk will move upwards at approximately 1 inch per second.

- **To Lower:** Press and hold the "Down" button (▼) on the control panel. The desk will move downwards at approximately 1 inch per second.
- Release the button at your desired height. The adjustable height range is from **28.7 inches (73 cm)** to **45.3 inches (115 cm)**.

Memory Presets

The control panel allows you to save and recall up to four preferred height settings for quick transitions.

1. **Set Desired Height:** Adjust the desk to your preferred height using the Up/Down buttons.
2. **Activate Memory Function:** Press the "M" button (Memory button). The display may flash or indicate it's ready to save.
3. **Save Preset:** Within a few seconds, press one of the numbered preset buttons (1, 2, 3, or 4) to save the current height to that specific memory slot.
4. **Recall Preset:** To move the desk to a saved height, simply press the corresponding numbered preset button. The desk will automatically move to the saved position.



This diagram visually represents the adjustable height range of the Flamaker Electric Standing Desk, demonstrating its versatility from a minimum height of 28.7 inches to a maximum height of 45.3 inches, accommodating both sitting and standing preferences.

MAINTENANCE

Proper maintenance will extend the life and performance of your Flamaker Electric Standing Desk.

- **Cleaning:** Wipe the desk surfaces (desktop and legs) with a soft, damp cloth. For stubborn marks, a mild soap solution can be used, followed by wiping with a clean, dry cloth. Avoid abrasive cleaners, harsh chemicals, or solvents as they may damage the finish.
- **Regular Checks:** Periodically inspect all screws and connections, especially those on the frame and legs, to ensure they remain tight. Retighten if necessary to maintain stability.
- **Motor Care:** The electric motor is designed for durability and quiet operation. To ensure its longevity, avoid overloading the desk beyond its specified 132 lbs (60 kg) weight capacity. Do not attempt to disassemble the motor or control box.
- **Cable Management:** Keep cables organized and free from entanglement to prevent damage to the wiring and ensure smooth operation of the desk's lifting mechanism.

TROUBLESHOOTING

If you encounter issues with your Flamaker Electric Standing Desk, please refer to the following common problems and their solutions:

Problem	Possible Cause	Solution
Desk does not move or respond to controls.	Power cable disconnected or loose connection.	Ensure the power cable is securely plugged into a working wall outlet and the control box. Check all cable connections between the motor, control box, and control panel.
Desk stops mid-movement or moves erratically.	Overload protection activated (too much weight). Obstruction in the lifting mechanism.	Reduce the weight on the desk to below 132 lbs. Check for any objects obstructing the legs' movement. Unplug the desk for 10-15 minutes to reset the system, then plug it back in.
Unusual noise (grinding, squeaking) during operation.	Loose components or minor friction.	Check all assembly screws for tightness, especially on the frame and legs. Ensure the desk is on a level surface. If noise persists, contact customer support.
Height presets are not working or saving correctly.	Incorrect saving procedure or temporary glitch.	Re-save your desired height settings carefully following the "Memory Presets" instructions in the Operating section. If the issue continues, try unplugging and replugging the desk.

If the problem persists after attempting these solutions, please contact Flamaker customer support for further assistance.

SPECIFICATIONS

Detailed technical specifications for your Flamaker Electric Standing Desk:

Feature	Detail
Brand	Flamaker
Model Number	0060B
Model Name	Standing Desk
Desktop Dimensions (W x D)	55.1" x 24" (140 cm x 61 cm)
Adjustable Height Range	28.7" - 45.3" (73 cm - 115 cm)
Weight Capacity	132 lbs (60 kg)
Lifting Mechanism	Electric
Lifting Speed	Approx. 1 inch/second
Noise Level	Low noise (<50 DB)
Material	Wood (desktop), Metal (frame)
Color	White
Assembly Required	Yes (Recommended 2 people)
Item Weight	45.2 Pounds



This image provides a clear visual of the Flamaker Electric Standing Desk's dimensions, indicating a desktop size of 55.1 inches in width and 24 inches in depth, along with its impressive weight capacity of 132 pounds, suitable for various office equipment.

WARRANTY AND SUPPORT

Flamaker products are designed for quality and durability. For specific warranty information regarding your Electric Standing Desk, please refer to the documentation included with your purchase. This documentation typically outlines the warranty period, coverage details, and terms and conditions.

For technical support, assistance with missing parts, troubleshooting guidance beyond what is provided in this manual, or any other inquiries, please contact Flamaker customer service. You can typically reach support through the retailer where the product was purchased or via the contact information provided on the official Flamaker website.

Online Resources: For additional product information and support, you may visit the official Flamaker Store on Amazon:

[Flamaker Store](#)

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0CMTW1QYT>

More documents and user manuals: <https://manuals.plus/>