Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

Vidattx PTK035

Vidattx POSEIDON PTK035 Rotary Tattoo Machine Pen Kit User Manual

Model: PTK035 | Brand: Vidattx

1. Introduction and Kit Contents

This manual provides essential instructions for the safe and effective use of your Vidattx POSEIDON PTK035 Rotary Tattoo Machine Pen Kit. Please read all instructions carefully before operation.

Kit Components:

- 1 x POSEIDON Tattoo Pen
- 20 x Tattoo Cartridges Needles (1205RL*5, 1207RL*5, 1209RS*5, 1207CM*5)
- 1 x Self-Cohesive Tattoo Grip Cover
- 1 x Wireless Tattoo Power Supply
- 1 x TYPE-C Charging Cable
- 40 x Ink Caps
- 2 x Practice Skin
- 2 x Transfer Paper
- 10 x 5ml Tattoo Ink
- 1 x 30ml Black Tattoo Ink
- 1 x 30ml Blue Soap
- 1 x Tattoo Gloves
- 1 x Painting Brush
- 1 x Tattoo Sticker
- 1 x Handbag
- 4 x Tattoo Table Mat
- 1 x Instruction Manual



Image 1.1: Overview of the complete POSEIDON Tattoo Kit contents.

2. Setup

Follow these steps to set up your POSEIDON Tattoo Machine Pen for operation.

1. **Charge the Power Supply:** Ensure the wireless tattoo power supply is fully charged using the provided TYPE-C charging cable. The battery has a capacity of 1500mAH and typically charges in 2 hours, providing 3-6 hours of working time depending on voltage and motor load.
2. **Attach the Power Supply:** Connect the wireless power supply to the top of the tattoo pen. It features an RCA connection for secure attachment.
3. **Insert a Cartridge Needle:** Select the desired tattoo cartridge needle. The kit includes various sizes (1205RL, 1207RL, 1209RS, 1207CM). Insert the needle into the pen by twisting it into place.
4. **Adjust Needle Length:** Rotate the grip of the tattoo pen to adjust the needle's protrusion length according to your preference.
5. **Prepare Ink:** Pour a small amount of tattoo ink into an ink cap.



Image 2.1: Attaching the wireless power supply and adjusting needle length on the POSEIDON Tattoo Pen.



Image 2.2: Detailed view of the wireless power supply interface, including power and voltage controls.

Your browser does not support the video tag.

Video 2.1: Demonstrates the unboxing, assembly, and basic operation of the POSEIDON Tattoo Pen Kit.

3. Operating Instructions

Once assembled, follow these steps to operate your tattoo machine pen.

1. **Power On:** Press and hold the power button on the wireless power supply to turn on the device.
2. **Adjust Voltage:** Use the '+' and '-' buttons to adjust the working voltage. The recommended working voltage is 6-11V. The display will show the current voltage.
3. **Dip Needle in Ink:** Gently dip the tip of the cartridge needle into the ink cap to load ink.
4. **Begin Tattooing (Practice Skin):** For beginners, it is highly recommended to practice on the provided practice skin to familiarize yourself with the machine's feel and control before working on human skin.
5. **Power Off:** After use, press and hold the power button to shut down the device.

Your browser does not support the video tag.

Video 3.1: Demonstrates the process of setting up the tattoo pen, adjusting voltage, and practicing on artificial skin.

Your browser does not support the video tag.

Video 3.2: Shows the tattoo pen in operation, including needle insertion and ink application.

4. Maintenance

Proper maintenance ensures the longevity and hygiene of your tattoo kit.

- **Disinfection:** The non-slip handle of the tattoo pen can be disassembled for thorough disinfection after each use. Use appropriate sterilizing solutions.
- **Needle Disposal:** Always dispose of used cartridge needles in a sharps container. Needles are for single-use only and are sterilized by EO gas in individual packs.
- **Cleaning:** Clean the tattoo pen and power supply with a soft, damp cloth. Avoid submerging electronic components in liquid.
- **Storage:** Store the kit in its provided handbag in a cool, dry place, away from direct sunlight and extreme temperatures.

5. Troubleshooting

If you encounter issues with your POSEIDON Tattoo Kit, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Tattoo pen does not turn on.	Low battery or power supply not connected properly.	Ensure the wireless power supply is fully charged. Verify the power supply is securely attached to the tattoo pen. Press and hold the power button to activate.
Inconsistent needle movement or weak power.	Low battery, incorrect voltage setting, or needle issue.	Recharge the power supply. Adjust the voltage to the recommended range (6-11V). Ensure the cartridge needle is correctly inserted and not damaged.
Ink not flowing properly.	Needle not properly dipped, or ink consistency issue.	Ensure the needle tip is adequately submerged in the ink cap. Check ink for proper consistency; if too thick, it may need thinning (use only professional tattoo ink thinner).

6. Specifications

- **Product Dimensions:** 3 x 2 x 1 inches
- **Weight:** 2.67 Pounds
- **Battery:** 1 x 12V Lithium battery (included), 1500mAH capacity
- **Working Voltage:** 6-11V (5-level adjustment)
- **Charging Time:** Approximately 2 hours
- **Battery Life:** 3-6 hours (depending on voltage and motor load)
- **Manufacturer:** Vidattx
- **Model Number:** PTK035
- **UPC:** 787502962035

7. Safety Information

Important Safety Precautions:

- Keep the tattoo kit away from naked flames or direct heat sources.
- Store all components out of reach of children.
- This product is intended for professional use or supervised training on practice skin.
- Always wear protective gloves during setup, operation, and cleaning.
- Ensure proper sterilization of all reusable equipment.
- Dispose of all sharps and contaminated materials according to local regulations.
- Do not attempt to modify the device.

8. Warranty and Support

Vidattx is committed to customer satisfaction. We provide a replacement or refund for all products if you are not 100% satisfied. No reason needed, smooth and simple. For any inquiries or support, please contact our customer service.

© 2025 Vidattx. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0CPV324WB

More documents and user manuals: **https://manuals.plus/**