

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Redragon](#) /

› [Redragon M916 PRO 3-Mode Wireless Gaming Mouse User Manual](#)

Redragon M916 PRO

Redragon M916 PRO 3-Mode Wireless Gaming Mouse User Manual

Model: M916 PRO

Brand: Redragon

INTRODUCTION

Thank you for choosing the Redragon M916 PRO 3-Mode Wireless Gaming Mouse. This manual provides detailed instructions for setting up, operating, and maintaining your new gaming mouse. Please read this manual thoroughly to ensure optimal performance and longevity of your device.

The Redragon M916 PRO is designed for precision and comfort, featuring a lightweight build, multiple connectivity options, and customizable settings to enhance your gaming experience.



Image: Top-down view of the Redragon M916 PRO Wireless Gaming Mouse in white, showcasing its ergonomic design and scroll wheel.

PACKAGE CONTENTS

- Redragon M916 PRO Wireless Gaming Mouse
- 2.4GHz USB Receiver
- USB-C to USB-A Charging/Data Cable
- User Manual

SETUP

Charging the Mouse

Before first use, it is recommended to fully charge the mouse. Connect the provided USB-C cable to the mouse's charging port and the USB-A end to a powered USB port on your computer or a USB wall adapter. The LED indicator will show charging status.

**150+ HRS,
400MAH BATTERY CAPACITY**

Apex Balance of Lasting & Lightweight

**400
MAH**

**150
HRS**

Image: The Redragon M916 PRO mouse highlighting its 400mAh battery capacity, offering over 150 hours of use.

Connecting the Mouse

The M916 PRO supports three connection modes: 2.4GHz Wireless, Bluetooth, and Wired (USB-C).



Image: The Redragon M916 PRO mouse illustrating its Tri-Mode connection capabilities: 2.4GHz, Bluetooth, and USB-C wired.

1. 2.4GHz Wireless Mode:

- Locate the 2.4GHz USB receiver. It is typically stored in a compartment on the underside of the mouse.
- Plug the USB receiver into an available USB port on your computer.
- Turn on the mouse using the power switch on the bottom. The mouse should automatically connect.

2. Bluetooth Mode:

- Turn on the mouse and switch it to Bluetooth mode (refer to the switch on the bottom of the mouse).
- On your computer, open Bluetooth settings and search for new devices.
- Select "Redragon M916 PRO" from the list of available devices to pair.

3. Wired Mode (USB-C):

- Connect the provided USB-C cable to the mouse and the USB-A end to your computer.

- The mouse will function in wired mode and charge simultaneously.

OPERATING INSTRUCTIONS

DPI Adjustment

The mouse features 5 redefinable DPI levels, with default settings at 1000/2000/4000/8000/26000. You can cycle through these levels using the dedicated DPI button, usually located on the top or bottom of the mouse. Each DPI level may correspond to a different LED color indicator.



Image: The Redragon M916 PRO mouse illustrating its DPI settings (1000 Red, 2000 Blue, 4000 Green, 8000 Purple, 26000 Yellow) and the DPI indicator light.

Programmable Buttons

The M916 PRO is equipped with 5 programmable buttons. These buttons can be customized using the Redragon dedicated software to assign various functions, macros, or keybinds according to your preferences.



Image: The Redragon M916 PRO mouse on a reflective surface, accompanied by an icon indicating 'PRO Software' for customization.

Software Customization

For advanced customization of DPI settings, button assignments, and other features, download the Redragon dedicated software from the official Redragon website. The software allows for fine-tuning of the mouse to suit specific gaming or work requirements.



Image: A close-up of the PixArt PAW3395 Premium Flagship Sensor chip, highlighting its 26K DPI MAX, 650 IPS, and 50G ACC capabilities.

MAINTENANCE

To ensure the longevity and optimal performance of your Redragon M916 PRO mouse, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry cloth to clean the mouse surface. For stubborn dirt, a slightly damp cloth can be used, but ensure no moisture enters the internal components. Avoid harsh chemicals or abrasive materials.
- **Storage:** When not in use for extended periods, store the mouse in a cool, dry place away from direct sunlight and extreme temperatures.
- **Battery Care:** Avoid completely draining the battery frequently. Charge the mouse when the battery indicator is low.
- **Cable Care:** Handle the USB-C cable gently. Avoid sharp bends or excessive pulling to prevent damage.

TROUBLESHOOTING

Issue	Possible Solution
Mouse not responding in wireless mode	<ul style="list-style-type: none">Ensure the mouse is powered on.Check battery level and charge if necessary.Verify the 2.4GHz USB receiver is securely plugged into a working USB port.Ensure the mouse is switched to the correct wireless mode (2.4GHz or Bluetooth).Try plugging the receiver into a different USB port.
Bluetooth connection issues	<ul style="list-style-type: none">Ensure the mouse is in Bluetooth pairing mode.Check your computer's Bluetooth settings and ensure Bluetooth is enabled.Remove the mouse from your computer's paired devices list and attempt to re-pair.

Issue	Possible Solution
DPI settings not changing	Ensure the DPI button is functioning correctly. If using custom DPI settings, verify they are correctly configured in the Redragon software.
Buttons not responding or performing incorrect actions	Check button assignments in the Redragon software. Ensure the software is up to date. Restart your computer and the mouse.

SPECIFICATIONS

Feature	Detail
Model	M916 PRO
Connectivity	BT, 2.4Ghz Wireless, USB-C Wired
DPI Levels	50-26000 (Default: 1000/2000/4000/8000/26000)
Sensor	PixArt PAW3395
Buttons	5 Programmable Buttons
Switch Type	Huano Switches (50 Million Clicks)
Battery Capacity	400mAh Lithium Polymer
Battery Life	150+ Hours (approximate)
Weight	49g (approx. 1.73 ounces)
Dimensions	7.09 x 4.72 x 1.97 inches
Special Features	Advanced Chip, Ergonomic Design

WARRANTY AND SUPPORT

Warranty Information

Redragon products typically come with a limited warranty against defects in materials and workmanship. Please refer to the warranty card included with your product or visit the official Redragon website for specific warranty terms and conditions applicable to your region.

Customer Support

For technical assistance, troubleshooting, or product inquiries, please visit the official Redragon support page or contact their customer service. You can find contact information and FAQs on the Redragon website: www.redragonusa.com

