

Luminzone 7J10F

Luminzone 7J10F Brushed Nickel 2-Light Flush Mount Ceiling Light User Manual

Model: 7J10F | Brand: Luminzone

1. INTRODUCTION

This manual provides essential information for the safe and efficient installation, operation, and maintenance of your Luminzone 7J10F Brushed Nickel 2-Light Flush Mount Ceiling Light. This fixture features a unique clear glass shade and a classic brushed nickel metal base, designed to complement various indoor settings with a modern farmhouse aesthetic. Please read all instructions carefully before proceeding with installation or use.

2. IMPORTANT SAFETY INFORMATION

- **WARNING:** To avoid electric shock, always disconnect power at the main circuit breaker or fuse box before installation or servicing.
- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with proper electrical wiring connections.
- This fixture is designed for indoor use only. Do not install in wet locations.
- Ensure the mounting surface is structurally sound and can support the weight of the fixture.
- Use only the specified bulb type and wattage to prevent overheating and potential fire hazards.
- The fixture is ETL listed for safety, ensuring it meets recognized safety standards.

3. PACKAGE CONTENTS

Carefully unpack your new light fixture and lay out all parts on a clear surface. Ensure all components listed below are present before discarding packaging materials.

- Flush Mount Ceiling Light Fixture (Brushed Nickel Base with 2 E26 Sockets)
- Clear Glass Shade

- Mounting Hardware (screws, wire nuts, mounting bracket)
- Instruction Manual

Note: *Bulbs are not included and must be purchased separately.*



Image: Detailed view of the light fixture's components, including the 2*E26 bracket, clear glass lamp shade, and brushed nickel metal frame.

4. SPECIFICATIONS

Feature	Specification
Brand	Luminzone
Model Name	7J10F BN
Color	Brushed Nickel
Material	Glass, Iron
Product Dimensions (L x W x H)	13.39"L x 13.39"W x 6.5"H

Number of Light Sources	2
Bulb Base	E26 Standard Base
Maximum Wattage per Bulb	60 Watts
Voltage	120 Volts (AC)
Installation Type	Flush Mount
Indoor/Outdoor Usage	Indoor Use Only
Special Feature	Dimmable with compatible bulb & switch



Image: Diagram illustrating the dimensions of the light fixture and compatible bulb types (E26 base, 60W MAX, 110-120V, ETL Certified).

5. INSTALLATION INSTRUCTIONS

This fixture is designed for hard-wired installation. It is not a plug-in design. Please follow these steps carefully. If you are unsure about any step, consult a qualified electrician.

1. **Turn Off Power:** Before starting, ensure the power to the circuit you are working on is completely OFF at the main electrical panel.
2. **Prepare Mounting Surface:** Attach the mounting bracket (included) to the junction box in your ceiling using the provided screws. Ensure it is securely fastened.
3. **Wire Connections:** Connect the fixture's wires to your household electrical wires. Typically, connect the black wire from the fixture to the black (live) wire from the ceiling, the white wire from the fixture to the white (neutral) wire from the ceiling, and the bare copper or green ground wire from the fixture to the ground wire from the ceiling. Secure connections with wire nuts (included).
4. **Secure Fixture:** Carefully tuck the wires into the junction box. Align the fixture base with the mounting bracket and secure it with the provided screws.
5. **Install Bulbs:** Screw two E26 base bulbs (not included, maximum 60W each) into the sockets. Compatible bulb types include incandescent, LED, CFL, and halogen.
6. **Attach Glass Shade:** Carefully place the clear glass shade onto the fixture and secure it according to the design (usually by screwing a finial or rotating the shade into place).
7. **Restore Power:** Once installation is complete and all components are secure, restore power at the main circuit breaker.

Your browser does not support the video tag.

Video: A product overview of the Luminzone Flush Mount Ceiling Light (Model 7J10F), demonstrating its appearance and light output when installed.

6. OPERATING INSTRUCTIONS

Once installed, your Luminzone 7J10F Flush Mount Ceiling Light operates like any standard hard-wired light fixture. It is controlled by a wall switch connected to its circuit.

- **Bulb Compatibility:** The fixture requires two E26 base bulbs, with a maximum wattage of 60W per bulb. It is compatible with incandescent, LED, CFL, and halogen bulbs.
- **Dimmable Feature:** This fixture is fully dimmable when used with dimmable E26 bulbs and a compatible dimmer switch (both sold separately).

7. MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your light fixture.

- **Cleaning:** To clean the fixture, ensure the power is off. Wipe the metal base with a soft, dry cloth. For the glass shade, use a mild glass cleaner and a soft cloth. Avoid abrasive cleaners or harsh chemicals, as they may damage the finish or glass.
- **Bulb Replacement:** Before replacing bulbs, turn off the power at the circuit breaker. Allow bulbs to cool completely. Unscrew the old bulbs and replace them with new E26 base bulbs (max 60W).

8. TROUBLESHOOTING

If you encounter issues with your light fixture, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
---------	----------------	----------

Light does not turn on	<ol style="list-style-type: none"> 1. Power is off 2. Loose wiring connection 3. Faulty bulb 	<ol style="list-style-type: none"> 1. Check circuit breaker and wall switch 2. Turn off power, check wiring connections 3. Replace bulb(s)
Light flickers	<ol style="list-style-type: none"> 1. Loose bulb 2. Incompatible dimmer switch/bulb 3. Loose wiring 	<ol style="list-style-type: none"> 1. Tighten bulb(s) 2. Ensure dimmable bulbs are used with a compatible dimmer 3. Turn off power, check wiring connections
Glass shade is difficult to attach/remove	Misalignment or debris	Ensure proper alignment and clear any obstructions. Do not force.

If the problem persists after attempting these solutions, please contact Luminzone customer service.

9. WARRANTY AND SUPPORT

Luminzone provides a **1-year warranty** for this ceiling light fixture, covering any quality or technical issues that may arise under normal use. We are confident in the quality of our product.

For warranty claims, technical assistance, or any other inquiries, please contact Luminzone customer service through the platform where you purchased the product. Please have your order information and product model number (7J10F) ready when contacting support.