

ABBIDOT ABBIDOT Dog Training Collar

ABBIDOT Dog Training Collar User Manual

Model: ABBIDOT Dog Training Collar

Brand: ABBIDOT

1. INTRODUCTION

This manual provides comprehensive instructions for the safe and effective use of your ABBIDOT Dog Training Collar. This device is designed to assist in training dogs weighing 10-120 lbs, offering 151 levels of static stimulation and 5 training modes including beep, vibration, and static shock. The receiver collar is IPX7 waterproof, making it suitable for various training environments. The remote control is not waterproof.

Please read this manual thoroughly before operating the device to ensure proper usage and to maximize training effectiveness while prioritizing your dog's safety and comfort.

2. PACKAGE CONTENTS

Upon opening your ABBIDOT Dog Training Collar package, please verify that all components are present and in good condition:

- 1 x Remote Control
- 1 x Receiver Collar with Adjustable Strap
- 1 x USB Charging Cable
- 2 x Sets of Contact Points (Short and Long)
- 1 x Test Light Tool
- 1 x User Manual (this document)



Image 2.1: The ABBIDOT Dog Training Collar package showing the remote control, receiver collar, and product box.

3. PRODUCT OVERVIEW

Familiarize yourself with the main components of your training system:

3.1 Remote Control

- LCD Display:** Shows battery level, training mode, intensity level, and dog selection.
- Intensity Adjustment Buttons (PUSH +/-):** Used to increase or decrease stimulation levels.
- Mode Button:** Cycles through training modes (Beep, Vibration, Static Stimulation).
- Stimulation Button:** Activates the selected training mode.
- Channel Button:** Selects which receiver collar to control (if multiple collars are paired).
- Charging Port:** USB-C port for recharging the remote.

3.2 Receiver Collar

- **Contact Points:** Deliver static stimulation. Choose appropriate length for your dog's fur.
- **Power Button:** Turns the receiver on/off and can be used for pairing.
- **Charging Port:** USB-C port for recharging the receiver.
- **Indicator Light:** Shows power status, charging status, and mode activation.
- **Adjustable Strap:** Securely holds the receiver on your dog's neck.



Image 3.1: Overview of the remote control and receiver collar, highlighting the 5 training modes: Light, Tone (Beep), Vibration, General Stimulation (1~16 Levels), and Boosted Stimulation (17~99 Levels).

4. SETUP

4.1 Charging the Devices

Before first use, fully charge both the remote control and the receiver collar. The devices come with built-in Lithium Ion batteries.

1. Connect the USB charging cable to the charging ports on both the remote and the receiver.
2. Plug the other end of the cable into a standard USB power adapter (not included).
3. The indicator lights will show charging status (e.g., solid red while charging, green when full).
4. Charging typically takes approximately 2 hours. The remote offers up to 10 days of standby time, and

the collar up to 16 days of work time on a full charge.



Image 4.1: Battery life information, showing 10 days for the remote and 16 days for the collar, with a 2-hour USB-C charge time.

4.2 Attaching Contact Points

Select the appropriate length of contact points (short or long) based on your dog's fur length. For dogs with thick fur, use longer contact points to ensure proper skin contact. Screw the chosen contact points firmly onto the receiver collar.

4.3 Fitting the Receiver Collar

Proper fit of the receiver collar is crucial for effective and safe operation.

1. Place the receiver collar around your dog's neck, ensuring the contact points are positioned underneath, making direct contact with the skin.
2. Adjust the strap so it is snug but not too tight. You should be able to fit two fingers comfortably between the strap and your dog's neck.
3. The collar is adjustable and cuttable, suitable for dogs from 10 to 130 lbs. Ensure the collar is not worn for more than 12 hours a day to prevent skin irritation.



LIGHTWEIGHT E-COLLAR FOR 10~130 lbs



Image 4.2: Collar fitting guide, illustrating contact point selection for different fur types and the adjustable nature of the collar for dogs weighing 10-130 lbs.

4.4 Pairing the Remote and Receiver

The devices are usually pre-paired from the factory. If re-pairing is needed:

1. Ensure both devices are fully charged and turned off.
2. Press and hold the power button on the receiver collar until the indicator light flashes rapidly.
3. Within 10 seconds, press the Stimulation button on the remote control.
4. If pairing is successful, the receiver's indicator light will flash slowly, and the remote will show the selected dog channel.

5. OPERATING INSTRUCTIONS

The ABBIDOT Dog Training Collar offers 5 distinct training modes to suit various training needs.

5.1 Power On/Off

- **To Turn On:** Press and hold the power button on both the remote and the receiver until the indicator lights illuminate.
- **To Turn Off:** Press and hold the power button on both devices until the indicator lights turn off.

5.2 Selecting Training Modes

Press the 'Mode' button on the remote control to cycle through the available training modes:

1. **Light Mode:** Activates a light on the receiver collar. Useful for locating your dog in low light conditions.
2. **Tone (Beep) Mode:** Emits an audible beep from the receiver. This mode has a fixed intensity level.
3. **Vibration Mode:** Delivers a non-harmful vibration to the receiver. This mode has a fixed intensity level.
4. **General Stimulation Mode:** Delivers static stimulation with adjustable levels from 1 to 16.
5. **Boosted Stimulation Mode:** Delivers static stimulation with adjustable levels from 17 to 99. This mode provides higher intensity for more stubborn dogs or specific training situations.

The remote offers a total of 151 levels of static stimulation, combining the general and boosted ranges, allowing for precise adjustment to your dog's temperament and training needs.

5.3 Adjusting Intensity Levels

For General and Boosted Stimulation modes, use the 'PUSH +' and 'PUSH -' buttons on the remote to adjust the intensity level. Always start with the lowest effective level and gradually increase if necessary, observing your dog's reaction.

5.4 Activating Training Modes

Once a mode and intensity level (if applicable) are selected, press the large 'Stimulation' button on the remote to activate the chosen correction.

5.5 Training Range

The ABBIDOT Dog Training Collar system has an effective range of up to 3300 feet (approximately 1000 meters) in open areas, allowing for flexible training in various outdoor environments.

5.6 Waterproof Feature

The receiver collar is IPX7 waterproof, meaning it can be submerged in water up to 1 meter for 30 minutes. This allows for training in wet conditions or if your dog enjoys swimming. The remote control is NOT waterproof and should be kept dry.

IPX7 Waterproof Collar Receiver



Image 5.1: A dog swimming while wearing the IPX7 waterproof ABBIDOT collar receiver, demonstrating its water resistance.

6. MAINTENANCE

Proper maintenance ensures the longevity and optimal performance of your training collar.

- **Keep Dry:** As per care instructions, keep the remote control dry at all times. While the receiver collar is waterproof, it is recommended to dry it thoroughly after exposure to water.
- **Clean Contact Points:** Regularly clean the contact points on the receiver collar to ensure good skin contact and prevent dirt buildup.
- **Inspect Collar:** Periodically check the collar strap for wear and tear. Replace if damaged.
- **Charge Regularly:** To maintain battery health, charge both devices regularly, even if not in frequent use.
- **Storage:** Store the device in a cool, dry place when not in use.

7. TROUBLESHOOTING

If you encounter issues with your ABBIDOT Dog Training Collar, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Collar not turning on	Low battery; Device not properly turned on.	Charge the receiver collar fully. Press and hold the power button until the indicator light illuminates.
Remote not turning on	Low battery; Device not properly turned on.	Charge the remote control fully. Press and hold the power button until the LCD screen activates.
No response from collar	Not paired; Out of range; Low battery; Improper contact.	Re-pair the devices (see Section 4.4). Move closer to the dog. Charge both devices. Ensure contact points touch the dog's skin.
Static stimulation feels weak or inconsistent	Poor contact; Incorrect contact point length; Low battery.	Ensure contact points are snug against the skin. Use longer contact points for thick-furred dogs. Charge the collar.
Shortened range	Environmental interference; Low battery.	Avoid areas with strong electromagnetic interference. Ensure both devices are fully charged.

8. SPECIFICATIONS

Feature	Detail
Brand	ABBIDOT
Model	Dog Training Collar
Training Modes	5 (Light, Tone, Vibration, General Stimulation, Boosted Stimulation)
Stimulation Levels	151 (1-16 General, 17-99 Boosted)
Waterproof Rating (Receiver)	IPX7
Range	Up to 3300 feet (1000 meters)
Recommended Dog Weight	10-130 lbs
Battery Type	Lithium Ion (included)
Charging Time	Approx. 2 hours (USB-C)
Remote Standby Time	Up to 10 days
Collar Work Time	Up to 16 days
Item Weight	11.3 ounces (320 Grams)
Product Dimensions	6 x 4.5 x 0.1 inches
Material	Plastic, Rubber
Color	Black
Manufacturer	Shenzhen Zheer Life Technology Co., Ltd.

9. WARRANTY AND SUPPORT

Your ABBIDOT Dog Training Collar is covered by a **1-year warranty** from the date of purchase, protecting against manufacturing defects.

For technical support, warranty claims, or any questions regarding your product, please contact ABBIDOT customer service through the retailer's platform or the official ABBIDOT website. Please have your purchase receipt and product model information ready when contacting support.

© 2024 ABBIDOT. All rights reserved.