

Orpat Potenza Plus 900 Watts

Orpat Commercial Juicer Mixer Grinder Potenza Plus 900W User Manual

Model: Potenza Plus 900 Watts

1. INTRODUCTION

Thank you for choosing the Orpat Commercial Juicer Mixer Grinder Potenza Plus 900W. This appliance is designed for efficient juicing, mixing, and grinding tasks in your kitchen. Please read this manual carefully before operating the appliance to ensure safe and optimal performance. Keep this manual for future reference.

2. IMPORTANT SAFETY INSTRUCTIONS

- Read all instructions before use.
- Ensure the voltage indicated on the appliance corresponds to your local mains voltage before connecting.
- Do not immerse the motor unit in water or any other liquid. Clean with a damp cloth only.
- Keep hands and utensils out of the jar during operation to prevent injury and damage to the appliance.
- Always ensure the lid is securely locked before operating the appliance.
- Unplug from the outlet when not in use, before assembling or disassembling parts, and before cleaning.
- Do not operate any appliance with a damaged cord or plug, or after the appliance malfunctions or has been damaged in any manner.
- This appliance is not intended for use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety.
- Avoid contact with moving parts.
- Do not use attachments not recommended or sold by the manufacturer.
- Do not use outdoors.
- Do not let the cord hang over the edge of a table or counter, or touch hot surfaces.

3. PRODUCT OVERVIEW AND COMPONENTS

The Orpat Potenza Plus 900W Juicer Mixer Grinder comes with a powerful motor unit and various attachments for different kitchen tasks.



Figure 3.1: Main unit with juicer, liquidizing, and grinding attachments.

Key Features:

- **900 Watts Powerful and Durable Motor:** Ensures efficient performance for tough ingredients.
- **Fine Hygienic Special Design S.S. Filter Net:** Maximizes juice extraction.
- **Optimum Speed Motor:** Designed for consistent results.
- **Power On Indicator:** For operational safety and convenience.
- **3 Speed Control Switch and Whip Switch:** Offers versatile control for different tasks.
- **Motor fitted with Double Ball Bearings:** Enhances motor life and durability.
- **Hygienic Stainless Steel Blades:** For effective processing and easy cleaning.
- **Transparent Unbreakable Food Grade Liquidizing Jar with Level Mark (1.5 Litre Capacity):** Ideal for blending

and liquidizing.

- **Hygienic Stainless Steel Grinding Jar (1 Litre Capacity):** Perfect for grinding spices and other dry ingredients.
- **Research Based Design of Cutter Spinner:** Synchronized with motor speed for maximum juice extraction.
- **Large Pulp Container:** For convenient disposal of pulp.



Figure 3.2: Highlighting the 900W motor and 22000 RPM for efficient processing.



Figure 3.3: Detail of the specially designed stainless steel filter for optimal juice extraction.

TOTAL WEIGHT: 6.2 kg



Figure 3.4: Overview of jar capacities and total product weight.

4. SETUP AND ASSEMBLY

Before first use, ensure all packaging materials are removed and components are clean. Assemble the appliance according to the task you wish to perform.

General Assembly Steps:

1. Place the motor unit on a stable, flat, and dry surface.
2. For juicing, attach the juicer assembly (filter, lid, and pulp container) securely onto the motor unit. Ensure it clicks into place.
3. For mixing or grinding, select the appropriate jar (liquidizing or grinding).
4. Place the selected jar onto the motor unit, aligning the grooves, and twist clockwise until it locks securely.
5. Ensure the jar lid is properly closed and locked before operation.

Your browser does not support the video tag.

Video 4.1: A short demonstration of unboxing and assembling the Orpat Juicer Mixer Grinder components, including the motor unit, juicer filter, and attaching the grinding jar. This video provides a visual guide for initial setup.

5. OPERATING INSTRUCTIONS

Always ensure the appliance is correctly assembled and securely locked before plugging it in and operating.

5.1 Juicing

1. Prepare fruits or vegetables by washing them and cutting them into pieces small enough to fit into the feeding chute. Remove any hard seeds or pits.
2. Ensure the juicer assembly is correctly fitted and locked onto the motor unit. Place a juice collecting container under the spout.
3. Plug in the appliance.
4. Turn the speed control switch to the desired speed (Low or High).
5. Gradually feed the prepared ingredients into the feeding chute using the food pusher. Do not force ingredients.
6. Once juicing is complete, turn the switch to 'OFF' and unplug the appliance.
7. Empty the pulp container as needed.

5.2 Mixing and Liquidizing

1. Attach the 1.5 Litre liquidizing jar to the motor unit and lock it.
2. Add ingredients to the jar. Do not exceed the maximum fill level indicated on the jar.
3. Securely close the lid.
4. Plug in the appliance.
5. Select the desired speed (Low, High) or use the 'Whip' function for short bursts.
6. Process until the desired consistency is achieved.
7. Turn the switch to 'OFF' and unplug the appliance before removing the jar.

5.3 Grinding

1. Attach the 1 Litre grinding jar to the motor unit and lock it.
2. Add dry ingredients (e.g., spices, coffee beans) to the jar. Do not overfill.
3. Securely close the lid.
4. Plug in the appliance.
5. Select the desired speed (Low, High) or use the 'Whip' function for short bursts to achieve fine grinding.
6. Process until the desired consistency is achieved.
7. Turn the switch to 'OFF' and unplug the appliance before removing the jar.

Your browser does not support the video tag.

Video 5.1: An overview of the Orpat Juicer Mixer Grinder's features and multi-functional performance, demonstrating its use for juicing, mixing, and grinding with various attachments. This video highlights the versatility and efficiency of the appliance in a kitchen setting.

6. MAINTENANCE AND CLEANING

Regular cleaning ensures hygiene and prolongs the life of your appliance. Always unplug the appliance before cleaning.

Cleaning Steps:

1. **Motor Unit:** Wipe the motor unit with a soft, damp cloth. Do not immerse it in water.
2. **Jars and Lids:** Wash the jars, lids, and blades with warm soapy water. Use a brush for thorough cleaning of blades and the juicer filter. Rinse thoroughly and dry immediately to prevent water spots or corrosion.
3. **Blades:** Handle blades with extreme care as they are sharp.
4. **Pulp Container:** Empty and wash the pulp container after each use.
5. Ensure all parts are completely dry before reassembling or storing.

7. TROUBLESHOOTING

If you encounter any issues, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Appliance does not start	Not plugged in; power outage; jar/juicer not locked correctly; thermal overload protection activated.	Check power connection; ensure jar/juicer is securely locked; allow motor to cool down if overheated.
Motor runs, but blades do not rotate	Jar not properly engaged with motor coupling; ingredients are jammed.	Re-seat the jar correctly; turn off, unplug, and clear any jammed ingredients.
Excessive noise or vibration	Uneven loading of ingredients; appliance not on a flat surface; worn out coupling.	Distribute ingredients evenly; place on a stable surface; contact customer support if coupling is worn.
Leaking from jar	Lid not properly sealed; rubber gasket missing or damaged; jar overfilled.	Ensure lid is securely closed; check and replace gasket if damaged; do not overfill jars.

If the problem persists after trying these solutions, please contact Orpat customer support.

8. SPECIFICATIONS

Feature	Specification
Brand	Orpat
Model	Potenza Plus
Colour	White
Maximum Power	900 Watts
Material	Stainless Steel (Blades, Grinding Jar)
Liquidizing Jar Capacity	1.5 Litres
Grinding Jar Capacity	1 Litre
Number of Speeds	3 (Low, High, Whip)

Feature	Specification
Product Dimensions (D x W x H)	48D x 27W x 37H Centimeters
Item Weight	6200 Grams (6.2 kg)
Power Source Type	Corded Electric
Included Components	Mixers (Motor unit, Juicer attachment, Liquidizing Jar, Grinding Jar)
Country of Origin	India

9. WARRANTY AND SUPPORT

Orpat products are manufactured with high-quality standards. For any warranty claims or technical support, please refer to the information below:

Manufacturer Information:

Ajanta LLP Orpat Industrial Estate, Rajkot Highway, Morbi – 363641. Gujarat, India
Phone: +91 - 02822 - 353012

Extended Warranty Plans:

Extended warranty plans may be available through third-party providers like Onsitego. Please check with your retailer for details on available plans.

- 1 Year Extended Warranty Plan by Onsitego
- 2 Year Extended Warranty Plan by Onsitego

For further assistance, please visit the official Orpat website or contact their customer service directly.