

- › [Logitech](#) /
- › [Logitech Signature Slim MK955 for Business Wireless Keyboard and Mouse Combo User Manual](#)

Logitech MK955

Logitech Signature Slim MK955 for Business Wireless Keyboard and Mouse Combo User Manual

Model: MK955 | Part Number: 920-012427

INTRODUCTION

This manual provides comprehensive instructions for setting up, operating, maintaining, and troubleshooting your Logitech Signature Slim MK955 for Business Wireless Keyboard and Mouse Combo. Please read this manual thoroughly before using your new device.



Image: The Logitech Signature Slim MK955 Keyboard and Mouse Combo, shown with its retail packaging.

SETUP

Follow these steps to set up your Logitech Signature Slim MK955 combo.

1. Battery Installation

The keyboard requires 2 AAA batteries and the mouse requires 1 AA battery (included). Ensure correct polarity when inserting batteries.

IN THE BOX



Keyboard: 134.8 x 433.8 x 23.1 mm
0.91 x 17.08 x 5.31 inches
Mouse: 118.7 x 66.2 x 42 mm
4.67 x 2.61 x 1.65 inches

Image: Contents of the Logitech Signature Slim MK955 box, including the keyboard, mouse, Logi Bolt receiver, and batteries.

2. Connectivity Options

Your combo offers two connection methods: Logi Bolt USB receiver or Bluetooth.

Using the Logi Bolt USB Receiver:

1. Locate the Logi Bolt USB receiver, typically found inside the mouse's battery compartment or within the product packaging.
2. Plug the Logi Bolt USB receiver into an available USB port on your computer.
3. Turn on the keyboard and mouse using their respective power switches. The devices should automatically connect.

SECURE WIRELESS CONNECTION



Image: A close-up view of the Logi Bolt USB receiver inserted into a laptop, positioned next to the Logitech mouse and keyboard, illustrating a secure wireless connection.

Using Bluetooth:

1. Turn on the keyboard and mouse.
2. Press and hold one of the Easy-Switch buttons (1, 2, or 3) on the keyboard or mouse for 3 seconds until the LED indicator blinks rapidly. This indicates pairing mode.
3. On your computer or device, open Bluetooth settings and select "Logitech MK955 Keyboard" or "Logitech MK955 Mouse" from the list of available devices to pair.
4. Repeat for the other device if connecting both via Bluetooth.

TIMESAVING SHORTCUTS

CUSTOMIZABLE THROUGH OPTIONS+ ⁽³⁾

Image: A close-up of the Logitech keyboard and mouse, highlighting the Easy-Switch buttons used for seamless multi-device pairing.

OPERATING INSTRUCTIONS

Keyboard Features:

- **Laptop-Style Typing:** Enjoy a comfortable and familiar typing experience with low-profile keys and a subtle scoop design.
- **Adjustable Tilt Legs:** Customize the typing angle for ergonomic comfort.
- **Customizable Function Keys:** Personalize F-keys and other shortcuts using the Logi Options+ software.
- **Easy-Switch Keys:** Quickly switch between up to three connected devices (computers, tablets, smartphones).
- **Quiet Typing:** Designed for minimal noise, ideal for shared workspaces.



Image: A detailed diagram illustrating the key features of the Logitech Signature Slim MK955 keyboard, including adjustable tilt legs, customizable function keys, Easy-Switch keys, LED indicator, low-profile keys, and number pad.

FAMILIAR, FLUID TYPING

LAPTOP-STYLE TYPING EXPERIENCE

Image: A user's hands typing on the Logitech Signature Slim MK955 keyboard, demonstrating the familiar and fluid typing experience.

Mouse Features:

- **SmartWheel Technology:** Switch between precise line-by-line scrolling and super-fast scrolling with a flick.
- **Contoured Shape:** Designed for a comfortable fit in your hand.
- **Customizable Buttons:** Assign custom functions to buttons using Logi Options+ software.
- **Silent Clicks:** Experience 90% less click noise compared to standard mice.
- **DPI Switch Button:** Adjust cursor speed for optimal control.

SUPER FAST SCROLLING



SMARTWHEEL TECHNOLOGY

Image: A hand operating the Logitech Signature Slim MK955 mouse, highlighting the SmartWheel for fast scrolling.



Fully compatible with Windows 11

Image: A detailed diagram outlining the features of the Logitech Signature Slim MK955 mouse, including silent clicks, DPI switch button, customizable function buttons, SmartWheel technology, Easy-Switch buttons, and contoured shape.

Logi Options+ Software:

Download and install the Logi Options+ software from the official Logitech website to unlock full customization options for your keyboard and mouse, including remapping keys, setting smart actions, and adjusting mouse sensitivity.

Your browser does not support the video tag.

Video: Official Logitech MK955 Product Video, showcasing key features and functionality.

MAINTENANCE

- **Cleaning:** Use a soft, lint-free cloth to wipe down the keyboard and mouse. For stubborn dirt, slightly dampen the cloth with water or a mild cleaning solution. Avoid harsh chemicals.
- **Battery Replacement:** Replace batteries when the low battery indicator illuminates. The keyboard uses 2 AAA batteries, and the mouse uses 1 AA battery.
- **Storage:** When not in use for extended periods, turn off the devices to conserve battery life. Store in a cool, dry place.

TROUBLESHOOTING

Connectivity Issues:

- **No Connection (Logi Bolt):**
 1. Ensure the Logi Bolt receiver is securely plugged into a working USB port.
 2. Verify the keyboard and mouse are powered on.
 3. Try plugging the receiver into a different USB port or a different computer to isolate the issue.
 4. Re-pair the devices using the Logi Options+ software if necessary.
- **No Connection (Bluetooth):**
 1. Ensure Bluetooth is enabled on your device.
 2. Place the keyboard/mouse in pairing mode (hold Easy-Switch button for 3 seconds).
 3. Remove any existing pairings for the device from your computer's Bluetooth settings and attempt to re-pair.
 4. Ensure your device's operating system is up to date.

Performance Issues:

- **Lagging/Unresponsive:**
 1. Check battery levels and replace if low.
 2. Reduce distance between devices and receiver/computer.
 3. Avoid sources of wireless interference (e.g., Wi-Fi routers, other wireless devices).
- **Keys Not Registering:**
 1. Clean around the affected keys to remove debris.
 2. Ensure the keyboard is fully charged or has fresh batteries.

Your browser does not support the video tag.

Video: Product Overview Video, demonstrating the features and setup of the Logitech Signature Slim MK955 combo.

SPECIFICATIONS

Brand	Logitech
Model Number	920-012427
Operating System Compatibility	Chrome OS, Linux, Windows 11 or later, Windows 10, macOS 10.15 or later
Connectivity Technology	Bluetooth, Logi Bolt USB Receiver
Power Source	Battery Powered (Keyboard: 2 AAA, Mouse: 1 AA)
Keyboard Dimensions (LxWxH)	17.71 x 5.9 x 2.4 inches
Item Weight	2.44 pounds
Color	Graphite

Special Features

Lightweight, Portable, Quiet Typing, SmartWheel, Easy-Switch

WARRANTY AND SUPPORT





For detailed warranty information and technical support, please visit the official Logitech support website:

www.logitech.com/support

You can also find additional resources and FAQs on the product support page for the Logitech Signature Slim MK955.

© 2024 Logitech. All rights reserved.

Related Documents - MK955

	<p>Logitech Signature Slim Combo MK955/MK950 for Business Setup Guide</p> <p>A comprehensive setup guide for the Logitech Signature Slim Combo MK955/MK950 for Business, detailing connection methods, keyboard and mouse functions, and system requirements.</p>
	<p>Logitech Signature Slim Combo MK955/MK950 for Business Setup Guide</p> <p>Learn how to set up and connect your Logitech Signature Slim Combo MK955/MK950 keyboard and mouse for business. This guide covers pairing via Logi Bolt receiver and Bluetooth, multi-device connectivity, and key features.</p>
	<p>Logitech Signature Slim Combo MK955/MK950 for Business Setup Guide</p> <p>Get started with your Logitech Signature Slim Combo MK955/MK950 for Business. This setup guide covers pairing options via Logi Bolt and Bluetooth®, multi-device connectivity, keyboard functions, system requirements, and technical specifications for a seamless business setup.</p>
	<p>Logitech MK950 Signature Slim Keyboard and Mouse Combo User Guide</p> <p>A comprehensive guide to setting up and using the Logitech MK950 Signature Slim Keyboard and Mouse Combo, covering Bluetooth and Logi Bolt pairing, software customization with Logitech Options+, and feature explanations.</p>



Logitech POP Icon Combo: Setup and Easy Switch Guide

A concise guide to setting up your Logitech POP Icon Combo keyboard and mouse using Bluetooth and the Logi App, including instructions for the Easy Switch feature.



[9 Best Practices for Modernizing Government Workspaces | Logitech](#)

Discover 9 essential best practices for modernizing government workspaces, enhancing productivity, collaboration, and public service delivery with Logitech solutions for the public sector.