



Manuals.plus /

› HSH /

› HSH LC080204 L-Shaped Computer Desk Instruction Manual

HSH LC080204

HSH LC080204 L-Shaped Computer Desk Instruction Manual

MODEL: LC080204

Brand: HSH

[Safety Information](#) [Product Features](#) [Parts List](#) [Assembly Instructions](#) [Specifications](#) [Care & Maintenance](#) [Warranty & Support](#)

1. SAFETY INFORMATION

WARNING:

- Always assemble the desk according to the provided instructions.
- Ensure the desk is properly anchored to the floor to prevent tipping.
- Be cautious when handling the desk due to its size and sharp edges to avoid injury.

2. PRODUCT FEATURES

The HSH L-Shaped Computer Desk is designed to provide a versatile and efficient workspace with ample storage. Its robust construction ensures durability, while its reversible design offers flexibility to fit various room layouts.

- **Large Working Space:** Features a generous 59.1"x 59.1" tabletop surface, ideal for multiple monitors, laptops, and other work or leisure activities.
- **Ample Storage Space:** Includes a long shelf and 6 drawers, with two large file drawers designed to hold letter, A4, or legal-size files.
- **Reversible and Space-Saving Design:** The L-shaped structure allows for corner placement, maximizing space utilization. The storage shelves can be arranged on either the left or right side to suit your preference.
- **Durable and Strong Bearing Capacity:** Constructed with high-quality MDF board and a heavy-duty metal frame, ensuring excellent durability and stability. The tabletop supports up to 150 Lbs.



Image: The HSH L-Shaped Computer Desk in a home office setting, demonstrating its large working surface and integrated storage solutions.



Image: A detailed view of the desk's drawers, highlighting the file storage capability for various document sizes.

3. PARTS LIST

3.1. Wooden Panels

- 1: Desktop Panel (x1)
- 2: Short Desktop Panel (x1)
- 3: Left Side Panel (x2)
- 4: Right Side Panel (x2)
- 5: Bottom Panel (x2)
- 6: Back Panel (x2)
- 7: Small Drawer Front (x4)
- 8: Large Drawer Front (x2)
- 9: Small Drawer Side (x4)

- 10:** Small Drawer Back (x4)
- 11:** Large Drawer Side (x2)
- 12:** Large Drawer Back (x2)
- 13:** Small Drawer Bottom (x4)
- 14:** Large Drawer Bottom (x2)
- 15:** Small Drawer Front Panel (x4)
- 16:** Large Drawer Front Panel (x2)

3.2. Metal Components

- 17:** Metal Frame (x1)
- 18:** Left Metal Leg (x1)
- 19:** Right Metal Leg (x1)
- 20:** Metal Tube (x1)
- 21:** Support Bar (x4)
- 22:** Metal Tube (x1)
- 23:** Shorter Metal Tube (x1)
- 24:** Longer Metal Tube (x1)
- 25:** Shorter Metal Tube (x1)
- 26:** Longer Metal Tube (x1)
- 27:** Support Bar (x1)
- 28:** Reinforcement Panel (x2)

3.3. Hardware

- A:** Cam Bolt ($\Phi 6 \times 44$) (x52)
- B:** Cam Lock ($\Phi 15 \times 9.5$) (x52)
- C:** Wood Dowel ($\Phi 8 \times 30$) (x24)
- D:** Long Bolt ($\Phi 7 \times 50$) (x10)
- E:** Short Bolt ($\Phi 6 \times 20$) (x10)
- F:** EVA Pad (x8)
- G:** Medium Bolt (M6*35) (x23)
- H:** Slide Screw ($\Phi 3 \times 12$) (x60)
- I:** Metal Bracket (x2)
- J:** Drawer Screw ($\Phi 3.5 \times 35$) (x24)
- K:** Handle (x6)
- M:** Handle Bolt (M4*18) (x12)
- N:** Allen Key (4mm) (x1)
- O:** Screwdriver (70*30*5mm) (x1)
- P:** Sticker (x8)
- L1:** Small Left Slide (x4)
- R1:** Small Right Slide (x4)
- L2:** Big Left Slide (x2)
- R2:** Big Right Slide (x2)

4. ASSEMBLY INSTRUCTIONS

Follow these steps carefully for proper assembly. Refer to the included hardware list for component identification.

4.1. How to Use a Cam Bolt & Cam Lock

1. Clockwise rotate the CAM BOLT until the shoulder is against the surface of the board.
2. Push a CAM LOCK into the board. The arrow in the CAM LOCK must point toward the hole in the edge of the board.
3. Insert the CAM BOLT into the CAM LOCK. Clockwise rotate to tighten the CAM LOCK.

4.2. Step-by-Step Assembly

1. Step 1: Prepare Side Panels

Attach slide screws (H) and cam bolts (A) to panels 3 and 4. Ensure wide openings face cam bolts.

2. Step 2: Assemble Cabinet Base

Connect panels 3 and 6 using wood dowels (C) and cam locks (B). Secure with reinforcement panel (28).

3. Step 3: Attach Outer Side Panels

Connect panel 5 to the assembled cabinet using wood dowels (C) and long bolts (D). Secure with EVA pads (F).

4. Step 4: Assemble Metal Legs

Connect left metal leg (18) and right metal leg (19) using medium bolts (G) and Allen key (N). Ensure flat sides face outward.

5. Step 5: Attach Metal Tubes

Connect metal tubes (20, 22, 23, 24) to the metal legs using short bolts (E) and medium bolts (G). Ensure flat sides face outward.

6. Step 6: Secure Metal Frame

Attach metal brackets (I) to panel 3 using slide screws (H). Connect the metal frame to the cabinet sides using long bolts (D).

7. Step 7: Install Support Bar

Attach support bar (26) to the metal frame using medium bolts (G). Ensure the hole is close to the short metal tube (23) and faces the right side panel (4).

8. Step 8: Install Shorter Support Bar

Attach shorter support bar (25) to the metal frame using medium bolts (G). Ensure the two holes face upward.

9. Step 9: Prepare Desktop Panels

Attach cam bolts (A) to desktop panel (1) and short desktop panel (2). Rotate clockwise until the shoulder is against the surface.

10. Step 10: Attach Desktop Panels

Place desktop panels (1 and 2) onto the assembled frame. Secure using cam locks (B) and wood dowels (C). Adjust to align properly.

11. Step 11: Assemble Small Drawers

Connect small drawer sides (9, 10, 13) and small drawer back (11) using drawer screws (J). Insert small drawer bottom (15). Repeat for all 4 small drawers.

12. Step 12: Assemble Large Drawers

Connect large drawer sides (11, 12, 14) and large drawer back (12) using drawer screws (J). Insert large drawer bottom (16). Repeat for both large drawers.

13. Step 13: Attach Drawer Fronts

Attach handles (K) to small drawer fronts (7) and large drawer fronts (8) using handle bolts (M).

14. Step 14: Install Drawer Slides

Attach small left/right slides (L1/R1) to small drawers and big left/right slides (L2/R2) to large drawers using slide screws (H).

15. Step 15: Insert Drawers

Carefully insert all assembled drawers into their respective slots in the desk cabinets. Ensure they slide smoothly.

16. Step 16: Apply Stickers

Cover any visible bolt holes with the provided stickers (P) for a clean finish.

Video: Official HSH Furniture assembly guide for the L-Shaped Desk, demonstrating the full assembly process.

Video: HSH Furniture's overview of the L-Shaped Desk with drawers, highlighting its features and design.

5. SPECIFICATIONS

Attribute	Value
Brand	HSH
Model Number	LC080204
Shape	L-Shape
Product Dimensions	19.7"D x 59.06"W x 30"H
Color	Rustic Brown
Style	Country Rustic
Top Material Type	Engineered Wood
Frame Material Type	Metal
Special Feature	Reversible
Maximum Weight Recommendation	150 Pounds
Number of Drawers	6
Number Of Shelves	1
Required Assembly	Yes

6. CARE & MAINTENANCE

To maintain the quality and appearance of your HSH L-Shaped Computer Desk, please follow these care instructions:

- Wipe with a dry cloth to remove dust and spills.
- Avoid using harsh chemicals or abrasive cleaners, as these may damage the finish.
- Keep the desk away from direct sunlight and extreme temperature changes to prevent warping or discoloration.

7. TROUBLESHOOTING

If you encounter any issues during assembly or use, please review the assembly steps carefully. For persistent problems, refer to the warranty and support information below.

8. WARRANTY & SUPPORT

HSH is committed to providing high-quality products and excellent customer service.

- **30-Day Free Return:** If you are not satisfied with your purchase, you may return it within 30 days for a free return.
- **12-Month Quality Warranty:** Your desk is covered by a 12-month quality warranty against manufacturing defects.
- **Customer Support:** For any questions, missing parts, or warranty claims, please contact HSH Furniture directly. Contact information can typically be found on the product packaging or through your retailer.